

amateur radio

JOURNAL OF THE WIRELESS INSTITUTE OF AUSTRALIA



VOL. 48, No. 2

FEBRUARY 1980


FEATURED IN THIS ISSUE:

- ★ 1979 RD CONTEST RESULTS
- ★ Review: KENWOOD R1000 GENERAL COVERAGE RECEIVER
- ★ Review: YAESU FT207R SYNTHESISED 2m HAND-HELD
- ★ THE WEE WILLIE WONDER ANTENNA COUPLER
- ★ AN 80 METRE VERTICAL

THIS IS A YAESU PRICE TICKET.

Notice the price?

There isn't one! Or if there is, it represents only the **maximum** you will have to pay. If anyone advertises, in Australia, a lower price than we show, we will guarantee to beat it! Our list prices are very competitive as they are – but we will guarantee to lower them if our prices are undercut!



Please take these prices with a grain of salt . . .



**WHY TAKE CHANCES?
BUY YOUR YAESU GEAR
FROM THE AUTHORISED
AUSTRALIAN YAESU
AGENTS!**

HF TRANSCEIVERS:

- FT-901D: Superb all-mode HF transceiver with digital readout. 6146B finals; 180 watts. The ham's dream! CatD-2854 **\$1266.00**
 FT-101Z: Up-graded version of the famous FT-101E. Suits the FT-901 accessories, same smart styling. CatD-2862 **\$849.00**
 FT-7B: Mobile or base, all HF bands. AM/SSB/CW. 12 volt operation. Easy controls for safer mobiling, too. CatD-2868 **\$649.00**

LINEAR AMPLIFIERS:

- FL-2100B: 1.2kW of muscle (drive it at 400 and it's coasting!) Tunes all HF bands; 240 volt operated. CatD-2646 **\$599.00**

VHF TRANSCEIVERS:

- FT-625R: The new all mode 6m rig for DX chasers. CatD-2886 **\$795.00**
 FT-207R: The 21st century microprocessor-controlled hand held for 2 metre operation. Complete with NiCads. CatD-2888 **\$358.00**
 CPU-2500RK: 800 channels from 144-148; 25 watts. CatD-2889 **\$549.00**
 FT-227RB: 2 metre mobile, dual power out, built-in memorizer. CatD-2891 **\$399.00**

RECEIVERS:

- FRG-7: Probably the most popular receiver in the world! 0.5 to 30MHz. famous Wedley Loop circuit. Mains or 12V. CatD-2850 **\$395.00**
 FRG-7000: Up-graded FRG-7, with digital readout, dual clocks & timer, etc. A superb receiver for the serious listener. CatD-2848 **\$625.00**

ACCESSORIES:

- FC-901 Antenna tuner: Suits most transceivers; tunes into virtually any load (almost a wet piece of string) CatD-2855 **\$265.00**
 DC/DC Converter: Suits both the 901 & 101Z. CatD-2856 **\$75.00**
 MEMORY UNIT: For both the 901 & 101Z. CatD-2858 **\$149.50**
 YE7A Mic: 500 ohms imp; with p.t.t. Suits most transceivers. CatD-2863 **\$14.50**
 Cooling Fan: For the 101Z (or replacement on 901) CatD-2865 **\$39.00**

TEST EQUIPMENT:

- YC-500S Digital Frequency Counter: 1ppm accuracy, 500MHz. CatD-2892 **\$475.00**

WE OFFER EASY TERMS THROUGH BFC FINANCE *

For us to better any price, simply show us the advertisement from an Australian company. After checking that they have stocks available at that price, we will sell it for a lower price. Offer open while stocks last.

DICK SMITH ELECTRONICS

NSW 125 York Street,
141 Horse Highway,
182 Pacific Highway,
38 Grosvenor Street,
263 Keira Street,

STONEY Phone 230 3377
CHURCHILL Phone 642 8927
GORE HILL Phone 429 5311
PARRAMATTA Phone 683 1133

WOLLONGONG Phone 29 3808

ACT 96-98 Clarendon Street,
399 Leachville Street,
VIC 650 Bridge Road,
QLD 168 Logan Road,
SA 203 Wright Street,
WA 414 Willson Street,

PERTH Phone 32 4944
MELBOURNE Phone 47 8434
RICHMOND Phone 429 8134
BURRANDA Phone 383 8233
ADLAIDE Phone 212 1962
BRISBANE Phone 328 6944

bankcard
welcome here

SHOPS OPEN 9AM to 5.30PM
(Saturday: 9am till 12 noon)
(Brisbane: Half hour earlier)
ANY TERMS OFFERED ARE TO
APPROVED APPLICANTS ONLY
RE-SELLERS OF DICK SMITH
PRODUCTS IN MOST AREAS OF AUSTRALIA.



EXCEPT WHERE NOTED, ALL ITEMS SHOWN IN STOCK AT PRICES GIVEN AT TIME OF GOING TO PRESS.

MAIL ORDER CENTRE: PO Box 321, NORTH RYDE NSW 2113. Ph 888 3200. PACK & POST EXTRA.



amateur radio

Published monthly as its official journal by the Wireless Institute of Australia, founded 1910.

FEBRUARY 1980

VOL. 48, No. 2

PRICE: \$1.20

Registered Office:
3/105 Hawthorn Road,
Caulfield North 3161.

MANAGING EDITOR:
BRUCE BATHOLDS* VK3UV

PRODUCTION MANAGER:
MARK STEPHENSON* VK3JOY

TECHNICAL EDITORS:
BILL RICE* VK3ABP
EVAN JARMAN* VK3ANI
RON COOK* VK3AFW
GIL SONES* VK3AUI

CONTRIBUTING EDITORS:
BOB ARNOLD VK3ZBB
MIKE BAZLEY VK8HD
ROD CHAMPNESS VK3UG
ROY HARTKOPF* VK3ACH
RON FISHER VK3OM
ERIC JAMIESON VK8LP
PETER MILL VK3ZPP
LEN POYNTER* VK3ZGP
WILL VERRALL VK3WV
GARRY WATKINS VK2DEW

DRAFTING:
NEIL OSBORNE* VK3YEI

BUSINESS MANAGER:
PETER DODD VK3CIF

*Member of Publications Committee

Enquiries and material to:
The Editor,
PO Box 150, Toorak, Vic. 3142

Copy is required by the first of each month. Acknowledgement may not be made unless specially requested. All important items should be sent by certified mail. The editor reserves the right to edit all material, including Letters to the Editor and Hamads, and reserves the right to refuse acceptance of any material, without specifying a reason.

Advertising: Material should be sent direct to P.O. Box 150, Toorak, Vic., 3142, by the 25th of the second month preceding publication. Photos: (OS) 24 6525—Hamads should be sent direct to P.O. Box 150, Toorak, Vic., 3142, by the 1st of the month preceding publication.

Trade Practices Act: It is impossible for us to ensure that advertisements submitted for publication comply with the Trade Practices Act 1974. Therefore advertisers and advertising agents will appreciate the absolute need for themselves to ensure that the provisions of the Act are complied with strictly. Readers are reminded that, when buying, obtaining or receiving goods from overseas including goods listed in advertisements by overseas organisations in this journal, Customs import duties and Sales Tax may be levied on the goods at the time of importation. These amounts, if any, are payable by the purchaser unless the terms of sale state otherwise and the seller has made specific reference to this effect in his quotation to the buyer or unless other prior arrangements are in force between the buyer and the seller.

Typesetting: MUELLER INDUSTRIES
1a Lovanswell Road, Moorabbin, 3189
Tel.: 553 0292

Printers: EQUITY PRESS PTY. LTD.
50-52 Lillingston Street, Collingwood, 3068
Tel.: 41 5064, 41 5055

CONTENTS

TECHNICAL

- An 80 metre Vertical
- Calculation of Great Circle Distances
- Simple Antenna Coupler

- 16 Amateur Satellites
- 14 Around the Trade
- 14 Awards Column
- 6 Contests — Commonwealth Contest 1980
- 40 Divisional Notes
- 41 Hamads
- 34 Ionospheric Predictions
- 39 International News
- 39 Intruder Watch
- 33 Letters to the Editor
- 42 Obituary
- 4, 19, 26, 32, 39 QSP
- 30 VHF-UHF — An Expanding World
- 8 WIA NEWS
- 36 You and DX

GENERAL

- C.A.R.E. (Community Amateur Radio Events)
- 17 RD Contest Results 1979
- 26 Hooray (for none of the above)
- 20 NOVICE NOTES — Beware the SWR Meter
- 29 Reviews —
- 11 The FT207R 2m Transceiver
- 8 The R1000 General Coverage Receiver
- 20 Western Zone Convention

DEPARTMENTS

ADVERTISERS' INDEX

Cover Photo

AMATEUR RADIO ASSISTS RUNNERS

The "Sun" City to Surf Race held in Sydney during August 1979 attracted some 21,000 runners. Amateur Radio provided communications consisting of a radio link in the lead vehicle, numerous check-points along the route and portable man-pack links. Eric Van de Weyer VK2ZUR seen here relaying a message for a race official at Bondi Beach, the race finish.

2 metres FM via a repeater was used as the primary system with a HF network

back-up. The lead vehicle relayed up to the minute positions of the front runners. Numerous fixed check-points provided information for medical assistance to exhausted runners. This is the second year that Amateur Radio has provided communications and it has proved to be a worthwhile contribution, bringing to the attention of the public what Amateur Radio can do.

Photo: VK2ATU

WIRELESS INSTITUTE OF AUSTRALIA

Federal President: Dr. D. A. Wardlaw VK3ADW

Federal Council:

VK1 Mr. R. G. Henderson VK1RH

VK2 Mr. T. I. Mills VK2ZTM

VK3 Mr. G. A. G. Williams VK3ZXW

VK4 Mr. A. R. F. McDonald VK4TE

VK5 Mr. C. J. Hurst VK5HI

VK6 Mr. N. R. Penfold VK6NE

VK7 Mr. R. K. Emmett VK7KK

Staff: Mr. P. B. Dodd VK3CIF, Secretary.

Part-time: Col. C. W. Perry, Mrs. J. M. Seddon and Mr. Mark Stephenson (AR Production).

Executive Office: 3/105 Hawthorn Rd., Cessfield

North. Vic. 3161. Ph. (03) 528 5982.

Divisional Information (all broadcasts are on Sundays unless otherwise stated).

ACT:

President — Mr. A. Davis VK1DA

Secretary — Mr. F. Robertson-Mudie VK1NAV

Broadcasts — 3570 kHz and 2m Ch. 6 (or 7): 10.00Z.

NSW:

President — Mr. F. S. Parker VK2NFF

Secretary — Mr. T. I. Mills VK2ZTM

Broadcasts — 1825, 3395, 7145 kHz, 28.32, 52.1, 52.525, 144.1, 146.8, 148.4, Rptr. Ch. 3 — Gosford, Ch. 4 — Lismore, Ch. 5 — Wollongong, Ch. 8 — Dural 11.00h local (Evening 0930Z). Relays on 160, 80 and 10m, VHF and Repr. Ch. 3, Ch. 5, Ch. 8, and Hunter Branch, Mondays 0930Z on 3595 kHz, 10m, and Ch. 3 and 8. RTTY Sunday 0930Z 7045, 14090 kHz, Ch. 52, 0930Z 3545 kHz, Ch. 82.

VIC:

President — Mr. E. J. Bugbee VK3ZZN

Secretary — Mr. G. F. Ashton VK3YFA

Broadcasts — 1840, 3600, 7136 kHz — 83.032 AM, 144.2 USB and 2m Ch. 2 (5) repeater: 10.30 local time.

Gen. Mtg. — 2nd Wed., 20.00.

QLD:

President — Mr. A. J. Anzore VK4QA

Secretary — Mr. W. L. Gleilis VK4AG

Broadcasts — 1825, 3580, 7145, 14342, 21175, 29400,

kHz; 2m (Ch. 42, 46): 09.00 EST.

Gen. Mtg. — 3rd Friday.

SA:

President — Mr. I. J. Hunt VK5GX

Secretary — Mr. W. M. Wardrop VK5AWM

Broadcasts — 1825, 3650, 7095, 14175 kHz; 28.5 and 53.1 MHz, 2m (Ch. 8): 09.00 S.A.T.

Gen. Mtg. — 4th Tuesday, 10.30.

WA:

President — Mr. Ross Greenaway VK6DA

Secretary — Mr. Peter Savage VK6HCP

Broadcasts — 3550, 7075, 14100, 14175 kHz, 28.485, 52.290 MHz, 2 molar Ch. 2 Perth, Ch. 6 Wagin. Time 0130Z.

Gen. Mtg. — 3rd Tuesday.

TAB:

President — Mr. I. Nicholls VK7ZZ

Secretary — Mr. P. T. Blake, VK7ZPS

Broadcasts — 7130 (AM) kHz with relays on 2m Ch. 2 (5), Ch. 8 (H), Ch. 3 (HW), 06.30 EST.

NT:

President — Mr. T. A. Hine VK8NTA

Vice-Pres. — Barry Burns VK8DI

Secretary — Robert Millikan VK8NRM

Broadcasts — Relay of VK6WV on 3.555 MHz and on 146.5 MHz at 2230Z. Slow Morse transmission by VK8HA on 3.555 MHz at 1000Z almost every day.

Postal Information:

VK1 — P.O. Box 46, Canberra, 2600.

VK2 — 14 Aitchison St., Crows Nest, 2065 (Ph. (02)

43 5795 Tues & Thurs (10.00-14.00).

P.O. Box 123, St. Leonards, NSW 2065.

VK3 — 412 Brunswick St., Fitzroy, 3065 (Ph. (03) 41 3535 Weekdays 10.00-15.00h).

VK4 — G.P.O. Box 1234, Adelaide, 5001 — HQ at

West Thebarton Rd., Thebarton.

VK5 — G.P.O. Box 11052, Perth, 6001.

VK7 — P.O. Box 1013, Launceston, 7250.

VK8 — (Incl. with VK5), Darwin AR Club, P.O. Box 37317, Winnellie, N.T., 5760.

Slow Morse transmissions — most week-day evenings about 09.30Z onwards around 3550 kHz.

VK QSL BUREAUX

The following is the official list of VK QSL Bureaux, all are inwards and outwards unless otherwise stated.

VK1 — QSL Officer, G.P.O. Box 46, Canberra, A.C.T. 2600.

VK2 — QSL Bureau, G.F. Hunter Branch, P.O. Taralga, N.S.W. 2284.

VK3 — Inwards QSL Bureau, Mr. E. Trebilcock, 340 Gillies Street, Thornbury, Vic. 3071.

VK3 — Outwards QSL Bureau, Mr. R. R. Prowse, 83 Brewer Road, Bentleigh, Vic. 3204.

VK4 — QSL Officer, G.P.O. Box 638, Brisbane, Qld., 4001.

VK5 — QSL Bureau, Mr. Ray Dobson VK8DI, 16 Howden Road, Fulham, S.A. 5024.

VK6 — QSL Bureau, Mr. J. Rumble VK6RU, G.P.O. Box F318, Perth, W.A. 6001.

VK7 — QSL Bureau, G.P.O. Box 371D, Hobart, Tas. 7001.

VK8 — QSL Bureau, G.F. VK8HA, P.O. Box 1418, Darwin, N.T. 5784.

VK8, 9 — Federal QSL Bureau, Mr. N. R. Penfold VK8NE, 588 Hunniss Rd., Woodlands, W.A. 6018.

QSP —

WARC 79 IN RETROSPECT

After all those years of preparation it is now time to look back on the results of WARC 79.

Results that have given the amateur service three new high frequency bands and access to many more bands by the amateur satellite service.

These results did not just happen, they were the result of a co-ordinated and concerted effort.

After the 1959 conference, John Moyle made a few very pertinent comments in his article in AR of March 1960 about the future of amateur radio in its relationship with and preparation for ITU conferences. Those lessons of 1959 were well learnt.

Firstly, our WARC 79 ground work preparation started many years before the conference with the development of an international amateur radio position formulated by the representatives of amateur radio societies in each of the three ITU regions.

This position, having been refined, was then presented to many administrations thus indicating a consistent amateur requirement. There was also an effective international organisation providing the back-up for national societies.

In Australia there was amateur participation from the very beginning of the Australian Government preparation for WARC 79. The importance and value of membership of the national delegation cannot be over-emphasised.

In view of the complexity of the WARC agenda the ability to have two amateur representatives on the Australian delegation was a godsend; particularly as there were many simultaneous working group meetings discussing amateur matters.

It was in these working group meetings that the decisions were made and delegates had the opportunity of putting their cases in order to influence these decisions.

Every stage in the WIA preparation for WARC 79 on behalf of Australian amateurs was vitally essential: None could have been bypassed —

- The preliminary preparation;
- The complete participation in the Australian preparatory group;
- The attendance at preliminary ITU meetings particularly the special preparatory meetings of the CCIR culminating in the acceptance of two members on the Australian delegation.

Notwithstanding the heavy cost in time and money, all this has proved to have been well worthwhile in results obtained.

**D. A. WARDLAW,
Federal President.**

WIA NEWS

6 METRE BAND

The text of the latest letter from the P. and T. Department reads: "Reference is made to your letter of the 12 October and 7 November 1979 concerning use of the 50-52 MHz band in Australia by the Amateur Service.

"The use of this portion of an Australian Television band outside of normal viewing hours is presently studied following the recent decisions made at the World Administrative Radio Conference.

"It is therefore considered that the appropriate time for the discussions you have requested will be after clear guidelines are established".

This question is being pursued as urgently as possible, especially as Melbourne's TV Channel 0 will move to Channel 10 near the end of January.

INTRUDER WATCH

Alf Chandler VK3LC, the Federal Intruder Watch Co-ordinator, having relinquished this post at the end of 1979, has handed over to Graham Fuller VK3NXX and this has been confirmed. Graham's address is P.O. Box 156, Healesville, Vic. 3777.

OFFICE

As shown in January AR the Executive office news address was notified. The telephone number is (03) 598 5962. The postal address is unchanged.

1980 FEDERAL CONVENTION AGENDA ITEMS

Item 80.121 from VK5 reads:

"That the P. and T. Department be requested to include on the 'application for an amateur station licence' the right to suppress publication of the licensee's name and address from the Australian Call Book".

Item 80.122 received from VK2 reads:

"That the WIA makes representations to the Department that the authorised maximum FM deviation on the 29 MHz band be increased from ± 3 kHz to ± 7.5 kHz".

Item 80.091, also from VK2, reads:

"That higher operating requirements for new HF bands be discussed".

The Executive will also be introducing several Agenda Items mainly of a procedural nature to permit discussion, and arising, on WARC 79, IARU and continuing action from previous conventions. The 1980 Federal Convention (the 44th) will be held in Melbourne (Brighton Savoy Hotel) from 25th to 27th April 1980. Agenda Items should be sent to your Division as quickly as possible so that they can be published in AR beforehand to allow members to make comments on them to their Divisions.

AR

The print run for AR reached 8000 for the first time. A WIA NEWS Special, reporting on WARC 79, was issued as an insert into January AR.

WARC 79 DONATIONS

The accounts for 1979 show that donations towards the expenses of WARC 79 received in that year from WIA members totalled \$5049 and from non-members (including AR advertisers) \$4330. As will have been noted from the Federal accounts (see AR July, page 30) the amount brought forward, including investments which have since been encashed, was \$13,955. The magnificent response for funds means that the expenses of this very important costly representation was just about covered. The Executive wishes to acknowledge the receipt with grateful thanks of further donations from members —

WIA (FEDERAL) DIRECTORY

MEMBERS OF EXECUTIVE

Dr. D. A. Wardlaw VK3ADW, Federal President.
Mr. P. A. Wolfenden VK3ZPA, Exec. Vice-Chairman.
Mr. K. C. Seddon VK3ACS, Member.
Mr. H. L. Hepburn VK3AFQ, Member.
Lt-Col. J. McL. Bennett VK3ZA, Member.
Mr. C. D. H. Scott VK3BNG, Hon. Treas.
Secretary: Peter B. Dodd VK3CIF.
Amateur Radio: Mark Stephenson VK3NOY

IARU LIAISON OFFICER AND
IMMEDIATE PAST FEDERAL PRESIDENT
Mr. M. J. Owen VK3K1.

INTRUDER WATCH CO-ORDINATOR
Mr. G. J. Fuller VK3NXX

FEDERAL REPEATER SUB-COMMITTEE

Mr. K. C. Seddon VK3ACS, Chairman.
Mr. J. J. L. Martin VK3ZJC.
Mr. P. B. Mili VK3ZFP.

MANAGING EDITOR AND
CHAIRMAN OF PUBLICATIONS COMMITTEE
Mr. B. Balthus VK3UV.

FEDERAL BROADCAST TAPE CO-ORDINATORS:

Mr. R. Fisher VK3COM.
Mr. W. Roper VK3ARZ.

FEDERAL EDUCATION CO-ORDINATOR

Mr. G. F. Scott VK3ZLR.

FEDERAL HISTORIAN

Mr. G. M. Hull VK3ZS.

FEDERAL CONTESTS MANAGER

Mr. W. A. Watkins VK2DEW

FEDERAL AWARDS MANAGER

Mr. D. Verrall VK5WV.

FEDERAL VHF/UHF ADVISORY COMMITTEE

Mr. K. G. Malcolm VK3ZYK, Chairman.
Mr. P. A. Wolfenden VK3ZPA.
Mr. J. W. Cowan VK3BGH.
Mr. L. James VK3BKF.
Mr. J. J. L. Martin VK3ZJC.
Mr. K. L. Phillips VK3AUQ.
Mr. W. M. Rice VK3ABP.

FEDERAL RTTY COMMITTEE

Mr. H. P. Mulligan VK2ABH, Chairman.
Mr. J. J. Lupton VK2BVJ.
Mr. R. E. Taylor VK2AOE.

PROJECT ASERT COMMITTEE

Mr. R. C. Arnold VK3ZBB, Chairman.
Mr. P. A. Wolfenden, VK3ZPA/7NB.
Mr. K. G. McCracken VK2CAX.
Mr. L. James VK3BKF.
Mr. G. C. Brown VK3YGB.

AMATEUR SATELLITES

Mr. R. C. Arnold VK3ZBB.

FEDERAL WICEN CO-ORDINATOR

Mr. R. G. Henderson VK1RRI.

VK/ZL/CO CONTEST MANAGER (VK)

Mr. N. R. Penfold VK6NE.

FEDERAL VIDEO TAPE CO-ORDINATOR

Mr. J. F. Ingham VK5KG.

FEDERAL COUNCILLORS

Please see main Directory.

ALTERNATE FEDERAL COUNCILLORS

VK1 — Mr. A. Davis VK1DA.
VK2 — Mr. P. B. Card VK2ZBX.
VK3 — Mr. A. R. Noble VK3BBM.
VK4 — Mr. D. T. Laurie VK4DT.
VK5 — Mr. C. J. Hurst VK5H1.
VK6 — Mr. P. J. Savage VK6NCP.
VK7 — Mr. P. D. Frith VK7PF.

LIST No. 10

	\$
Hornsby & Dist. ARC	125.00
VK5WO	25.00
Darwin ARC (VK8DA)	50.00
plus —	
VK8NTA	10.00
VK8DI	10.00
VK8NRM	10.00
VK8ZJM	10.00
VK8JW	10.00
Brisbane DX Club	20.00
VK3SO	7.00
VK4PS	10.00
VK4NFG	5.00
VK2AFU	10.00
VK6YD	10.00
L60132	2.00
VK2AZF	8.00
VK6ZGY	1.50
VK6WV	2.20
VK3BFQ	10.00

QSP

JANUARY AR

In the hiatus caused by holidays the quantity received of the January issue was a little short unfortunately. A few people near the end of the labels missed out in the mailing. The missing copies will be sent out as soon as possible after the printers return from the annual shut-down. ■

SIMPLE ANTENNA COUPLER

M. N. O'Burtill VK3WW
3 Maxwell Street, Lallor

A simple and effective antenna coupling unit for the novice and low power operator.

Like most operators I like to explore new fields and of necessity have to adapt equipment to particular needs. In this case it was portable operation from my caravan using an FT7 with a helical antenna and a Marconi 300 ohm ribbon antenna.

I soon decided that an aerial coupling unit was needed. The design, apart from electrical considerations, demanded that the unit be physically small, easy to tune and calibrate and be inexpensive. As the FT7 is a lower power rig, small tuning capacitors could be used.

I chose the Roblan single gang broadcast tuning capacitor which retails for about \$5 each. I had on hand a Toroid core, which was red and marked G 29SW478 U142. This core measures 20 mm outside diameter, 13 mm inside diameter and 6 mm deep. I think any toroid of about this size which is capable of working in the range 3 to 30 megahertz would be suitable. The Neosid type part No. 28-023-34 should be suitable also.

Winding the coil on a small toroid can be difficult, particularly when it comes to making taps every 3 turns. My method in this case was to wind on 3 turns of 20 gauge wire and leave a half inch lead on each end. I then removed this winding and straightened it out, next I cut 9 other pieces of wire of exactly the same length. Clean the enamel for half an inch on each end of each wire and carefully tin each end. Now wind 3 turns with the half inch ends pointing across the toroid. Wind another 3 turns and lightly solder one end of the first coil to the start of the second coil, continue like this until you have 30 turns wound round the toroid. Spread or compress the turns so that the coil is fairly evenly spaced around the toroid.

Now starting at the first tap, unsolder the join and twist the half inch ends together to make a good mechanical join and then resolder. Repeat this process at each tap point and leave the two ends of the coil free.

Carefully solder each tap point to the ten position switch. You will find that this method holds the coil quiet rigidly and no further mounting is required. The earth end of the coil is connected to a convenient chassis point using as short a lead as possible. The tuning capacitors are in series with the antenna and therefore are at RF potential. It is essential that they

be completely insulated from the chassis and that insulated knobs be used. A scrap of perspex sheet is a good insulator in this case. I mounted the capacitors on a piece of perspex then laid another piece under this and bolted the lot to the chassis. Of course the holes in the front plate through which the capacitor tuning shafts pass must be large enough to avoid the possibility of the shafts touching the metal plate. Likewise do not mount the capacitors too close to the front plate, the shaft is long enough to allow this.

TUNING UP

From the circuit, Fig. 1, you will note that I have included a switch to allow direct feed. This is handy for testing the effectiveness of the aerial coupling unit. Hook up the rig, SWR meter and aerial coupling unit as in Fig. 2 and tune in the signal with the aerial coupling unit switched out (direct feed). Note the S metre reading and switch the coupling unit in. Set C1 and C2 to maximum capacity and L1 to maximum inductance.




FIG. 1: Circuit diagram C1 and C2 Roblan 10-415 pF single gang. S1-10 position rotary switch. S2-DPT switch. L1 — 30 turns tapped every 3 turns on ferrite toroid, Neosid Part No. 28-023-34 or similar.






FIG. 2: Block diagram of coupler in use

Switch the taps on L1 and see if you get an increase in received signal. Now tune C1 and C2 alternately to peak the signal and note the settings of L1, C1 and C2. Switch the coupler out and apply power from the transmitter and note the SWR reading. Of course you should tune clear of the received signal a few kilohertz so that you don't cause interference. Now switch the coupler back into circuit and note the SWR reading.

At this stage I should explain that you don't always get a really good indication



The completed unit



Inside view

on received signals. If the SWR is too high or not improved from direct feed, switch the coil one tap each side of its present setting. What you are looking for is a drop in reflected power and an increase in forward power. A twin meter bridge is very useful in this situation. The meter indications are quite dramatic and show clearly when the correct tap is found. After this, alternately adjust C1 and C2 to obtain maximum forward and minimum reflected power. You should be able to achieve virtually one to one SWR on any reasonable antenna.

Once you have found the correct settings for an antenna on one band make a note of them, as they will be a good starting point for that band on any other antenna.

WHAT ABOUT HIGHER POWER?

Yes this circuit will work with higher powered rigs. Larger capacitors must be used, that is ones with greater plate spacing, and to avoid excessive heat loss a larger toroid is recommended. I am indebted to Charlie VK3BIT for bringing this circuit to my notice. It really works well, is easy and cheap to build and with low power rigs can be quite a small size which will fit in anywhere. ■



CALL SCALAR



MELBOURNE (03) 725 9677

SYDNEY (02) 570 1788

BRISBANE (07) 52 2594

OR CONTACT YOUR HAM GEAR RETAILER

SC22DX 5 Band Vertical
SCOOR Series; HF Mobile Resonators
Quad Kits • SC33DX; 3 Band Beam
Mobile HF Helicals • W2AU Baluns
Reyco Antenna Coils • Strain Insulators
UHF & 2 Metre Gain and Unity Whips, Beams
Gain Colinear Base Antennas • Magnabase

FRANK WELSH
MIKE KILPATRICK
RON SMITH
BRIAN ROBINSON

VK3BPV
VK2NMO
VK2DCK
VK4HQG

**Professionally Designed
with Amateurs in Mind.**

SCALAR GROUP

20 SHELLEY AVENUE, KILSYTH, VICTORIA. 3137.

20 THE STRAND, PENSHURST, NEW SOUTH WALES, 2222.

969 ANN STREET, FORTITUDE VALLEY, QUEENSLAND. 4006.

EQUIPMENT REVIEW:

THE KENWOOD R1000 GENERAL COVERAGE RECEIVER

Ron Fisher VK3OM

Trfo Kenwood have a long history in the manufacture of general coverage receivers. Many hundreds of 9R590/DE and DS's are still in use. The later R300 series did not reach the popularity of the earlier receivers. It seems now that Kenwood have produced a receiver that could lead the field for some time to come.

The R1000 is a fully solid state general coverage communications receiver with all required facilities but at the same time offering simple operation. It is obviously aimed at short wave listeners and at the growing market of people interested in overseas reception to keep up with current affairs. It is also the in-things for amateur operators to have a general coverage receiver handy.

CIRCUITRY AND TECHNICAL DESCRIPTION

The R1000 tunes from 200 kHz to 30 MHz in thirty bands each one MHz wide. An analog dial with 10 kHz calibration divisions is supplemented with a LED digital readout with one kHz resolution. This readout is also switchable to a crystal controlled clock with facilities for preset switching on and off both the receiver and auxiliary equipment such as a cassette recorder. Selectivity is taken care of with three Murata ceramic filters. These provide for wide AM, 12 kHz, narrow AM, 8 kHz and SSB with 2.7 kHz selectivity. A first for this type of receiver is the inclusion of a noise blanker. Other features include an RF attenuator for the receiver front end, a dimmer switch for both the digital display and dial and S meter illumination and an audio tone control.

The R1000 is the first receiver of its type to get away from the Wadley Loop principle and yet still have the advantages of this type of operation. The PLL synthesizer provides a heterodyne signal to the first mixer to up-convert to 48.0 MHz. The second mixer converts to 455 kHz and this is also fed from the synthesizer. Both first and second mixers are balanced. The synthesizer output is also used to switch in appropriate band pass filters for the receiver front end. This of course eliminates the need for separate front end tuning and the need to follow main tuning with the preselector to maintain sensitivity. As if

this was not enough, the synthesizer also drives the digital readout.

The R1000 has a built-in AC power supply designed to operate from 100 to 234V. There is no provision for any in-built battery supply — but a DC connector allows for externally supplied 12 volt DC operation.

APPEARANCE AND IMPRESSIONS

Kenwood have carried through the general appearance of the 120 series transceivers to the R1000, although the front panel dimensions are slightly larger and the cabinet depth slightly less. The R1000 weighs in at 5.5 kg. Overall the appearance would have to be rated as very good and the only criticism possible is the analog dial and 'S' meter. The faces of both are completely opaque and finished in a bright silver. The calibration points are rear illuminated in bright green, but under conditions of high ambient light, reflection from the silver makes the dial and 'S' meter hard to read. With low external light both are very legible.

Controls are in general easy to use. The only exception to this is the tone control which is concentric and to the rear of the volume control. As its diameter is only slightly larger than the volume control it is hard to operate. Perhaps the next model will have a small lever extending from it to help.

The unusual carry handle seems to be either liked or completely disliked, however it does serve a useful dual purpose. As well as being a carry handle it also acts as a variable tilt angle support for the receiver when installed on a desk.

Another feature is the rear panel. This is recessed and set at an upward facing angle, and allows connections to be changed easily with the set in situ. Connections can also be routed into the back panel with the set pushed hard against a wall.



PHOTO 1: Good appearance — the R1000 and a TS520

THE R1000 IN USE

For comparative tests we set up the R1000 alongside a TS820S, with a two position coax switch to feed both from the same antenna. The antenna for low frequency reception was at first a parallel connected 80 metre dipole. It was soon obvious that this was a bit too much. Even with the RF attenuator at the 40 dB point there was quite a bit of cross modulation. We finished up with about 10 metres of wire stretched out on the floor and this gave excellent broadcast and long wave reception. Aircraft NDBs were audible at good strength over distances of 100 km or so. Quality of broadcast reception was outstanding. With a Hi-Fi speaker plugged into the extension speaker output, the high frequency response was superior to my AM/FM Hi-Fi outfit. This was of course using the wide AM mode of the R1000.

However, over to the short wave bands and naturally the first part we checked were the amateur bands. Anything audible on the 820 was equal in every way on the R1000. It was only under the most difficult QRM conditions that the superior selectivity of the 820 made a slight difference. But mark this, the difference was slight and this applied to all bands including ten. The turning rate, although somewhat faster than the TS820S was still good at

50 kHz per knob revolution and a very smooth dial drive made tuning of SSB easy. It should also be noted that SSB resolution is made considerably easier with the 2.7 kHz bandpass as compared with receivers with similar tuning rates but wider selectivity. The calibration of the digital readout proved to be quite accurate in the AM mode and a plus or minus one kilohertz error on SSB depending on the sideband selected. One of the highly rated points of the R1000 is the noise blanker, however we found its action rather disappointing. In fairness, it was no worse than the blanker in the 820S but I have never considered that one very good either. It did reduce ignition noise to some extent and appeared more effective on the higher frequencies above 20 MHz.

The quartz controlled clock was extremely accurate for the duration of our test. It is of course independent of the mains, so that even when the R1000 is run from a battery supply the clock will still operate. On a personal point, I would have preferred a 24 hour type to the 12 hour one. AM and PM indicators however overcome this to some extent.

Output to a cassette recorder is made via a 3.5 mm phone socket and audio level proved excellent for the aux. socket on my AIWA recorder. This output is at a constant level and is not affected by

the setting of either the volume or tone control.

While on the subject of the tone control, I thought that its effect was too small and more top cut would have been useful in many cases.

However, most criticism would have to be mild in view of the overall superb performance of the receiver. The R1000 is well ahead of any other comparable receiver on the market at the present time.

Overall stability proved most impressive with total drift not exceeding one kilohertz over several hours of operation.

INSTRUCTION BOOK

The receiver tested was an early sample and did not come with an instruction book and in fact it was to be several weeks before one came to hand. When it did, I was delighted until I opened it and found not one, but several instruction books all in different languages. This means that instead of one large (at first sight) book, there is one rather small book. The information contained is completely directed at a non-technical user. Apart from the block diagram and the circuit diagram there is no technical description at all.


It seems a pity in this age when equipment is getting better all the time, general instruction books are steadily getting worse.



PHOTO 2: Rear view of the R1000. Note easy access to connections.

In conclusion, I am collecting all the old bottles I can find to rake up a down payment on an R1000. Our test model was supplied by VICOM International of Melbourne and all enquiries regarding price and delivery should be directed to them.

FIGURE 1 (below): Schematic diagram of the R1000. Of special interest is the PLL synthesiser unit.



CHIRNSIDE ELECTRONICS



All-New FT-101Z Series:

High-performance HF Transceiver with today's technology backed by a proud tradition. This rig includes variable IF bandwidth, digital plus analog frequency display, a built-in RF speech processor, and wide receiver dynamic range.

YAESU.

FT-101Z, 160-10M Transceiver, analog dial.....	\$750.
FT-101ZD, 160-10M Transceiver, Digital.....	\$898.
optional digital display for FT-101Z.....	\$148.
optional Fan.....	\$39.
optional DC-DC converter.....	\$79.
SP-901, ext. speaker.....	\$53.
YD-148 Desk mike.....	\$45.
FT-901DM, 160-10M Transceiver.....	\$1322.
FT-901, ext. VFO for FT-901 & FT-101Z.....	\$429.
YO-901, Panoramic adapter moniterscope.....	\$475.
FC-901, Antenna coupler.....	\$248.
FTV-901, Converter, 6M, 2M, 70 cm. all inc.....	\$785.
FTV-901, Converter, 6M, 2M, only.....	\$539.
YR-901, Morse reader.....	\$78A.
FRG-7, Communication receiver.....	\$559.
FRG-7000, Digital communication receiver.....	\$509.
LF-2A, Narrow band filter for FRG-7.....	\$20.
FT-7B, 80-10M Transceiver.....	\$599.
PP-12, 12 Amp. power supply for FT-7B.....	\$159.
YC-7B, Digital display for FT-7B.....	\$119.
QTR-24 24 hr. World clock.....	\$33.
QTR-24D, Deluxe 24 hr. World clock.....	\$49.
FT-227RA, 2M, Scanning digital transceiver.....	\$379.
FT-227RB, 2M Digital programmable transceiver.....	\$40A.
YP-150, Dummy load/Watt meter.....	\$109.
FF-50DX, Low pass filter, 2kw.....	\$39.

QTR-24D, Deluxe 24 hr. World clock. \$49.

EMOTATOR ROTATORS



103LXX, Medium Duty.....	\$164.
802CXX, Heavy Duty.....	\$248.
1102MXX, Extra Heavy Duty.....	\$359.
1103MXX, Extra Extra Heavy Duty.....	\$395.
503 Mast Clamp.....	\$32.
103 Mast Clamp.....	\$22.
VCTF-7, 7 Core Cable, per Metre.....	\$1.20
VCTF-8, 8 Core Cable, per Metre.....	\$1.60.

DIWA

DR-750DS, Medium Duty.....	\$175.
DR-750DD, Heavy Duty.....	\$249.

FT-207R, 2M Hand held transceiver. . . Fully programmable. . . \$335.

AUTHORIZED DEALER

VCOM

ICOM



CHIRNSIDE MOBILE HELICAL WHIPS.

Chirnside Helical Whips feature an all adjustable stainless steel tip rod for easy tuning.

Finished in heavy PVC heatshrink tubing and chrome plated fitting, will fit any 3-8 x 24 TPI thread base.

80 M.....	\$21.
40 M.....	\$20.
20 M.....	\$20.
15 M.....	\$19.
10 M.....	\$19.
Bumper mount to suit.....	\$9.

SET OF ALL FIVE FOR ONLY \$95 INCLUDING BUMPER MOUNT.

CHIRNSIDE TRAP VERTICAL

Chirnside Vertical Antenna Type CE-5B Features.

Long length and high Q traps makes the CE-5B more efficient than similar types of antennas especially on 80 Metres.

It is also very easy to tune and its construction is very rugged.

- Easy to tune.
- Rugged construction.
- Easy to assemble.
- 12 month guarantee on parts and workmanship.
- Only \$99.-.



\$139

CHIRNSIDE CE-42 rugged duo band beam features 4 elements and uses independent reflectors for optimum results.

3 elements on 15 M.

3 elements on 10 M.

Director and driven elements have hi-q traps.

Forward gain is 8 dB and front to back ratio is in excess of 20 dB.

Dozens of reports have indicated F/B ratios in excess of 28 dB.

CE-42 15-10 M. Duo-Band..... \$139.

CE-5B 5 Band Vertical..... \$99.

CE-4B 4 Band Vertical..... \$85.

Compare our antennas with other brands and see that it is of a better quality.

Ask about our rotator - antenna package deal and save \$\$\$\$\$\$.



welcome here

FAST MAIL ORDERS.

CHIRNSIDE ELECTRONICS, 28 Edwards Road, Chirnside Park, Lilydale, 3116. Phone (03) 726 7353

EQUIPMENT REVIEW:

THE YAESU FT-207R

Ron Fisher VK3OM

It is often said that good things come in small packages. The new Yaesu FT-207R is a hand held two metre FM transceiver and even for one used to using hand held equipment the 207R would have to be rated as very small. When it is considered just what this rig will do, the whole thing becomes quite remarkable. However, back to the beginning.



PHOTO 1: Front view of the FT207R

Two metre hand held transceivers go back quite a few years in the history of FM in Australia, but strangely cover only a very few models. Yaesu were rather late into the hand held field with the FT-202R announced a year or so ago. I am not certain if any of these were actually imported into Australia. These were six channel devices of apparently conventional electrical design with normal crystal control. Transmitter output was rated at one watt. The new FT-207R uses the same case but from there on, apart from the fact that they both operate in the two metre band there is very little in common. The FT-207R has more electronics built into its 68 x 181 x 54 mm case than almost any other mobile size package. Lets look at what it offers

It has full microprocessor control with keyboard dial up frequency control. It covers the entire two metre band in ten kilohertz steps with a switch selected 5 kHz upshift. Four memory frequencies can be entered via the keyboard and scanning of either the four memories or the entire band is available with the scan stepping on either a busy or clear channel. Operating frequency is indicated with a LED readout and of course the usual 800 kHz offset for repeater operation can be selected with the function switch. In addition any other desired offset can be programmed into the system. Once a memory is programmed it is held even if the transceiver is switched off, for as long as the in-built nicad battery retains its charge. As the memory uses about 5 milliamps, this is limited to about 80 hours assuming no actual operation of the transceiver

Transmitter output is rated at a generous 2.5 watts and on test actually produced just over three watts.

The FT-207R as supplied for test was complete with a nicad charger/AC adapter, external microphone/speaker, flexible antenna and adaptor to charge the battery when removed from the transceiver.

At least some of these are optional extras and it would be well to contact the distributors for all-up prices.

An interesting point is that the nicad battery is rated at 10.5 volts and the manual states that the transceiver should not be operated on a voltage in excess of exactly 12 volts. It would seem therefore that operation should not be attempted from a standard 12 volt car system which would rise to about 14 volts. Strangely, Yaesu do not have any sort of adaptor or regulator for such operation.

CIRCUIT DESCRIPTION

As could be imagined the little box contains a large number of semiconductor devices. There are in fact 31 transistors, 5 FETs, 10 ICs, 35 diodes plus 2 LEDs and a LED display. The receiver circuit is a standard double conversion with 10.7 MHz and 455 kHz IFs. However it comes as a surprise to find bipolar transistors in the RF and first mixer stages, but in practice sensitivity was first class.

The transmitter starts off at 10.7 MHz and is mixed directly with the 133.3 to 137.3 MHz output of the synthesized frequency control to produce the 144 to 148 MHz output. This same synthesized output is also injected into the receiver first mixer to convert the two metre signals to the first 10.7 MHz receive IF. Reference to the block diagram indicates the operation of the synthesizer and its control from the 4 bit microprocessor chip. An interesting point is that when the VCO is in an unlocked condition, voltage is removed from both the transmitter and receiver and the frequency display indicates 'E' for error condition. Transmitter output is switchable from the nominal 2.5 watts down to 200 mW simply by inserting a resistor in series with the voltage supply to the final and driver stages.

Diode switching is employed for transmit receive changeover which allows for normal push to talk operation with the external microphone. A microswitch is employed in the PTT switch on the transceiver which gives very positive and light control.

THE YAESU FT-207R ON AIR

This is one transceiver where it is absolutely necessary to read the instruction manual before trying to go on the air.

The transceiver was used in turn by four experienced amateurs and all found that the set had unexplained "faults". However the fault turned out to be the operators' and not of the set. In each case the manual had not been fully digested. But back to the start with a look at the controls and their functions. The top panel has the volume/on/off, squelch, mode switch for simplex or repeater operation, a 3.5 mm socket for external earphone or speaker, a BNC antenna connector and a multi pin miniature connector for the external microphone speaker unit. On the front of the set is the frequency selection keyboard, the LED frequency readout, the two LEDs to indicate transmit condition and incoming receive signal. Three miniature slide switches select the 5 kHz up condition, frequency display off and keyboard lock. The two latter require some additional explanation. The display off switches the display off once a frequency has been selected after a three second delay. If a new frequency is dialled up the display operates again for three seconds. While scanning the display operates and switches off three seconds after scanning stops. The keyboard lock switch retains the dialled frequency even if a new one is dialled up either accidentally or purposely.

FROM



ELECTRONICS

The Little Handie ... with the big features FT-207R

CPU controlled synthesized Handie

The "horse-and buggy" days of crystal-controlled handies are gone! Yaesu's engineers have harnessed the power of the microprocessor, bringing you 800 channels, digital display, memory and scanning from a hand-held package. Only with Yaesu can you get these big performance features in such a compact package.

*4 bit CPU chip for frequency control *Keyboard entry of all frequencies *Digital frequency display *800 channels across 144-148 MHz *Up/Down manual scan, or auto scan for busy/clear channels 10 kHz or 12.5 kHz scanning step models available *Four channels of frequency memory *Priority channel with search-back feature *Keyboard lock to prevent accidental frequency change *Two-tone input for autopatch *Memory backup *±600 kHz or odd repeater splits *Display ON/OFF switch for battery conservation *2.5 watts (min) RF output *Equipped with rubber flex antenna and one NiCd battery pack

OPTIONS FOR FT-207R

*NC-2 Quick Charger *YM-24 Remote Speaker/
Microphone *Leather Carrying Case *Extra NBP-9
Battery Packs

SPECIFICATIONS: FT-207R

GENERAL

Frequency coverage 144-148 or 144-148 MHz
1per local regulation(s)
Emission type: F3
Batteries: NiCd battery pack
Voltage requirement: 10.8
VDC ± 10% maximum
Current consumption:
RX 150 mA (35 mA
switched)
TX 800 mA (400-250 mA
low)
Memory backup: Approx.
4 mA.
Case dimensions: 68 x 181
x 54 mm (HWD)
Weight (with batteries):
880 g

Display OFF

TRANSMITTER

Power output:
2.5 watt RF 250 mW RF
Deviation: ± 3 kHz
Spurious radiation: 60 dB
or better
Microphone impedance:
type 200 ohms resistance

RECEIVER

Circuit type: Double
conversion
superheterodyne
Intermediate frequencies:
1st IF = 10.7 MHz
2nd IF = 455 kHz
Sensitivity: 0.32 µV for
30 dB quieting
Selectivity: ± 7.5 kHz at
60 dB down
Audio output: 200 mW at
10% THD

COFFEY HARBOUR (085) 543206 TAINWORTH (067) 801363 INVERELL (067) 221303 OLD
BIRCH (077) 722100 TONGUE HILL (081) 621100 WARRAMONGEE (081) 621100
BIRCH (077) 722100 TONGUE HILL (081) 621100 WARRAMONGEE (081) 621100
BIRCH (077) 722100 TONGUE HILL (081) 621100 WARRAMONGEE (081) 621100

AGENTS & SUPPLIERS: W.A. COMO (093) 450439 PERTH (08) 3217698 KALGOORLIE
(08) 3217698 WARRAMONGEE (081) 621100 WARRAMONGEE (081) 621100
(021) 6571550 SEVEN HILLS (03) 8242881 NEWCASTLE (049) 8242881 WAGGA WAGGA
(089) 231925



60 Shannon St., Box Hill North, Vic., 3129. Phone 892213
Distributors in all states and N.T.

STAN ROBERTS VK3BR
JIM BA L VK3ABA

CALCULATION OF GREAT CIRCLE DISTANCES

C. K. Maude VK3ZCK

2 Clarendon St., Avondale Heights 3034

Over many years radio amateurs and others have tried to calculate the distance between two known points on the earth's surface using mathematical tables or slide rules. These methods can be quite time consuming and frustrating.

The basic equation used is

$$D = \arcsin(\sin(\text{lat I}) \times \sin(\text{lat II}) + \cos(\text{lat I}) \times \cos(\text{lat II}) \times \cos(\text{lon I} - \text{lon II})) \times M$$

where —

lat I is the latitude of the first point and lon I is the longitude of the first point and lat II is the latitude of the second point and lon II is the longitude of the second point, all of these being in decimal degrees, and where M is the multiplier for kilometres, miles or nautical miles.

For those having scientific calculators, one of the programmes shown here can be used. There are programmes for fully programmable types and simple models, for reverse polish notation and for algebraic modes.

The only information that is required to obtain the great circle distance between any two points is the latitude and longitude of both points in degrees, minutes and seconds. The latitudes and longitudes must first be converted to degrees and decimals, remembering that 60 seconds make one minute and 60 minutes make one degree. Answers can be calculated in kilometres, miles, or nautical miles by using the appropriate value of M as shown.

For kilometres use M = 111.12
For Miles (statute) 68.047
For Miles (nautical) 60.00

NOTE:

When longitudes are East change the sign to -ve.

When latitudes are South change sign to -ve.

If both are East or both are South no change is necessary.

Example:

Melbourne Airport: Lat 37 40 30, long 144 50 32,

Launceston Airport: Lat 41 32 45, long 147 12 48,

lat I = 37.675, lon I = 144.842,
lat II = 41.547, lon II = 147.214.
Distance: 475.72 km, 295.6 miles, 256.67 nautical miles.

Note that if only degrees and minutes are used the accuracy is still better than 0.5 per cent for this example. ■

LISTING OF PROGRAMMES

CALCULATOR TYPE				
RPN		Algebraic		
Step	HP45, HP35, HP55, etc.	Novus 3500, NS 4510	With store — TI59, etc.	With brackets — TI25, etc.
1	Clear all functions	Clear all functions.	Clear all functions.	Clear all functions.
2	lon I ENTER	lon I ENTER	lon I =	lon I =
3	lon II =	lon II =	lon II =	lon II =
4	COS	COS	COS X	COS X
5	lat I COS X	lat I COS X	lat I COS X	lat I COS X
6	lat II COS X	lat II COS X	lat II COS =	lat II COS =
7	lat I SIN	STO CLR	STO CLR	+ (
8	lat II SIN X	lat I SIN	lat I SIN X	lat I SIN X
9	+	lat II SIN X	lat II SIN	lat II SIN
10	ARC X COS or COS⁻¹	RCL +	= + RCL =) =
11	M X	ARC COS or COS⁻¹	ARC COS or COS⁻¹	ARC COS or COS⁻¹
12	Answer	M X	X	X
13	Answer	Answer	M = Answer	M = Answer

Calculator function and operation keys are shown in bold type.

CW ELECTRONICS PROCESSED HAM



***149**

***MACROTRONICS M65
HAM INTERFACE FOR PET
MICROCOMPUTERS.**

***269**

The M-65 is a complete Morse Code and RTTY system for the PET microcomputer. It is made up of two parts: the hardware and the software. The hardware consists of one PC board which is connected to your rig and to your PET user port. No modifications are required to either your radio equipment or to the PET — everything plugs into existing jacks. No external power supply is required. The software consists of two computer programs — MORSE and RTTY — supplied on one audio cassette. Both programs

are written in BASIC with machine language subprograms. Each requires 8K bytes of RAM. Program MORSE allows continuous speed adjustment from one to 100 words per minute in any of three modes of operation: Receive, Send, and Code Practice. In addition, up to ten programmable message memories (2550 characters total) allow "brag tapes", pictures, etc. direct from the keyboard. A special feature allows sending the time automatically at the press of a single key!

Other MACROTRONICS modules include the M650 Deluxe RTTY and Morse system interface with software cassette.

MLK-1 loop Keyer module,
MSK-1 Solid State Keyer module,
FSD-1 Phased-locked loop
de-modulator, ***149**

especially for the RTTY enthusiast.
If you have a TSR-80 or a Sorcerer,
we can help you too!

**AUST.
AGENTS**



***309**

TR 128

**RTTY REGENERATIVE
SPEED CONVERTOR**

TTL compatible connections for direct hook-up to the FLSHER TU-170, also adaptable to other terminal units.

- 60, 67, 75, 100 WPM and 110 BAUD ASCII
- Continuously variable character rate
- Stable crystal-controlled oscillator.
- Low power CMOS circuitry.
- 128 Character storage capacity with storage status meter to show buffer fill
- One-board (total circuitry) construction.
- Pre-loads and repeats up to 128 characters.
- Power requirement 115V 60Hz, 5W



**TU-170
AUTO START *299**

State of the art design features make the TU-170 ideal for HF and VHF autostart operation at an unchallenged price.

- SIZE 7 1/4" W x 3 1/4" H x 7 1/2" D
- Stable audio frequency shift oscillator produces phase coherent sine wave tones
- Proved 170 Hz shift active filter demodulator.
- TTL compatible inputs and outputs for auxiliary equipment.
- Lighted tuning meter for easy tuning.
- High level output for scope tuning.
- Current regulated loop keyer and power supply
- 100 Hz shift CW keying input
- Autostart with threshold control and solid state relay

*DEALER ENQUIRIES WELCOME

CW ELECTRONICS

**CNR MARSHALL RD & CHAMBERLAIN ST.
TARRAGINDI — BRISBANE PH. (07) 48 6601
P.O. BOX 274, SUNNYBANK, QLD, 4109.**

80 METRE VERTICAL

M. N. O'Burtill VK3WW
3 Maxwell St., Lator, Vic. 3075

Here is a 23 foot antenna that is cheap, effective and easy to build. It is the answer for 80 metre operation when you can't erect a 136 foot flat-top.

The antenna is made from 3/4 in. aluminium tubing for the lower section and part of the upper section, which is tuned by telescoping 1/2 in. and 3/8 in. tubing.

The loading coil is wound with 14 SWG enamel covered wire and is probably the hardest part of the whole project.

I mounted the antenna on a 30 foot corner pole and have the base of the antenna about 10 feet above the ground but there is no reason why it should not work with the base at ground level.

Using a wooden mast is an easy way of erecting a vertical, and providing it is insulated from the mast the antenna is not affected in any noticeable way.

I used a series of wooden blocks and shelf brackets to hold the vertical in place. Each block measured 4 1/2 in. x 2 1/2 in. x 3/4 in. and had a 3/4 in. hole positioned as shown in Fig. 1. 3 in. lengths of clear plastic tubing were then slid on to the aluminium tubing and positioned so as to insulate the antenna from the mounting blocks. Ordinary hose clips were used to hold the tubing in place once the blocks were mounted on the mast and the plastic tubing of course insulated the aluminium tubing from the hose clips.

If you have any trouble sliding the plastic on to the tubing, boil up some water and let the plastic lie in it for a few minutes; it softens very quickly.

The loading coil manufacture and mounting was the hardest part of the project, yet it seems quite simple at first. All you need is about 20 feet of 14 SWG wire, 3 pieces of perspex or similar insulating material, a coffee tin, a co-operative XYL, and lots of patience.

The aim is to finish up with a coil 4 1/2 in. diameter with 38 turns spaced to take up about 10 in.

My method was to carefully mark out the three pieces of perspex and then drill 38 holes in each, spaced one diameter of 14 SWG apart. Two perspex pieces measured 9 in x 1 in. and the third 10 in. x 2 in., which provided the method of mounting to the mast. I also used two more pieces to join the two 9 in. x 1 in. pieces across the coil to stiffen the mounting. It is hard to put into words, but the photograph should get the message across.

I first close-wound the coil on a 4 in. diameter coffee tin. As soon as tension was released the coil expanded to 4 1/2 in. diameter.

The next job is the hardest. Starting from one end of the coil thread the three perspex spacers on to the coil. You cannot do this single-handed, so be nice to your XYL or recruit some unsuspecting local amateur to help you. An hour or so later you will have a nice coil and/or a divorce case pending—no matter, it's all in the cause of science or something.

GETTING IT ALL TOGETHER

Mount the stand-off blocks on the mast as shown in Fig. 2, being careful to keep the holes in line. Next mount the coil using the large perspex spacer as the mounting to the mast. Next slide the tubing into position and tighten the hose clips to hold it firmly in place.

Carefully bare the wire at each end of the coil and tin about 1/2 in. Now wrap a couple of turns around the tubing at each end of the coil and solder the wire to a lug held in place by a self-tapping screw. Use the same method at the base of the antenna to connect to the coax socket.

TUNING

At this stage I should mention that my mast is hinged to an extended barge-board and can be easily tilted to horizontal. This is necessary as all adjustments are made by sliding the 3/4 in. tubing at the top of the antenna.

I find the best method of getting any antenna on frequency is to use a noise bridge and a general coverage receiver. If you don't have a noise bridge you can buy or build one. A good article on building one appeared in AR for July 1971, with modifications in AR October 1971.

There are two reasons for using a general coverage receiver.

One is that your first try could well have the antenna out of band limits. Also most modern transceivers are too sensitive and selective and make finding the null hard work. In any case adjustments are small, say 1 in. or 2 in. at a time, so you have to be prepared to do a lot of climbing up and down the ladder.

I selected 3.6 MHz as centre frequency and SWR checks show a bandwidth of at least 50 kHz each side of centre.

The test of any antenna is how it works under all conditions. Previously I have used a G5RV in inverted V configuration, so I ran checks against this antenna. The table shows the results—generally over longer paths (200 miles or more) the vertical won every time.



Coil close-up showing construction detail

All verticals are noisier than horizontals and this one is no exception. However, the increase in noise was not too bad, perhaps because an inverted V has some vertical properties anyway.

It would be great to have an 80 metre dipole and a vertical but this isn't on for the average suburban block, so I think this vertical is quite an efficient antenna under the circumstances.

MULTI-BAND AS WELL

After satisfying myself that the vertical was working well on 80m I tried loading it on other HF bands.

I fed it through an aerial coupling unit (Willy Willy's Wonder, AR January 1977) and found I could load it quite well on 40m, 20m and 10m.

Of course on these extra bands it does not perform as well as a full size dipole, but is suitable as an emergency antenna capable of working all VK and ZL at least.

All things considered, this antenna is cheap, fairly easy to build and tune and performs well on 80m. With a little imagination it could be made to fit most houses.

No radials were used but an earth spike at the base is essential. My vertical is fed with 70 ohm coax because I had some available. It would probably perform better with 50 ohm and even better with a 2:1 RF transformer, so there is room for improvement if you have the bits and pieces available.

All soldered connections were covered with DENSIO 510 tape to provide weather-proofing. This tape is covered in wax, which enables moulding by hand once it is wrapped around the tubing.

This article is written mainly for the amateur with limited space, and it is hoped that it will enable more amateurs to enjoy 80m operation.

TEST TABLE

Distance	G5RV	Vertical
2-10 NM	0	+ 10 dB
Melbourne-Sydney	0	+ 2 S points
Melbourne-ZL2	0	+ 2 S points
Melbourne-Wagga	0	+ 1 S point
Melbourne-Adelaide	0	+ 1 S point
Melbourne-Hobart	0	No Difference
20-200 NM	0	+ 1 S point
10-20 NM	0	+ 2 S points



The 80 metre vertical




FIG. 1: Wooden blocks stand off construction.




FIG. 2: Stand off mounting positions

C.A.R.E.

(Community Amateur Radio Events)


In times of emergency amateurs often provide the only communication link. One recent occasion was on February 15, 1979, when the US Embassy in Teheran was occupied by Iranian nationals. Charles (Chuck) Watter W4RHE had been keeping in touch with his sister and her family in Teheran via a local amateur. After the US Embassy's communication facilities were shut down Charles became the official relay station for the State Department in Washington and kept the link operating until the Iranian amateur station was closed down. The information passed via the link gave the US its only information in relation to the safety of its embassy staff during the initial stages of the occupation.

Letters of thanks from the White House and the House of Representatives were sent to Charles.

Charles, who from 1980 to 1982 held the call VK8TB, has been licensed for 31 years and welcomes VK QSOs and VK visitors.



Charles W4RHE (left) presented with letter by Congressman Nelson



Letter signed personally by President Jimmy Carter

THE PHILIPS FM321

A 70CM 40 CHANNEL
FULLY SYNTHESISED
AMATEUR RIG

Australian Designed
Australian Made



FOR ONLY
\$299*

With these features ● 40 synthesised channels with electronic channel change and LED readout. ● Channel selection up or down from front panel or hand microphone. ● A LED each for power on, transmit and receive. ● 5 watt RF and 1 watt audio power. ● Combined signal strength and RF power meter. ● Single or two frequency simplex operation on any of the 40 channels. ● Instant selection of these modes plus any one nominated repeater channel. ● 5MHz TX/RX separation on repeater mode. ● PL259 antenna socket. ● 6 pole crystal filter combination for improved selectivity. ● High sensitivity.

and this performance

Typical data at 22°C 13.8V

Frequency Range. TX 433.025MHz to 434.000MHz

438.025MHz to 439.000MHz

RX 438.025MHz to 439.000MHz

Frequency Stability: Better than 6ppm 0°C to +80°C

Supply Voltage: 11 to 16.2Volts—V_e earth

TRANSMITTER

Power Output: 5Watts

Spurious Output: -83db(out of band)

Audio Response: 6db/octave pre-emphasis

300Hz to 2KHz

RECEIVER

Audio Output: 10Watt at 10% THD into 8Ω

Selectivity: 50db at ±25KHz

Sensitivity: 0.3μVpd (12db SINAD)



PHILIPS

Please send me an FM321
by registered mail

To: **Philips - TMC**
Radio Communications Division, AUSTRALIA
P.O. Box 105, Clayton,
Victoria, Australia, 3168

NAME _____ ADDRESS _____

STATE _____ POSTCODE _____

CALL SIGN _____

CHEQUE No/MONEY ORDER No _____ IS ENCLOSED FOR

\$ _____

OR

PLEASE DEBIT MY BANKCARD No _____

EXPIRY DATE _____

FOR \$ _____ SIGNATURE _____

* Add \$4.00 for packing and postage






PHOTO 1: The much sought-after RD Contest Trophy — a reminder of those amateurs who became Silent Keys during World War II. (See page 27 for last year's results.)

QSP

16 GHz DX RECORD

According to Ham Radio of Oct. '79 a new 3 cm band record was set on 27th July by 4CHY/7 and 12FZD/2. The distance of 633 km was from a mountain top NE of Milan by the latter station to Testa del Gargano on the Adriatic Coast by the latter. Both used Gunnplexers and 1m dish antennas.

ALL AIRWAVES ARE NOT FREE

An article, so entitled appeared in Oct. '79 QST and gives much food for thought. It is too lengthy to quote in full but deals with MDS (Multi-Point Distribution Service) systems in the 2.5 GHz region which are over-the-air relay systems for premium movies and other specialised TV fare received on a monthly rental basis and providing receiving system equipment (typically around \$50 per installation) and interception of geostationary (common carrier programmed) satellites channels.

PHILATELISTS' NOTE

West Germany has issued a 60 pfennig WARC commemorative postage stamp which shows the front panel of a Collins KWM-2 transceiver, tuned to the 21 MHz CW band. Plans for a separate amateur radio commemorative stamp have been dropped resulting from this issue. Ham Radio, Oct. '79.

HISTORIC "JUNK"

In his editorial to Oct. '79 Ham Radio Jim Fisk W1FR commented his inability to attend an auction recently of surplus electronic equipment dating back to the '920s but into custom-made wooden cases which were then in fashion. Most of the buyers, he said, were antique dealers who were interested only in the finely crafted cabinets — the priceless radio equipment inside was destined for the trash heap. He quoted another dealer's opportunity to pass for acquiring old gear for his collection from a sale of a local deceased amateur's collection of "junk" which filled four large warehouses. He recommends amateurs to talk to their heirs and clue them in as to what items, if any, belong in a museum. Put the details down in the will and give your executor the names of trusted amateur friends to help dispose of more modern gear at a fair market value as the equipment's value would be meaningless to most ex-collectors.

MARITIME EMERGENCY

The following is pieced together from articles in the Toowoomba Chronicle of 11th, 14th and 28th December, received from Steve St George VK4SE, all acknowledged with thanks. Stephen Zadkovic with his wife Jenny VK4XV/MM and his brother Gary sailed from Brisbane aboard the 32 ft Toowoomba-built steel sloop "White Wave" in August '79 on a round-the-world trip. Daily skeds were kept between VK4SE and the sloop which ran into cyclone Albert some 500 miles south-east of Rodrigues Island in the Indian Ocean. Before the storm reached its peak on 3rd December, VK4SE received a relayed position fix from the sloop and several other amateurs in Australia, South Africa and Mauritius joined in a listening watch. VK4SE also reported the details to "Marine Operations" in Canberra. The sloop was "oled four times during the storm. The life raft went overboard on the first roll, but the mast went in the second capsize next day, but throughout the radio was saved and when dried out, Jenny was able to transmit Morse for a contact with a ZS station on 8th December using a makeshift antenna rigged up on 6th December. By that time the battery was nearly flat, they had no fuel and no mast but were making two knots under jerry rig. The ZS authorities were ready to mount a search and rescue operation but before they could act, clearance was requested from Canberra. However, the Mauritian authorities did act and the sloop made harbour for shipment to Toowoomba for repairs. All the occupants were safe and had returned home.

EMPLOYMENT OPPORTUNITY

- Brisbane -

The Company, a young energetic business with high growth possibilities in the area of Amateur Radio, Micro Computers and Commercial test and communications equipment.

POSITION 1 - Service Technician.

A qualified technician to manage our service centre. Previous experience in communications equipment and digital technology essential. A pre-requisite is an Amateur Radio licence and some sales experience an advantage.

POSITION 2 - Sales Engineer

To handle our quality range of products (as above). The market area includes government and commercial bodies. A pre-requisite is an Amateur Radio licence or will agree to obtain one at the earliest opportunity. Some service experience would be an advantage. The position involves some travel.

Salary & conditions negotiable.

APPLICATIONS

Initial applications should be in writing stating work experience, qualifications and other relevant details.

Mark Confidential
Att: Mr. Brian Beamish

CW ELECTRONICS

P.O. BOX 274, SUNNYBANK QLD 4109

HOORAY FOR

(NONE OF THE ABOVE!)

Submitted by
Bruce Saxton VK3NSB
77 Edithvale Road, Edithvale, 3196

This concoction is dedicated to all those hard working amateurs who so generously give of their spare time to present courses and lectures to aspiring students of NAACP and AOCP.

The idea was taken from the Educational Magazine, Vol. 36, No. 5, 1979, titled, Hooray for (None of the above).

The time is set as some time in the future.

I wasn't aware of the awesome changes sweeping through our educational system until I visited the Henry Radio School the other day and had a little chat with its Principal, Dr. Homer P. Dantic. "How are you?" Inquired Dr. Dantic, shaking my hand. "(A) Just fine, (B) not too bad, (S) so-so, (D) not too hot, (E) at death's door?" "(A) thank you," I said, "and you?" "(B)" said Dr. Dantic, "But let me tell you I certainly was (D) last month when our Novice grade students scored in the thirty second percentile of the seventh stanine at the Novice grade level on the Standard Webley-Vickers Radio Theory Test." "Good grief," I cried, "What an indictment of your educational methods. Did you discover a solution?" "Well it was clearly a multiple choice problem," said Dr. Dantic. "Tell me, do you think we should have (A) purchased one of the 1156 other sample tests now on the market, with the hope that there would be at least one test that would make our faculty look good; (B) attempted to attract a better calibre of student through a recruitment programme; (C) drastically revised our teaching methodology; (D) burned down the school; (E) none of the above?" "Let's see," I said. "I think . . ." "Sorry, your time is up," said Dr. Dantic, clicking his stop watch. "Actually after much thought, we took the plunge and decided to (C)." "You mean you have drastically revised your methodology for teaching Radio Theory?" I asked. "No, we have drastically revised our methodology for teaching our students how to score well in multiple-choice tests," said Dr. Dantic.

"Would you like to see one of our new dynamic instructional modules in action?" I said I would, indeed. It was a most enlightening experience. The module we visited contained 32 students and Miss Ann Tenna, an enthusiastic young teacher. As we entered the room Miss Tenna was reviewing a homework assignment. "Who can tell me the name of the assistant who polished Marcon's ebony rod with catskin?" she asked "Adrian?" "The name," said Adrian, "is (B)." "Very good, Adrian," said Miss Tenna. "Now, Peter, please tell the class the age of the pilot of the first communication satellite." "It is (D)," said Peter. "Wrong, wrong, wrong," shouted the class, "it is (E)."

Miss Tenna regained control and continued with the probing questions. "What is the square root of 15 712?" (Answer (C)) "Does Mr. Diode still work for Telecom?" (Answer (A).) And so the lesson continued.

"I didn't know you taught the historical aspect of Radio Theory," I remarked to Dr. Dantic. "We don't," he replied. "Then how can Miss Tenna test the students on it?" I asked. "She's not testing on that," explained Dr. Dantic, "She's testing their ability to take tests."

Well, I wish you could have seen the crackjack way in which those students performed. When Miss Tenna cried "Go!", all the students had their papers flipped over in a millisecond and their pencils flashing away as they ruled the little marks on the answer sheet. By the time Miss Tenna blew her whistle Peter was only half way down the page, Miss Tenna looked at him and sighed "How often do I have to tell you, Peter?" she admonished, "When you see that you won't have time to finish a test, simply slash a vertical line down the page, hitting as many boxes as possible. If each question has five alternative answers, you will thereby increase your score by an average of 20 per cent. Adrian will now read your answers to the class?" "Yes," said Adrian, "(B), (B), (B), (B), (B) . . ." "I take it you answered (B) to every question," interrupted Miss Tenna. "Can you tell us why?" "Simple," said Adrian, "I recognised the format of the Hispano-Suza Multiphasic Norm-Referenced Scholastic Evaluation Test. I immediately recalled that the computer readouts we studied last week indicated (B) was the correct answer 28.8 per cent of the time in Hispano-Suza multiphase, as compared to 16.9 per cent for (A), 18.3 per cent for (C), 19.7 per cent for (D) and only 16.3 per cent for (E)." "Very good," said a beaming Miss Tenna. "Class dismissed."

Miss Tenna's admiration for Adrian was echoed by Dr. Dantic when we were out in the corridor. "Adrian is the brightest student we've had here at Henry Radio School in years," he said. "He has already single handed raised our faculty performance record 13 per centiles on the Standard Webley-Vickers Intermediate Placement Test. And thanks to his score of 799 on the Academic Aptitude test, he will move directly to AOCP classes next year." "Most impressive," I said. "Yes," he said, "We are predicting a brilliant academic future for this young chap as he seeks the answers to those all-important questions." "In which facet of amateur radio would he specialise?" I asked. "Multiple-choice testing, of course," he replied.

PENSIONERS

ONLY YOUR DIVISION CAN
APPROVE RE-GRADING TO PENSIONER STATUS — PLEASE
APPLY TO YOUR DIVISION IF
YOU BELIEVE YOU CAN NOW
QUALIFY.

WESTERN ZONE CONVENTION

Jack Thomas VK3NTR
1 Sowans Crescent, Ararat 3377

The Annual Convention of the Western Zone of the Wireless Institute, Victorian Division, was held at Halls Gap on the 10th and 11th of November 1979 and was a great success. The Saturday venue was held with a dinner at the Mountain Grand Guest House with 84 attending. Guest of honour was the President of the Victorian Division, Mr Eric Buggee VK3ZZN and his lovely wife, with many visitors from many parts of Victoria and interstate visitors.

Sundays venue was slightly marred by an opening of the heavens but this was only a minor setback as the proceedings were carried out in the Halls Gap Hall. Forty-six ladies plus a couple of wandering OMs took advantage of the day to have a memorable sightseeing tour of the Halls Gap area.

Trade exhibits were excellent and many an amateur left with an empty pocket. Imark, Vicom, Wecam, Hamilton Electronics and the Moorabbin Club contributed to the drawing of funds and provided excellent displays of various gear.

The convention was a unanimous success and many people have pledged to return to the Halls Gap area again, independent of any conventions. I wish to thank sincerely all those who attended and those whose help effort made the convention worthwhile. Special thanks to Sylvia Rose and her son and the trophy donors for the various events. We hope those who attended left satisfied and those who could not attend can make it to our next convention.



PHOTO 1: Jack VK3NTR congratulates Gordon VK3NO (right) who won the lucky entrance. Brian VK3ZBS looks on.



PHOTO 2: Laurie VK3NDL (c) presents Jack VK3NTR with an award.

VICOM: THE ONE STOP COMMUNICATIONS SHOP!

Daiwa Low Pass Filters

F030LS 32 MHz, Fc, 200 w, 3 stages \$20.00

Daluzs

AS-BL Asahi 50 ohm for beams — \$34.00
BL50A 50 ohm, 4 KW, 1:1 for dipoles — \$32.00
BL70A 70 ohm, 4 KW, 1:1 for dipoles — \$32.00

Leader Test Equipment

LAC 895 Antenna Coupler 3:5 — 28 MHz — \$182
LPM 885 SWR/PWR Meter — \$97
LPM 880 RF Power Meter \$139
LDM 815 TR Dip Meter \$89.00
LBO 310 3" Ham Oscilloscope — \$330
LA 31 Ham Monitor scope adaptor — \$26.00
LSG16 Signal Generator — \$119.00
LSW250 TV-FM Sweep Generator — \$429.00
LAG28 Audio Generator — \$166.00

Tubes

6KD6 Finals for Yaesu linears — \$10.00
6JS6C Finals for Yaesu transceiver — \$10.00
12BY7A Driver — \$4.75
6146B Finals — \$13.00

ICW Filters

FT101E Yaesu — \$39.00
TS520S YG3395 Kenwood — \$57.00
TS20S YG68C Kenwood — \$59.00

Morse Keys

HK702 Deluxe Key with marble base — \$41.00
HK708 Economy Key — \$23.00
HK706 Operator's Key — \$25.00
MK701 Manipulator (side-swiper) — \$45.00
PALOMAR 1C Keyer — \$149.00

Jaybeam Antennas

5Y/2m 5el 2m, 7.8 dBi gain, length 1.6 m — \$43.00
8Y/2m 8el 2m, 9.5 dBi gain, length 2.8 m — \$51.00
10Y/2m 10el 2 m, 11.4 dBi gain, length 4.4 m — \$84.00
10XY/2m 10el 2m, cross yagi, 11.3 dBi — \$114.00
D8/70cm Twin 8el, 70 cm, 12.3 dBi, 1.1 m — \$64.00
P8M 18/70 18 el, 70 cm, 14.9 dBi, 2.8 m — \$96.00
MBM 48/70 48el, 70 cm, 15.7 dBi, 1.83 m — \$83.00
MBM 88/70 88el, 70cm, 18.5 dBi, 3.98 m — \$105.00
PMH/2C Phasing harness — \$20.00
8XY/2m 2m cross yagi, 8el, 9.5 dBi, 2.8 m — \$99.00
12XY/70 cm 70 cm cross yagi, 12el, 13.0 dBi, 2.6 m — \$139.00

Nagara

SS56 6 m 5el beam 1 KW — \$159.00
VSJR 80-10 m trap vertical, 6.7 m high — \$129.00
40-10m trap vertical, 5.2 m high — \$99.00

Hy-Gain Antennas

204BA 4 el monobander for 20 m — \$259.00
203BA 3 el beam 20 m — \$199.00

Scalar

M2T 1/4 wave 2 m mobile whip, top only Qty 1-4 — \$7.00

M2ST 5/8 wave 2 m mobile whip, top only Qty 1-4 — \$14.00

BASE B/L for above — \$4.00

Microphones

VM-1 Noise cancelling, hand ptt, low z — \$10.00

Coaxial Cable

RG58AU mil spec, 30m reels — \$13.91
RG213/U mil spec per metre — \$1.50

Kenwood Transceivers

TS520S HF transceiver — p.o.a.
TS120S Solid state 100w — p.o.a.
TS120V Solid state 10W — p.o.a.
TS180S Solid state 10w — p.o.a.
R-1000 Communications Receiver — \$498.00

Monitor Receivers

747 Vicom Aircraft Scanner — \$199.00
210 Bearcat 210, scanner — \$469.00
HF12 VHF pocket, 12 channels — \$149.00

Coaxial Relays

CX-2L 1.8 thru 170 MHz, 100w pep — \$45.00
CX-2H 1.8 thru 450 MHz, 200 w pep — \$69.00

Coax Switches

CS201 2 position, commercial quality — \$23.00
CS401 4 position, commercial quality — \$59.00

Speech Processors

RF680 Phasing type, 6dB gain, dc — \$109.00
RF440 Phasing type, 6dB gain, dc — \$109.00
RF440 Phasing type, 6dB gain, ac/dc — \$126.00

ICOM

IC701 HF transceiver — \$1199
IC280 2m Remotable — \$450
IC251A 2m All-mode — \$847
IC551 6m 100 watts — \$799
IC551D 6m 100 watts — \$850
IC255A 2m Digital — \$425
IC502A 6m portable — \$269

QUALITY ANTENNA ROTATORS




DAIWA

Typical operating characteristics:

Power consumption	DR7500S (medium duty)	DR7600S (heavy duty)
Motor	40VA	40VA
Rotation time (approx)	24V split phase	24V split phase
Rotating torque	50 sec	64 sec
Braking Torque	500kg/cm	600kg/cm
Vertical load	2000kg/cm	4000kg/cm
Weight	200 kg	200 kg
Cable	4.5 kg	4.6 kg
PRICE (cable \$1 per m)	6 core \$189.00	6 core \$259.00

Available from your VICOM dealer

Authorised dealers throughout Australia




— Sydney 339 Pacific Hwy
Crows Nest
Ph (02) 436 2766

— Brisbane 48 6601
— Perth 321 3407
— Adelaide 43 7981

— Head Office and Mail Orders
68 Eastern Road
5th Mills Vic. 3205
Ph (03) 699 6700
Telex 36935

VICOM

ANNOUNCING A NEW COMMUNICATIONS COMPUTER!



TONO

THETA 7000E

**NEW IMPROVED MODEL
FEATURING
STACKS OF EXTRA TRICKS!**

The new Theta 7000E has all the features of the popular 0-7000, plus a lot more! Now every Amateur can enjoy the visual display of CW, RTTY, and ASCII in both transmit and receive modes. Just connect the TONO to any TV set via the antenna terminals or to a page printer from the parallel port provided. Bring up your CW speed in receiving or sending by either watching receiver-sent or from recorded cassettes.

SOME OF THE OUTSTANDING FEATURES:

THETA 7000E COMMUNICATIONS COMPUTER

Due to the most up-to-date computer technology, just one piece of equipment can now handle both transmitting and receiving in CW, RTTY and ASCII.

VHF and Composite video output provided:

Both home TV set and video monitor outputs are provided for display purposes.

Interface:

Centronics. Compatible interface enables easy connection of a low-cost dot printer for hard copy.

Wide range of transmitting and receiving speeds.

10 communication speeds for transmitting (with automatic CW speed adjustment on receive) and 8 communication speeds for receiving in RTTY and ASCII. The multiple speed feature makes the Theta 7000E ideal for Amateur, business and commercial use.

Build-in demodulator for high performance.

Three-step shift (either 170Hz, 425Hz, 850Hz) can be obtained in High Tone and Low Tone by the switch. Manual adjustment is available by FINE TUNING control.

Crystal controlled modulator.

A transceiver without AFSK function can transmit in RTTY mode by utilizing the high stability crystal-controlled modulator controlled by the computer.

Convenient ASCII key arrangement.

The keyboard layout is the same as a regular typewriter and automatic insertion of LTR/FIG code makes operation a breeze.

Large capacity display memory.

The two-page display memory contains 32 characters x 16 lines per page. Page selection is operated via the keyboard.

Split-screen.

With a keyboard command, the same page can be divided in two, the upper half for transmit and the lower half for receive. Sentences can be edited whilst receiving.

Automatic Transmitter/Receiver switch.

The transmit/receive switch is controlled by the microprocessor. (Manual operation is also available). Build-in remote control key function controls the transmit/receive switch of the transceiver.

Anti-noise circuit.

A new anti-noise circuit prevents garbled messages when there is no signal.

Battery backed-up memory.

Data in the battery backed-up memory is retained when the external power source is removed. The Theta-7000E has provision for 64 characters x 7 channels in the non-volatile memory. Data in this memory can be repeated 1-9 times from a keyboard instruction. Every channel can read out continuously. The channel number in use is displayed on the screen.

SEND function.

The SEND function sends the whole data displayed on the screen, including the stored data in channels, with an instruction from the keyboard. The message can be stopped and easily restarted.

Buffer memory.

A 32-character buffer-memory is displayed on the 17th and 18th lines on the screen. The characters move to the left ending one by one as soon as they are transcribed. Data in the channels can be displayed in the buffer.

Rob out function.

Mistakes can be erased whilst the information is still in the buffer memory. If the mistake has already been sent correcting code will be transmitted.

Stimulusless access of the memory.

Whilst receiving it is possible to write into the channel memory and the buffer memory from the keyboard. When sending from the channel memory or the screen it is possible to write into the buffer memory.

Pre-loading function.

The buffer memory can momentarily store data and release it on an instruction from the keyboard.

Channel No., Page No., and Case No.

Channel No., Page No., and Case (FIG/LTR) in RTTY are displayed in the 17th line of the screen.

CR (Carriage return)/LF (line feed) cancel function.

When receiving CR or LF they are replaced by = (equal) and (underline) respectively for effective use of the screen.

Cursor control function.

Full cursor control (up/down -- left/right) is available from the keyboard.

WORD MODE operation.

Characters can be transmitted by word groupings.

Automatic CR/LF.

While sending, CR/LF are automatically inserted once every 72 (60 or 80) characters.

Fast scan.

With a keyboard instruction, received data can be read and sent out at the same time. A cassette tape can be used as the source data.

WORD WRAP AROUND function.

In receive mode word-wrap-around prevents the last word of line from splitting in two.

Transmit/receive in ASCII mode in RTTY.

On instruction from the keyboard, the same AFSK signals as used in RTTY are transmitted in ASCII mode.

CW characters after Element.

Keyboard controlled CW identification is available if required.

MARK-AND-BREAK (SPACE-AND-BREAK) system.

Either mark or space tone can be used to copy RTTY.

Monitor circuit.

A built-in monitor circuit with an automatic transmit/receive switch enables checking of the transmitting and receiving state. In receive mode it is possible to check the output of the mark filter, the space filter and AGC amplifier prior to the filters.

CW practice function.

The Theta-7000E reads data from the key and displays the characters on the screen.

Variable CW weights.

For CW transmission, weights (ratio of dot to dash) can be changed within the limits of 1:3:1:6.

Cross-pattern checking output terminal.

Provision has been made for attachment of an oscilloscope to aid tuning. This supplements the tuning LED and audio monitor provided in the system.

Log-computer output provided.

The Theta-7000E has an output terminal for connection to a log keeping computer.

Test message function.

"RY" and "OB" test messages can be repeated with this function.

VICOM Back-up.

Supported by VICOM 90 day warranty and technical service.

\$899 incl. S. Tax

Distributed by:

VICOM

Available from VICOM dealers
throughout Australia

☐ Melf: 68 Eastern Rd. ☐ Syd. 339 Pacific Hwy. ☐ Bris. 48 6601
☐ 5th. Melf. ☐ Crowe Nest ☐ Perth 321 3407
☐ Ph. 699 6700 ☐ Ph. 436 2766 ☐ Adel. 43 7981

THE FAMOUS 2M FM MOBILE IC22S


ICOM



**1000'S
SOLD IN
AUSTRALIA**

STILL ONLY \$299

SYNTHESISED



- **IDEAL FOR MOBILE**

No digital display, easy to use on the move without looking.

- **STACKS OF CHANNELS**

22 programmable channels — 11 popular ones already done and 11 for you to program to your own choice.

- **REPEATER REVERSE**

Full reverse at a flick of a switch.

- **SUPERB QUALITY AND PERFORMANCE**

The ICOM name is synonymous with reliable communications, as thousands of happy owners will confirm.

- **COMPLETE**

Comes complete with mic, mobile mounting brackets, dc lead and comprehensive instruction manual. Backed by Vicom 90 day warranty.

- **LOW RECEIVER NOISE**

The IC22S uses a FET front end and high-Q helicalised cavity resonators. Signal gain of 90dB or more up to second mixer.

- **PROGRAMMABLE DIODE MATRIX**

It's easy to add extra channels. Just solder in the diodes!

SIMPLY THE BEST!

Typical Technical Characteristics

General: (Australian Model). Number of semiconductor Transistors 41. FET 7. IC 13. Diode 33 (Except Matrix Board). Frequency Coverage: 45-148 MHz. Antenna Impedance 50 Ohms unbalanced. Power Supply Requirements: DC: 13.8V \pm 15%. Negative Ground 2.5 A Max. Current Drain. Transmitting Approx. 4.0A. Receiving At Max. Audio Approx. 0.7 A. Squelched Approx. 0.4A. Dimensions 58mm(H) x 156mm(W) x 218mm(D). Net Weight 1.9 Kg. Channels Installed: R1-8, 40, 50, 51. Transmissions: Transmitting Frequency: 22 Channels in the 2m Band. Programmable by a diode matrix for any channels on 25KHz spacing. Emission Mode 16F3. Output Power: 10W Max. Frequency Deviation: 5KHz. Modulation System: Variable

reactance phase modulation. Spurious Emission: More than 60dB below carrier. Microphone Impedance: 600 Ohms. Input level: 10mV typical. Dynamic or optional Electret condenser microphone. Receptor: Receiving Frequency: 22 Channels in 2m Band. Modulation Acceptance: 16F3. Receiving System: Double super-heterodyne. Intermediate Frequency: First IF: 10.7MHz. Second IF: 455KHz. Sensitivity: Less than 0.5uV for 20dB Noise quieting. More than 30dB S+N+D+N+D at 1 uV. Squelch Sensitivity: Less than 0.3uV. Spurious Response Rejection Ratio: More than 60dB. Selectivity: \pm 7.5KHz at the -6dB point: \pm 15KHz at the -60dB point. Audio Output Power: More than 1 Watt. Audio Output Impedance: 8 Ohms.

**Available from authorised dealers
throughout Australia**

VICOM

Check it out at your VICOM dealer.

☐ Mels. 68 Eastern Rd. ☐ Syd. 339 Pacific Hwy ☐ Bris. 48 6601
Sth. Mels. Crows Nest ☐ Perth 321 3407
Ph. 699 6700 Ph. 436 2766 ☐ Adel. 43 7981

AMATEUR SATELLITES

R. C. Arnold VK3ZBB

OSCAR 7

Efforts to maintain AMSAT OSCAR 7 on its old schedule of operation have been successful in recent months. For those who may not remember, Mode A operates on odd days of the year with Mode B on the even days. Wednesday is experimental day on Mode X.

The tentative launch date of the British UOSAT Amateur Satellite is 13th September, 1981.

Probably the most "up to the minute" and comprehensive notes on satellite activity are found in the newsletter of the Mode "J" Club. I can only repeat some snippets from this newsletter as they are rather dated by the time they appear in AR, but I am sure many OSCAR fans must have qualified for membership of the Club and could receive their own copy — details have been published in recent editions of these notes.

Congratulations are due to Larry Roberts WB8MC, the editor of Mode "J" Newsletter, for a job well done.

Have you ever thought of exchanging your AMSAT membership during a satellite contact? If you work a station not possessing a membership number, give details of AMSAT and suggest he should join this elite organisation. The same suggestion goes for Mode "J" contacts.

LOOKING AHEAD

1980 May — AMSAT Phase III satellite.

1980 Sometime — Two more Russian Amateur satellites.

1981 September — UOSAT.


1984 A French Amateur Satellite is expected to be launched from Kourou in French Guiana on an Ariane Mission. It will probably carry two transponders, one on Mode J (up 145 down 435 MHz), the other with uplink 435 MHz and downlink 1260 MHz (this seems to conflict with the latest WARC information — Bob)

Do you realise the AMSAT OSCAR 7 has completed five years of operation? It is interesting to note that the prime load with which AO7 was launched only lasted about 1½ years.

OSCAR IN THE CLASSROOM

Bill Magnusson VK3JT who is vitally interested in the use of amateur satellites for educational purposes, has agreed to act as Phase III OSCAR Education Programme Co-ordinator in Australia. Bill has asked me to include the following notes.

"With the imminent launch of Phase III and the general upturn in interest in VHF, UHF and satellite communication, an attempt will be made in 1980 to tie together the very considerable educational possi-



SCHEMATIC 1: Spacecraft antenna placement and pattern AMSAT OSCAR Phase III-A.

bilities of the AMSAT programme in this country.

"I have been asked to act as education co-ordinator and one of my first priorities will be to compile and distribute a register, hopefully as complete as possible, of all school-based radio clubs or groups with an interest in the amateur satellite programme. A considerable amount of in-

formation of interest to such groups is already available from AMSAT and ARRL and I will be in a position to disseminate this and to act as a central source for collection and distribution of such information. I will also be making approaches through the various State education departments for advertising space in gazettes and journals and through standing com-

mittees in the physics, general science and electronic practices areas. I'm sure many secondary schools have radio clubs. Many such clubs are run by or have available a licensed radio amateur. I will be trying to show these clubs that it really is quite easy to become involved in OSCAR and that the educational spin-off is immense. It should be well within the grasp of even the most modest club to take part.

"Should anyone reading this feel they could contribute or require information, or would like to be placed on a register, they could write to me, care of Footscray Technical School, Ballarat Road, Footscray, Vic 3011".

The following updated information on AMSAT OSCAR Phase III-A has been received from Steve Place WB1EYI and should be of value to those contemplating monitoring this satellite:

"AMSAT OSCAR Phase III-A, as all previous OSCAR satellites, will receive a numerical designator once it successfully achieves orbit. At that time it will be referred to as either AMSAT OSCAR X (probably AMSAT OSCAR '9') or AMSAT X (AMSAT 9), NOT OSCAR X. The proper abbreviation will be A-O X (probably A-O 9).

The latest updates on the projected orbital parameters (these figures are still tentative) are shown in Table 1.

Revised Maximum access time

The projected maximum access time has changed. Given the new period of about 10 hours and 28 minutes, a station at 30° N latitude, for example, will have about 9½ hours of continuous access. This, of course, would be for the ideal pass for a particular station at this latitude; stations at different latitudes will have differing times. Also, certain orbits may not be accessible at all. Apogee latitude will vary gradually as it North, increasingly favouring higher N latitudes, and access times for a given location will change. Eventually, apogee drift will swing south and occur over the equator and below, favouring S latitudes.

Rate of change in apogee latitude

Immediately after firing, the projected initial latitude of apogee will be about 24.8° N lat., and of perigee will be about 24.8° S lat. The rate of change of apogee, and perigee, altitude (drift) will not be constant. The initial argument of perigee (angle in the orbital plane from the line of nodes to perigee — measured counterclockwise) will be about 210°; its rate of change will be constant at about 0.07° per day.

To determine the change in the latitude of apogee and perigee, use the following relationship (angle of inclination = 57°) (W_0 = argument of perigee)

$$\text{perigee latitude} = \arcsin \{ (\sin i) \times (\sin WW_0) \}$$

For example, ten days after firing, assuming the projected values are correct, the argument of perigee will have changed to:

$$210^\circ + (10 \text{ days} \times 0.07^\circ/\text{day}) = 210.7^\circ$$

and from this, we calculate that perigee will occur at:

$$\begin{aligned} \text{perigee lat.} &= \arcsin \{ (\sin 57^\circ) \\ &\quad \times (\sin 210.7^\circ) \} \\ &= -25.35^\circ \text{ ("—" means S lat.,} \\ &\quad \text{apogee is "+" Or N)} \end{aligned}$$

In other words, in ten days, perigee will occur about 0.5° further South, and apogee 0.5° further North. Again, the rate of change of the argument of perigee is constant, the rate of change of apogee/perigee latitude is not.

Firewheel — the primary payload

AMSAT OSCAR Phase III-A will ride piggyback", or as the secondary payload aboard the European Space Agency Ariane LQ2 mission. The primary payload is an experiment called Firewheel which will be mounted atop what ESA calls the "CAT" or Application Technology Capsule. Phase III will be mounted below Firewheel, affixed to the side of the CAT. Firewheel comprises a series of canisters, arranged around the top circumference of the cylindrical CAT, containing explosives, lithium, barium and other compounds. When exploded, these will form a visible, "glowing", steam-like cloud, enabling scientists to study the patterning of the earth's magnetic field. Phase III will be clear of the experiment before the explosive charges are fired.

Transfer orbit bulletins

During the transfer orbit, AMSAT engineers will make precision ranging measurements to determine the actual orbital parameters as accurately as possible for the critical kick motor calculations. One-way bulletins

will occasionally be transmitted near apogee to explain the status of the mission, but the satellite will not be available for general use until a short time after firing. All are urged not to interfere with this work.

Special Service Channels

Included in the Phase III bandplan are six SSCs; the correct sequencing, placement, focus and co-ordinators follow:

- L1 Scientific (formal, scheduled) N1DM — 17 kHz up from General Beacon
- L2 AMICON (computer) WA2LQO — 21 kHz up from General Beacon
- L3 NTS (formal, record CW traffic) K1XA — 25 kHz up from General Beacon
- H1 CW/RTTY Bulletin, CW Practice W1EH — 17 kHz down from Engr. Beacon
- H2 Education (schools and ham) WB1EYI — 21 kHz down from Engr. Beacon
- H3 Phone Bulletin (international) G3IOR — 25 kHz down from Engr. Beacon

All SSCs are 4 kHz wide. Send all comments, inquiries and suggestions to the co-ordinators via AMSAT headquarters.

General Beacon format

The General Beacon, located at about 145.81 MHz, will contain much useful information. Each hour will be formatted the same so that listeners will know exactly when to listen to get the information they need.

A suggested format appears in Table 2.

TABLE 1:

Parameter	Transfer Orbit	Final Orbit
inclination	17.5°	57°
apogee altitude	34,385 km	34,385 km
perigee altitude	200 km	1,500 km
argument of perigee	190.587°	210°
drift rate (arg. of per.)	0.7838°/day	0.07°/day
anomalistic period	603.78 minutes	628.8 minutes
perigee latitude	about 3.2° S lat.	about 24.8° S lat.
weight of spacecraft: 75 kg (165 lbs.)		

TABLE 2:

Time	Interval (minutes)	Duration (minutes)	Content
T0	0-1	1	CW i.d. and preamble
T1	1-3	2	basic orbital data
T2	3-6	3	CW telemetry data
T3	6-21	15	CW bulletin board
T4	21-26.5	5.5	RTTY rescans of above
T5	26.5-30	3.5	CW telemetry
T6	30-31	1	CW i.d. and preamble
T7	31-33	2	basic orbital data
T8	33-36	3	CW telemetry data
T9	36-51	15	CW bulletin board
T10	51-56	5	RTTY week's orbits
T11	56-60	4	fill to the hour with CW telemetry

CW code speed will be 15 words per minute.

Telemetry formatting

With previous OSCARs, telemetry was transmitted as raw data — numbers that were in themselves meaningless and which had to be "translated" by equations or graphs into meaningful data such as voltages and currents. Phase III, however, will transmit meaningful data that has been processed in its flight computer. During the 3 minute telemetry transmissions, 20 channels out of a possible 64 will be sent in a five number format. The first two digits will be the decimal channel number, followed by the three digit value. The user will look up a given channel number in a table in which he will be told where to place the decimal point and what the unit of measurement is. For example, 32498 would be channel 32 (decimal) with a value of 498. From the table, you would find that the value should be multiplied by 0.1 and was a measure of watts: transponder power out. The transponder was putting out 49.8 watts (this is strictly an example and channel assignments may change).

AMSAT calling frequency: 28.880 MHz (no scheduled activity but excellent source of information if individuals are monitoring. All are encouraged to check in).

The following diagrams illustrate the antenna arrangements on AO Phase III-A together with their patterns for 70 cm and 2m.

OSCAR 8 orbital parameters are forever changing and it has been difficult to predict what they may be at the time of

publication of these notes. It is surprising what a significant effect 10⁻³ seconds per orbit has when estimating times some 2½ months ahead. The predictions for February are submitted with "fingers crossed" and I hope they will turn out to be reasonably accurate — at least any inaccuracy should be consistent.

ORBIT PREDICTIONS — FEBRUARY 1980

OSCAR 7

Date	Orb. No.	Max Z	Eqv. *W
1	23845	0119	87
2	23857	0018	72
3	23870	0112	86
4	23882	0012	70
5	23895	0105	84
6	23907	0005	69
7	23920	0100	82
8	23933	0154	95
9	23945	0053	81
10	23958	0147	94
11	23970	0047	79
12	23983	0141	93
13	23995	0040	78
14	24008	0135	91
15	24020	0034	76
16	24033	0128	90
17	24045	0028	75
18	24058	0122	88
19	24070	0021	73
20	24083	0119	87
21	24095	0018	72
22	24108	0109	85
23	24120	0109	85
24	24133	0009	70
25	24145	0103	84
26	24158	0055	82
27	24171	0151	98
28	24183	0050	80
29	24196	0144	94

OSCAR 8

Orb. No.	Max Z	Eqv. *W
9728	0048	53
9742	0059	64
9756	0053	55
9770	0056	59
9784	0100	57
9798	0103	58
9812	0107	58
9826	0110	59
9840	0113	60
9854	0117	61
9868	0120	62
9882	0124	63
9896	0127	64
9910	0130	64
9924	0134	65
9938	0137	66
9952	0141	67
9966	0001	42
9980	0004	43
9993	0008	44
10007	0011	45
10021	0015	46
10035	0018	47
10049	0021	47
10063	0024	48
10077	0027	48
10091	0031	50
10105	0034	51
10119	0038	51

QRP

CW REQUIREMENT


The editorial in Oct. '79 QST seeks expression of opinion by U.S.A. amateurs that there should be no change in Article 41 of the ITU Radio Regulations. This is the article dealing with the Amateur Service. The ARRL makes it clear that no change should be made to this Article — a position maintained by ARRL for some years. Deep is this: the FCC proposed that the Morse Code requirement below 144 MHz be eliminated. "A change which is not wanted by the Amateur Radio Service is effected, and we don't like it!" "Nearly everyone is concerned over the possibility that one of the strengths of the Amateur Radio Service would be eroded if these rumors are true." Well, as everybody now knows, WARC '79 dropped the minimum frequency requirement for Morse code to 30 MHz from 144 MHz.

INDUCTION COOKING RANGES

An article in Oct. '79 QST draws attention to a new technological development in cooking appliances to come onto the market soon. AC at a frequency between 20 and 40 kHz is circulated in a coil under a smooth ceramic cooking top. When an iron pot is placed on the top (which is in the induction field of the coil) eddy currents are induced in the pot causing it to become hot and cook the food within it. It is stated that the induction range is much more economical and there is no danger of fire from oil spillage because the ceramic cooking top remains cold, moreover it is easy to clean being smooth. However, these ranges are a potential source of serious RF interference and the FCC in the U.S.A. has adopted regulations from 1.2,1980 which will apply to any induction cooking range using a frequency of 10 kHz or higher. Before any such range is put on the market certification is required that it meets certain radiation and conduction limits.

JOIN A NEW MEMBER — NOW!

BELCOM LS707 UHF ALL MODE TRANSCEIVER



BRIEF FEATURES

- * All solid state devices
- * All modes — AM, USB, LSB, CW, FM
- * Continuous band coverage from 430-440MHz
- * Provision for up to 100 fixed crystal channels

- * Power Out-Put SSB, FM, CW 10 Watts AM 4 Watts
- * Double/triple conversion receiver
- * 5 Amp Power supply available as option
- * Stand microphone available as option

NOW AVAILABLE DUTY FREE AT ONLY \$895.00

I M A R K

Pty. Ltd., 167 Roden St., West Melbourne, Vic. 3003
Phone (03) 329 5433

1979 REMEMBRANCE DAY CONTEST RESULTS

WINNER — VK5 DIVISION

	a.	b	c	d	e.	YEA PHONE						ZJ	292	YFZ	196	AJR	70	
VK1	65	180	38892	40.6	15809	DDG	2327	WT	324	MAW	119	292	YLD	259	AIE	150	R4	73
VK2	132	2035	66436	6.5	4309	ARX	2268	BDH	323	FM	118	292	ZYL	255	XH	138	ZFI	66
VK3	93	1545	59941	8.0	3428	DO	1824	ND	320	XT	118	292	AVL	253	BAK	137	AWZ	65
VK4	103	855	52147	13.7	8200	BYF	1735	NHD	317	DEW	118	292	NWH	248	YRP	136	BIS	63
VK5	175	816	98904	26.8	28539	WVT	1689	NRH	289	NJH	116	292	BRL	243	AMW	134	VCE	62
VK6	6	80	7599			DM	1590	WW	289	AJH	112	292	YIW	241	VAN	132	SCR	60
VK6A	93	462	66434	20.5	14595	NMY	1540	OH	294	OC	112	292	GJM	237	AJH	131	ZBB	59
VK9	1					BYZ	1320	DAJ	287	DAB	107	292	ZI	227	NLT	103	ACS	57
VK7A	83	184	46724	35.3	18936	WI	1236	BMX	286	NMX	102	292	BKN	220	NZ	101	BVJ	44
VK2	2		1218			NQL	1193	VJH	268	NBD	102	292	BUJ	202	AER	101	AVV	34
						BPK	1058	CH	286	NUK	101	292	BKU	182	NOV	94	YLC	28
						BDN	995	AGM	254	CF	89	292	NRW	177	JL	89	VMK	22
						DCL	937	VB	283	DDQ	87	292	NIM	167	BLI	84	YCG	18
						BXD	928	AJL	281	VCO	86	292	NZW	157	BGS	81		
						VRW	901	WA	252	VED	84	292						
						VKM	894	BRF	246	BOT	80	292						
						BAM	879	VIE	231	WB	78	292						
						DFI	856	AIC	227	LE	70	292						
						VDF	814	TK	226	NHA	69	292						
						WDJ	780	AZR	221	NHF	69	292						
						AWI	779	VIE	217	HZ	67	292						
						ATZ	767	VMJ	213	SW	66	292						
						BPR	754	VJN	205	RJ	62	292						
						DEQ	731	VDN	194	BBO	62	292						
						BD8	724	AHM	192	VBX	62	292						
						VAD	627	APP	181	BLK	61	292						
						BT3	613	GV	180	NYU	48	292						
						BQS	588	NWW	186	BYD	46	292						
						LF	581	BUT	183	VHC	46	292						
						SS	577	NWL	182	WG	40	292						
						AGS	578	MUA	176	ZVN	40	292						
						ASH	578	ALZ	175	ZLK	40	292						
						VAB	568	VBU	174	BOC	38	292						
						VBV	567	VJB	171	ASY	38	292						
						VWJ	552	DEI	168	NVO	38	292						
						ASU	529	DEV	168	BSQ	37	292						
						BPF	497	AQ	160	DBK	36	292						
						YEM	478	AIM	159	VOH	36	292						
						DEQ	462	VKM	159	ZTD	35	292						
						NZ	431	VOK	157	BHM	33	292						
						AOA	420	NV	155	AWK	30	292						
						BYG	417	BYG	152	ADW	32	292						

Col'mn,

- a Full call logs received
- b Full call licences issued (31 March 1978)
- c Total points score
- d Percentage participation of full calls
- e Trophy score (a x c / b = e)

The following details show the section and the points scored:

VK1 CW

PG	1408	CDR	98	PM	88
DH	828	RP	86	SSU/P	54
DA	442	RC	82	DS	54
FT	372	GGG/P	80	Ji	42
MW	252	BP	78	AVL	22
8DBSP	192	KA	78		

VK1 PHONE

GB	2604	RK	170	RP	436
JN	1945	AG	185	KA	436
TD	1854	■	162	BP	428
DA	1549	■	158	XU	418
NAV	1188	N/A	153	VW	405
GM	1087	ZAR	148	KP	370
NBM	1029	AYM	131	NCE	370
KB	847	ACA	118	AYL	312
OV	840	ZOB	113	ZAH	309
MX	781	DS	112	PM	278
NBC	738	ZW/P	85	RJ	271
NAT	735	MF	94	NAL	269
BR	628	JH	83	VP	284
RC	621	BB	80	NBF	283
KV	601	DF	68	Ji	260
NAS	575	EG	62	NCP	258
NGL	595	EP	52	LF	252
FT	538	ZW	52	ZT	250
RH	514	YS	50	DH	228
AW	481	GGG/P	37	8DB/P	227
RM	471	CDR	23	WI	207
NCN	471	88U/P	10	BC	193
NAM	453	M/L	9	NBS	182

VK1 RECEIVING

LF0035	R. M. Filibeart	1312
LF10042	P. Zarw	1184
LF0062	G. J. Berger	918
	J. Calles	878
LF0018	K. Ray	473

VK2 CW

SX	1214	IC	248	BYF	46
ACF	1116	ZC	222	BCC	56
EL	■	OBA	220	NAW	54
CBF	822	ABB	212	DEW	50
QL	810	NMX	158	ASY	42
BAT	718	VM	152	■	38
BMO	628	BLK	128	DR	36
II	514	JM	120	ACA	34
QF	■	PM	102	■	30
BW	434	BNL	100	ZMY	14
GT	400	BBB	74		
CO	340	IV	72		

VK3 CW

XB	1178	AMD	378	YL	134
AEW	1060	AJB	348	ARS	128
YF	788	ANI	322	AOK	98
FC	788	MJ	304	MEA	80
YK	638	AMB	290	ABA	78
DG	578	BOO	244	BKU	58
BDH	518	LV	220	APW	54
VI	480	RJ	180	FA	24
VF	438	SV	178	BYA	22

VK3 PHONE

WP	2554	BJQ	997	NEA	448
AQZ	2053	AUQ	882	BPH	436
DSH	1761	NAW	819	BRR	412
BPF	1767	GJ	738	LP	386
WVW	1624	GRM	688	VAH	363
NMI	1362	SM	673	NEV	361
NQB	1360	AYF	650	APW	357
NLO	1327	XF	641	BHRJ	337
BIR	1275	BDL	590	ARV	315
NKQ	1243	EF	586	AZA	298
BHC	1167	BOO	580	AM	286
DS	1085	NAP	567	HQ	280
■	1055	ANA	563	BOG	280
ADW	1028	AMA	542	BLV	278
DF	999	NSQ	542	BYA	274
NLS	936	ZY	463	BHT	266

VK3 RECEIVING

L30042	E. Trebilcock	788
L31203	P. Barclay	894
	N. Blake	579
L31158	K. Brown	403

VK4 CW

LV	1278	UA	408	CO	78
KX	1242	XA	388	XJ	76
GH	806	LT	280	DY	40
HH	808	JH	200	ZA	32
ARC	462	UC	198		
CG	460	YG	182		

VK4 PHONE

UX	2088	LZ	324	ZBV	103
QQ	1770	ADW	324	BF	101
NOD	1732	NXL	323	NWH	101
WIZ	1699	UG	315	DH	85
AMH	1282	NAP	315	U	94
ADA	1254	OX	305	NVS	94
YB	1238	RP	305	AEK	90
YL	1236	AEM	287	AF	87
NOP	1218	HUI	286	NCY	81
NOI	1198	AMJ	282	NGB	81
KW	1177	UC	258	RE	75
NFU	1084	ABG	246	ABB	74
ADR	1089	NTE	225	ZRO	70
AMB	1047	VV	219	ZRF	68
KD	919	FE	212	GM	62
DO	853	NQC	211	AHD	58
CI	808	NMB	208	MU	58
AAK	787	HB	205	PJ	56
TE	783	AOB	201	ZBJ	54
ACT	768	UA	193	FU	52
NUJ	757	VT	191	HZ	52
PK	758	NQ	189	AAU	51
GA	728	NKK	188	IE	49
OZ	718	EH	174	NV	48
PH	714	MA	169	A_C	47
PS	695	NJB	157	QY	41
AMO	604	NHO	156		40
ARD	600	NVM	150	NRI	37
YT	592	ABM	140	XZ	34
AG	568	ABA	139	PV	34
ACH	555	BE	136	ZT	30
RT	540	CZ	136	VU	27
AAM	482	NGJ	132	AHO	25
NTK	425	AGT	127	TK	24
NKG	398	NUH	127	GT	22
ZH	343	WT	123	NLV	19
NOM	341	NS	120	NHS	13
AUS	338	PZ	120	ARH	11
HL	335	LE	119	ZOE	11
FK	326	MXJ	105	ZSD	11
IZ	324	CY	104	ZA	7

VK5 CW					VK5 RECEIVING										VK7 RECEIVING										
JM	1284	NLC	300	KQ	84	R. Whitford					2690					BP	322	DG	143	NAD	58				
BN	1016	QR	216	ZX	84	L50340 R. A. Cunningham					536					LH	302	LR	139	IC	58				
OR	958	QQ	194	AU	66	B3C30785 D. Nelson					344					NXB	235	DL	138	RP	49				
FM	856	RT	180	JG	66	R. Dayman					112					NFR	275	ZAT	137	ZBY	36				
SW	804	FX	174	PK	52	D. Warrington					85					NJX	248	NOW	136	KS	35				
XD	856	ABB	180	NJL	62	L50122 G. Edmeades										NGR	228	NAM	124	AX	35				
LI	854	KU	116	LK	48											PS	224	ZLB	118	ZAJ	28				
HO	398	RG	84	NMQ	36											NOA	261	ZTA	102	NB	26				
															FT	199	NBI	96	MK	24					
															GF	178	KK	86	AQ	18					
															YY	166	ZAO	88	ZLD	18					
															NFJ	149	ZAG	78	ZSJ	13					
															CF	148	CT	74	ZAK	12					
															NSA	186	NKD	73	RR	12					
															AL	148	IL	86	GB	8					
VK5 PHONE					VK5 CW					VK7 RECEIVING															
CX	2552	VY	349	ZHR	114	RS 826					PD	318	BD	34	L70107 G. Mutton					2228					
GH	2123	ASA	347	NAQ	111	RU 792					PM	292	JK	26	VK5 CW										
MM	1887	ZAT	345	WU	109	ED 842					GW	246	FI	12	HA 960										
KK	1806	DL	363	WIE	107	VK 486					NFA	104	AWI	12											
WV	1997	ABW	338	NRO	107	AJ 470					GA	66	PA	10											
NTB	1347	NLS	323	ZJJ	105	HX 418					VG	64													
LF	1348	NLS	324	SE	104																				
ARC	1345	NCD	316	EQ	103																				
NX	1278	ZCM	318	DJ	102																				
ABP	1276	NAJ	314	ACE	102																				
ZH	1253	NHB	314	DF	100																				
DV	1182	AZ	312	XL	99																				
OU	1100	NHO	309	NJB	99																				
AGO	1090	NDG	307	VB	97																				
DK	1088	ZBI	304	EC	96																				
NN	1084	AJJ	301	NTC	95																				
BI	1081	LO	300	US	94																				
TY	1057	RW	294	AJM	94																				
ZK	1017	VQ	294	NON	94																				
LZ	958	ZE	284	NCY	94																				
LZ	932	ZF	278	MU	93																				
DR	928	NBG	278	YK	88																				
TS	921	NTK	274	NCH	88																				
N-E	914	SW	271	PP	87																				
ADD	887	NKZ	268	NHR	87																				
DI	848	NPF	265	EP	86																				
TZ	841	RK	287	NTT	86																				
NNC	839	NXY	285	NOC	84																				
XT	833	ZPE	263	NPB	84																				
AIC	827	ZVK	262	NJO	83																				
EN	745	NCE	261	AP	81																				
XZ	723	OM	248	NWP	81																				
NDF	719	ABR	241	ZBH	79																				
NKA	718	NP	241	KC	77																				
SN	698	AKB	237	ZJ	77																				
LN	694	OT	234	ZBV	77																				
SL	688	OW	222	GF	76																				
AMW	688	ZZ	220	GG	72																				
BW	684	ADC	219	NAT	72																				
TR	642	NMY	208	NOK	71																				
KR	633	ARV	205	IR	70																				
NON	618	EP	200	UE	70																				
FO	576	HN	198	OC	68																				
ATW	871	NVW	194	YQ	68																				
ON	668	ZRJ	193	NGK	64																				
ZJG	651	RI	188	NJO	64																				
NCL	647	GB	182	QJ	63																				
HI	644	NGA	180	DQ	61																				
ZG	638	PK	177	IO	60																				
GI	633	AQ	175	YW	59																				
FX	628	AVQ	174	ARX	59																				
CGR	628	YV	173	ZAR	58																				
NJ	616	LC	171	NKC	58																				
HL	610	NBA	167	NVA	57																				
GI	492	NKW	167	VU	55																				
NFC	488	ZJE	156	CA	54																				
NBY	482	KR	161	HW	54																				
NBH	472	NBA	157	UX	52																				
ATM	470	VE	156	ZKK	50																				
LM	447	ZBC	156	NCC	43																				
NMO	445	HIM	150	AWR	42																				
NKT	434	KH	149	NIC	42																				
IZ	429	NGQ	149	ZU	37																				
NGB	427	NEM	145	AC	36																				
BP	410	NGC	144	DF	36																				
NCX	407	N3W	142	ZIS	35																				
SS	402	HNE	142	N5I	29																				
LV	392	QV	140	QV	29																				
NHQ	399	RV	139	AKR	33																				
IT	396	ZQ	137	ZAP	33																				
ND	379	ZB	136	BTP	32																				
NEM	378	WN	134	KT	26																				
NWT	378	NRO	133	JG	26																				
A-M	378	BAG	129	RR	26																				
EA	369	NCK	129	OK	25																				
FL	359	OZ	128	RM	23																				
XI	359	JK	125	NCS	23																				
NHM	358	TW	125	ZTA	22																				
NVO	358	WC	124	TL	20																				
NAT	355	NAC	124	ZGZ	20																				
NTU	353	DM	121	RT	11																				
DH	355	YY	121	RT	7																				
NDW	352	NHC	121																						

VK6 CW					VK6 PHONE					VK7 RECEIVING														
NBU	2863	EV	523	ZCB	163	PD 2864					AN	520	NCZ	145	VK5 CW									
JP	2276	HU	505	DA	141	FS 2214					EB	503	NGU	133	HA 960									
NFI	2111	TP	502	KY	127	NFI 2111					TP	502	KY	127										
RG	2054	LP	493	YO	127	RG 2054					LP	493	YO	127										
AO	2047	PC	420	GL	125	AO 2047					PC	420	GL	125										
MF	1771	EO	401	ZLT	126	MF 1771					EO	401	ZLT	126										
ER	1744	NEY	401	JL	104	ER 1744					NEY	401	JL	104										
YL	1721	FI	400	AWI	87	YL 1721					FI	400	AWI	87										
IC	1673	YG	388	AT	84	IC 1673					YG	388	AT	84										
ED	1633	RL	383	NDK	87	ED 1633					RL	383	NDK	87										
KQ	1547	BD	375	NHR	83	KQ 1547					BD	375	NHR	83										
NGA	1145	SH	374	NDY	83	NGA 1145					SH	374	NDY	83										
WV	1053	XC	362	NE	75	WV 1053					XC	362	NE	75										
GW	1041	GA	342	OK	73	GW 1041					GA	342	OK	73										
NGV	1012	OX	337	WI	72	NGV 1012					OX	337	WI	72										
UN	872	YE	336	YM	71	UN 872					YE	336	YM	71										
UT	858	NGC	334	WZ	68	UT 858					NGC	334	WZ	68										
HW	834	CM	322	SO	63	HW 834					CM	322	SO	63										
NGR	821	LV	321	ZKI	90	NGR 821					LV	321	ZKI	90										
WT	810	HAG	289	GI	58	WT 810					HAG	289	GI	58										
NFA	810	ZIT	289	GN	58	NFA 810					ZIT	289	GN	58										
XJ	801	CR	270	ZC	58	XJ 801					CR	270	ZC	58										
DY	800	HE	259	GC	55	DY 800					HE	259	GC	55										
XP	754	ZZ	256	NCO	55	XP 754					ZZ	256	NCO	55										
JK	748	UA	248	NEA	55	JK 748					UA	248	NEA	55										
NGH	726	UH	243	ZHU	44	NGH 726					UH	243	ZHU	44										
JK	711	NGB	220	FM	41	JK 711					NGB	220	FM	41										
PG	827	BE	219	LG	35	PG 827					BE	219	LG	35										
FE	810	TU	218	NGJ	32	FE 810					TU	218	NGJ	32										
WL	698	QR	211	JY	17	WL 698					QR	211	JY	17										
YF	682	OD	198	ML	15	YF 682					OD	198	ML	15										
NHA	588	NDV	178	ZCU	11	NHA 588					NDV	178	ZCU	11										
NHK	578	ZGA	176			NHK 578					ZGA	176												
VK6 RECEIVING					VK7 CW					VK7 PHONE					VK7 RECEIVING									
L60030	F. H. Price	1702			L60036	K. Dean	1703			L60037	L. Baxter	1704			L60038	G. Mann	1705							
L60039	D. Robson	1635			L60040	D. Handcombe	1714			L60041	J. Grandawit	183			L60042	D. Handcombe	174							

Log presentation has improved dramatically this year ably supported by some divisions distributing well designed front sheets to entrants.

Especially noteworthy was an entry from Frank VK2Z1 who is totally blind. His log was a verbal one on tape and I was delighted to be able to score his entry for him. Al but one contact was through an Oscar satellite.

From my own observations during the contest there was a very friendly atmosphere evident but it's a bit slow through with all entries! The comments and threats I received, with a small minority of ops, showed some amateurs in a very poor light. I cannot accept any blame where an entrant fails to read the rules before entering a contest.

I will however, apologise for being a little late with the results but I was absent from Orange due to work commitments for the best part of three months from September.

The 1980 'Friendly' contests will be even better and bigger than before and I am looking forward to an even larger number of entries. Thank you for supporting your divisions and the memory of those who paid the supreme sacrifice. ■

NOVICE NOTES

BEWARE THE SWR METER

For many years standing wave ratio has been the yard (or is it metre) stick when antennas are discussed. This has been accentuated since the advent of CB. Many CBers would be happy with a piece of wet string if it showed an SWR of 1.1 at the end of a 50 ohm line.

The only thing that an SWR meter will tell you is how close the match between the feeder line and the antenna feed points is, it will not necessarily tell you if the antenna is resonant. If the antenna feed point happens to be the same as the impedance of the feeder line, the SWR meter will give you the right answer, i.e. that the antenna is resonant.

However, in practice, the antenna may have anything but the right feed point impedance. Indeed the rule is generally that it is not. Let us consider the quarter wave vertical for a moment fed with 50 ohm coaxial cable. With a very good ground plane, this antenna will have a feed point impedance of about 35 ohms at resonance. This will exhibit an SWR of 1.4 to 1. Often the SWR is lower, around 20 ohms or so resulting in an SWR of 2.5 to 1. Altering the length of the antenna to get the SWR down will shift its resonant frequency and decrease its efficiency.

You will ask: what about losses due to high SWR? A study of a chart in the ARRL Handbook in the chapter on transmission lines showing losses against SWR, will reveal that the SWR has to be quite high, 6 to 8 to 1, before these losses will cause concern.

Your next question is: how else do I do it if I can't trust my sacred SWR meter? The answer lies in three instruments. The

THE MAN BEHIND THE MICROPHONE



first is a tape measure. If you are erecting an 80 metre dipole, measure it, first of course, find the correct length and here again, there are charts in ARRL Handbook. The second instrument is that sadly neglected field strength meter. After all, you are only really interested in making your antenna radiate the best signal strength that can be achieved. The lowly field strength meter will do just this, indicate the relative radiation directly on the meter — and with no ifs or buts.

The third instrument is an antenna impedance bridge. This will tell you two vital values — the resonant frequency and the feed point impedance of your antenna. There are a couple of instruments on the market for about the same price. The Palomar RX noise bridge is the better of the two as it will also give the inductive or capacitive reactance of the antenna. With this instrument we can also determine the impedance.

Submitted by
Denn's Breitkreuz VK4ZEW/NMK ■

CQDX GROUP REFORMED

Owing to internal problems the CQDX Club has been reformed. Irresponsible and selfish behaviour on the part of a minority of the members, and the fact that the hams in the group have now found that they have little in common with the CB element, caused the whole concept of the club to be reformed.

It must be pointed out that though the CBers in the club were amongst the most responsible of the members, there was little to offer them once those who wished to attain amateur status had done so.

MAN BEHIND THE MICROPHONE

Many stations recently worked VK2DFM alias Konrad HB9ARQ on his recent visit to Australia. Konrad hails from a small village in the eastern part of HB9 near Lake Constance and the Austrian border. He is QRV with an FT200 and tri-band beam on 10-15-20 metres and on RTTY with a modified model 25 teleprinter. Konrad enjoys activity on VHF and UHF with 15W SSB into a 10 element yagi on 2 metres and on 432 MHz using a 28/432 MHz transverter into a 19 element long yagi. ■

We have issued a new certificate and an honorary committee comprising VK3s NDO, NNR, NOA, NNY, NAC, VEW, VGO, NDO.

So far these amateurs are the only members of the new club. Three or four former members are being approached to rejoin, and a couple of others have been excluded.

The group is now strictly an amateur DX group. I am acting as honorary secretary but there are no other official officers and no dues other than THE WILLINGNESS TO CO-OPERATE WITH EACH OTHER.

The new rules are simple . . . go all out for DX by all means, but never forget to help others whilst you are doing it. The code set down by Paul M. Segal still applies.

In short . . . give your mates a go . . . an old Australian tradition that seems to be less in evidence these days.

From Trevor C. Reid VK3NNR. ■

VHF-UHF

An expanding world

Eric Jamieson, VK5LP

Forrester, S.A. 5233

AMATEUR BAND BEACONS

Freq.	Call Sign	Location
50.005	HA4HJR	Moniera
50.008	HY1RO	Brazil
50.010	HL8TG	Seoul
50.023	HN2PR	Haiti
50.025	BY8RC	Jamaica
50.028	Z8PHW	South Africa*
50.030	Z8ZVHF	Gibraltar
50.038	HC1JX	Quito
50.038	KL7CQJ	Anchorage*
50.038	FYTHF	French Guiana*
50.040	Z8VHF	Edenvalle
50.040	W8MHZ	San Diego
50.048	VE6ARC	Alberta
50.050	K8PV	San Francisco
50.050	Z8ZE	South West Africa
50.050	Z8ZLN	South Africa*
50.050	VE8NAB	Alberta
50.055	W8PEF	Hinola
50.060	PY2XBL	Sao Paulo
50.068	W8ZML	New Orleans*
50.070	W8KMA	Arizona
50.075	KJ3/4	Columbia (repeaters)
50.080	W1AW	Connecticut
50.080	T12NA	Costa Rica
50.088	VE18IX	New Brunswick
50.090	W8JRA	Los Angeles*
50.090	W8FJA	Ohio
50.098	K7CHZ	Arizona*
50.100	Z8HVB	South Africa*
50.101	F08DR	Tahiti
50.103	HB4JH	Ohio*
50.104	KH8EOJ	Pearl Harbour
50.110	K8BJH	Guam*
50.110	J01YAA	Marcus Island
50.110	K08RO	Japan*
50.110	AL7TC	Antarctica*
50.498	SB4CY	Cyprus
51.002	ZL1BPW	Auckland*
51.899	YJ2BP	New Hebrides
52.100	W0C8C	Cassy Base
52.150	VK8KK	Wesleys*
52.200	VK8VF	Daher
52.300	VK8RTV	Perth
52.350	VK8RTU	Kalgoorlie
52.400	VK8RTW	Launceston
52.440	VK8RTL	Townsville
52.450	VK8ZW	Sydney
52.500	J431GY	Nagoya
52.500	ZL1VHM	Palmerston North
52.510	ZL1MHF	Mt. Clelie
52.550	VK8RTW	Albany
52.900	VK8RTT	Carnarvon
53.000	VK8VF	Mt. Lofy
54.010	VK8ZW	Sydney
54.498	VK8RTT	Mt. Newbulla
54.475	VK8RTA	Canberra
54.500	VK8RTW	Albany
54.600	VK8RTT	Carnarvon
54.700	VK8RTG	Vermont
54.800	VK8VF	Mt. Lofy
54.900	VK8RTT	Ulverstone
55.000	VK8RTV	Perth
145.100	ZL1VHF	Auckland
145.150	ZL1VHF	Wakato
145.200	ZL1VHF	Wellington
145.250	ZL1VHF	Manawatu
145.300	ZL1VHF	Christchurch
145.400	ZL1VHF	Dunedin
145.400	ZL1VHF	Braemar
145.475	VK8RTW	Ulverstone
433.000	ZL1VHF	Wellington
433.150	ZL1VHF	Wakato
433.200	ZL1VHF	Christchurch

433.250 ZL1VHF - Manawatu

145.700 ZL1VHF - Wellington

* Denotes attended operation

No changes to the beacon list this month, other than to include the attended operation beacon provided by David VK5KK. This has been heard over a wide area on 52.150 MHz, currently it is signing VK5KK with FSK, about 25 watts to a 3 element beam pointed north, and is located at Wathles about 60 km north of Adelaide, at David's GTH.

There are a number of other attended beacons operating in the U.S.A. but I don't propose listing these unless important. Full time beacons will be given priority in the very long list now being provided.

The correct frequency of the Geelong beacon when in operation will be 52.330 MHz, call sign VK3ROG. According to the Geelong ARC Newsletter, the frequency was determined with the WIA "Band Plan" in mind, which has been so arranged for beacons to operate between 52.3 and 52.5 MHz. The second figure after the decimal point is to indicate the State, e.g. VK3ROG on 52.330, the second 3 represents VK3. VK2 would be 52.32, VK7 52.37 etc.

NEWS FROM HONG KONG

Also from the Geelong ARC Newsletter is news of a recent QSO between Mike VK3ASQ and Tony VS3EE on 10 metres during which the following information was exchanged. The Hong Kong allocation is 53.050 to 51.150 plus 52.025 + 10 kHz (CW) and 52.100 + 10 kHz (SSB). Power Max 1333 watts PEP (50 watts AM). VS3EE runs low power to a GP aerial. VS3EE 50.110 low power VS3EE calls CQ (Voice via VOX) for 1 minute, listens for 1/2 minute when conditions are good, and monitors 28.490 MHz when on 8 metres.

NORTHERN HEMISPHERE ON SIX

B.I. WOJO sends a lot of information from his column in QST re six metres. Despite the approaching winter in the north, the band seems to have remained open almost continuously to exotic places. What follows is a condensed version of B.I.'s information, which is too vast for this column!

What took place between 15-10 and 15-11-79 as this is being written, all but eclipses those outstanding records from 20 years ago. Started 18-10 when VE8 worked JAS. A big day was 20-10 when VE1AVX lists 14 QSOs via the 28-30 MHz route to Europe, as well as a two-way contact with EI2W. VS8WZ was still able to send 50 MHz. On 21-10, VS8WZ worked 22 stations in Europe crossband, including SM7PU with G's and DLs making the rest it has been noted as a result of these contacts that the strongest signals on 10 metres are not necessarily the strongest signals on 6 metres!

"But that was only the beginning! Almost day a path existed to Europe from about 1300Z, followed a few hours later with transcontinental openings right across U.S.A. EI2W and ZB8SL are the only ones on 50 MHz in Europe and these have worked right across U.S.A. to W8! Not bad for a barefoot FT20B! Active European countries include G GM GW DL EI ZB2, SM, LA, HB, PAO, OK and EA. SB4CY beacon heard, but no sign of SB4Z4.

"Another beacon that has been driving everyone crazy is that of FYTHF in French Guiana. The 50.038 MHz FSK signal from this station has been received many mornings, to over 59, but the operation is seldom available for contacts. Other than to HC1JX north-south contacts have been rare, thus NP2XPW (KZ8NW) failed to work all U.S. states before departing the Canal Zone on 12-11. John HC1JX has 45 States to his credit!

"If 6 metre stations are scarce in Europe because of allocations, and in South America because of lack of propagation, there is no scarcity in the direction of Japan, e.g. between 2310Z on 2-11 and 0120Z on 3-11 N5CT worked 83 JAs plus HL9TG! At the same time at least one U.S.A. station has worked more than 700 JAs and going for the WJJA Prefecture Award! Reports of working 40 to 50 JAs are common. 5-11 and 6-11 provided a good opening to Alaska and many stations got their 50th State. The opening was so wide spread that WL7ACY contacted 270 stations in 45 States! The following day propagation opened to

KH8 from as far away as VE1. KH6 AA notes working over 100 stations, some using his IC502 and whip antenna! KX6AO was worked from the Washington area to provide a new country KX6DX at Guam also worked.

"The conditions were so good during mid November that stations like WA2CAN worked several west coast stations with a IC502 and whip while W3IP worked a W8 with 20 m.watts and a dipole, and WA1QD made a mob to crossband contact with G37VB. In summary, it has been wild, and continues to be, and will possibly surpass even 1958. We're having fun!

It certainly reads like it. Our only hope is the something akin to these conditions will come to the Southern Hemisphere during March and April. If it doesn't it will set another pose in the history of propagation as to the differences between the two hemispheres. Our misfortune is that we have no land areas akin to that of the Japan to U.S.A. path with large masses of interested six metre operators. We have Africa to the west with limited six metre interest and South America to the east further away and with interests unknown, particularly on the west coast. Most interest from that continent seems to be the north-south path to the U.S.A. and that from the eastern area of the continent. But let us not give up hope yet!

SIX MONTHS ON SIX

John VK8ZBU has done some researching and provides the following to sum up the six metre activity during the last six months of 1978.

June and July provided a few weak signals, the 'drought' broke briefly on 13-8 when VK3AMK, VK3VD and VK3ZTK were worked, between 0300 and 0350Z. August and September were not very productive, only brief and weak openings to VK4.

Things improved a little in October. Roger VK8ZRT in Adelaide Springs was 5 x 9 at 1240Z on 26-10, also Graham VK8ZVV earlier 5 x 9. Considerable solo activity was noted between 1-11 and 13-11 with a lot of signals. JA9QDM and VK4ZAA in Brisbane being only brief contacts until 15-11, when a good opening to VK7 occurred 5 x 9 contacts taking place with VK7MC VK7ZG, VK7ZYT, VK7VTW, VK7AE VK7BC VK7LZ and others, from 0800Z.

"The following day 15-11 VK4ZAY and VK4ZNG announced the presence from Townsville at 0300Z, then followed VK4ZAY VK4UX VK2VC, plus another group of VK4s, ZL2CQ and ZL2BPO. Conditions mainly unstable with considerable QSB. Quiet until 25-11 when Neville VK2QF at Mudgee was worked 5 x 9 at 0442Z, then David VK4UX. On 27-11 Townsville stations again 5 x 9 into Adelaide. VK4ZAY, VK4ZNG and VK4XZ around 0700Z, later VK4ABP (ex VK4ZBB) at Longreach was 5 x 8 at 0725Z, then at 0730Z band opened again to Townsville. Barry VK4ZBJ reports an increase in 6 metre activity in Townsville with about 12 stations able to work on the band, at least 7 of whom have already been worked. I suspect this year, the June 'pall' to Rockhampton has not been in good shape during the openings to the more northerly areas, perhaps it is undergoing repairs or clearing.

Generally improved conditions due to less solar activity produce some good signals on 28-11 - opening at 0300Z and continuing until 0800Z available were the following Gary HL9TG, Noel 289GA, Bill ZL2CQ, Brian ZL2BPO, JA7MEV, Barry VK4ZBJ, Joe VK4JH, Jan VK2ZIO, Adrian VK2YHU Phil VK8ZZY. Also on this day GQ VK5RO hit 5 x 8 air down and worked 52 Japanese stations! JY8PD was reported as heard by VK5ZJ and VK5ZBU though JY8 not worked in Adelaide.

Following two quiet days, on 3-12 good reports from VK7 and VK2 preceded an interesting opening on 4-12 starting at 0700Z with VK2BHD and VK1RK, plus many other very strong VK2s. At the same time extremely strong signals received from Gippsland VK3 stations into Adelaide. VK3CCM and VK3YKA. During this opening ADI VK60D could be heard on backscatter from Carnarvon working into Sydney. Also heard east of VK6, finally at 1100Z he worked into VK5.

On 5-12 VK8ZZZ VK8ZKT and VK8ZTF were worked then VK4ACE. Den's a new station at Mt Isa called in around 0800Z. At 1250Z it opened

to the regulars in VK7. On 6-12 and 7-12 only opened to VKACE and the Townsville gang, and on 8-12 to VK7 again, plus VK5CQM. On 10-12 very quiet during day but open to the VK7s again at 1230Z, with just enough time to say "Good evening before the band shut for the night". With few exceptions conditions were such that signals would reach the 9 metre and disappear. The Japanese near stations were weaker, though fairly consistent at times.

On 11-12 daylight hours very quiet, one pleasant contact was with Lance VK5ZBC, the first in many years, the QSO only with VK5RO was with "Adult Modu" with excellent signals all round!

12-12 0510Z VKACE followed by VK4JH, plus Graham, band being open until 0742Z to VK4. At 0850Z Graham VK8GB heard in QSO with VK4 but weak in Adelaide. VK4 worked VK3, and VK4RO's VITTY good copy on 52.085. 0815Z VK5ZOR worked VK7ZLB, at 0904Z Ray ZL2KXT worked several VKs at 8 x 9. At 1030Z VK4 to VK7.

13-12 Townsville beacon 0500Z, followed by Hal VK4DO chasing Ross Hull numbers, at 0636Z to VK2ZF, 0736Z VK4ZTV, then Bill VK4ZWH and John VK4JF VK4ALM and VK4ZAA. At 0918Z Geoff VK4JF heard calling 1, then he was worked in Adelaide 5 x 9 0845Z, and attempts made to hear Geoff's two metre signal. Considerable activity between eastern States and Z.

14-12 Nothing until 0900Z, then VK5AMK worked Tony VK5ZB at Mt. Isa then back to VK5RO, VK5OK, VK5OM, VK5ZED, VK5KZ and others. Beacons from VK2, 4 and 6 during opening.

Thanks for the fill-in up to this date John, which now allows me to continue with some information to conclude the chapter from my own log.

18-12 VK4ZWB at 0443Z and VK4ZBJ at 1128Z, nothing else. 19-12 2305Z VKACE 5 x 9. Continued to fade the fingers until 23-12 when VK4ZLB came in really early at 2337Z, followed by a string of other VK4s and VK2s, but the VKs mainly confined to the far north area. 0120Z 19-12, at 0200Z a station in fact was just had to try 2 metres with him, but the absence of any short skip at one indicated the MUF was not high enough. At 0518Z J1ERQ heard the first opening to JA for some time, this time as led by Es. JAs were mainly 5 x 9 and covered JAI, 2, 7, 8 areas.

Of particular note on 22-12 were very strong (well over 50) signals from Japanese stations on 10 Mhz, but not reaching 20 Mhz. The JAs were working themselves via a strong Es opening in their own country — It was interesting to hear them calling the J or call areas Hal, VK4DO reported working 1587 JAs from February to November 1979! Incidentally, the JAs on 23-12 worked in VK1, 2, 3, 4, 5, 6, 7, 8 and 9 as far as we know, with signals 10-12 dB below the strongest. Not many call areas left for them to work that day!

24-12 JAI to 9 areas, VK4ZAA, and VK8GF, plus VK5BXT advising he will be shifting to Sydney from Moree in 1980. Speaking to Graham VK8GB on 28885 alternate frequency, he advised Brian VK5VV on his four 2 metre beams in a recent storm, and that Brian would be going to P29 (Rabaul) for a period of 3 years during 1980. Graham advised that 2, 3 and 4 had been worked from Carpent's Pass, plus P29 beach. He was hoping to work the Balli DX-Operation during the next few days up to 5-1-80. The VK8VB beacon is at present running low power since the storm.

25-12 Started off a bit slow, probably everyone eating Christmas meals. At 0736Z opened to VK4, then VK3ATN backscatter at 0805Z. At 0847Z VK4Z01, 0858Z VK6KZ, 0924Z VK2ASZ plus others, 1104Z VK4VX again on backscatter, also VK5BHD, then just to complete the day Aub VK5XY in a A-bay worked on 144.050. Also noted that HA4PT worked VK4JB at 1645Z for first H4T to VK4 contact. I am told.

26-12 Early start at 0135Z to VK4DO, still changing numbers, gave me 580741. At 0142Z VK8GF so strong again that 2 metres had to be tried! 0204Z VK4ZBI and VK4ZTions interspersed throughout the day. At 1031Z Report received that Lat VK3ZBJ had heard a VK8 (96ZF) in Melbourne on 27-12. 27-12 Open to VK4ZNG at 2333Z 5 x 9. Worked had a spell until 29-12 when Joe VK4JH

came through 5 x 9 at 0905Z, then VK4ZBJ, the remainder of the day was a rest period for Es!

30-12 opened early with VK4ZLS at 0407Z, then an interesting set of conditions produced very strong signals from VK3 northern areas from 0500Z, with VK3AMP, VK5YNN, VK3OT and VK3ATN predominating. Later Ken VK3AOK was heard at 0130Z at 5 x 4. These short skip conditions caused the VK5 stations to occur on to 2 metres before Es were bringing in strong signals from VK4 at the same time, but no success. Ted VK2ARA was grabbed at 0145Z 5 x 9. Open to VK4 for most of the day, at 0942Z VK8GF 5 x 9 again, followed by 5 x 9 signals from VK2ZKO, VK6ZED, VK8BV, VK5RO, VK6ZZ and others. At 0930Z observed VK4ZJB worked VK8WD and others, 5 x 9 reports. TONY VK5BV advises he could be on 432 Mhz soon.

2-1-80. Probably the last of any worthwhile Es for this period, opening at 2318Z to VK2AS1, VK2ZRU and VK2BHO. John VK2BHO almost always alerts us the band is open because his strong CW signals herald the opening! At 1148Z VK7ZF and VK7ZTA, and the same two stations again at 1233Z. The long "Good-night" Lat VK4ZAA worked VK5BXT, and VK3J worked ZL on 31-12. Also a report from Gerry VK5ZZZ that the DX-petition to Balli, YB9X for work 160 JAs on 8 metres up to 2-1 but no VKs — that's not surprising considering the lack of Es from the Darwin plus area this year.

SIX METRES FROM SUNBURY

A newcomer to six metres, Graham VK8ZOS, has been thrilled with his working to date, and I can understand why. On 10-10 he obtained an IC50Z, and the following day had his first contact to JA from his car, using the IC50Z barefoot to a whip antenna. When I think of the years to look me to work my first JA ... SLP. At home Graham runs the 502 into a 25 watt linear and a beam antenna with 8 dB gain. On 24-11 mobile between 0840 and 0845Z, worked VK5YA, VK5ZDR, VK5RO and VK5ZPE the latter up to 5 x 8 in the bandgap! From the home shack on 3-12 worked a string of VK2s plus heard VK3OT and others. 4-12 VK4 barefoot. And so it goes on.

Good luck Graham, hope you passed the CW in November, and also hope this note won't mean you will forsake the VHF bands!

A LOOK ON TWO METRES

One might be forgiven for thinking there is no two metre activity with so much happening on six metres, but this is not the case. Looking across the country, I now confirm via the VK5 VHF Group Bulletin that a new two metre internal record has been established there between Andy VK6OX in Carnarvon and Aub VK5XY in Albany, on 144.100, during October or Nov. CW and later to be repeated on SSB on 2-11-79. Distance 1160 km. Perth stations were not reported, but the Carnarvon beacon was VK5RTT on 144.600 Mhz.

VK5CK STIRS THE VKs

From his hilltop location near Piccadilly in the Mt. Lotly Ranges, Dave VK5CK using a pair of stacked 13 element beams (a 15L and a 20L) with 50 watts has certainly been stirring up the VK3s in all directions. The following details are given in the hope that VK3 won't despair that their efforts go un-noticed, but do remember there are other VK3s available too, but not from such super location, therefore, they will probably be weaker!

18-11 starts off this saga, most contacts unless otherwise noted have been on 144.1, or thereabouts, and signal reports mostly the same both ways. So our old friend Roy VK3AIV hits the receiver at 5 x 9 1-1, and the same again on 19-11. VK3AIV 5 x 9, VK3ZL 5 x 2, 28-11, VK5ZHP 5 x 2, and heard a VK7 working a VK3. 27-11, VK3AXV 5 x 8, same again 28-11, 1-12: VK3XY 5 x 9, VK3XTN, VK3AIV both 5 x 9, VK6ED 5 x 1, VK6NL 5 x 1, heard VK3ARB 6-12 VK3XY 5 x 9, 18-12 VK3AXV 5 x 9, 21-12 VK3AKP 5 x 7, 22-12 VK3ZSQ 5 x 9, VK3BVF 5 x 4, VK3ZHP 5 x 1, VK3ZL 5 x 9, VK3YV 5 x 9, VK3YV 5 x 1, VK3XV 5 x 7, VK3AXV 5 x 9, plus a brief CW contact with K3AUU 5 x 1.

25-12, VK3ATN 5 x 5, VK6WG 5 x 5, VK8BE 5 x 5, VK5AXV 5 x 9, VK3ATN 5 x 7, VK5OK 5 x 5, 26-12 VK3YPD 5 x 1, VK3AXV 5 x 8, VK3YH 5 x 2,

VK3ZBJ 5 x 5, VK3ZE 5 x 7, VK3BFV 5 x 4, VK3ATN 5 x 5, VK3YLH 5 x 5, 29-12 VK3ATN 5 x 3, same on 30-12. And that sort of thing is still continuing!

It is interesting to note that daily contacts both early morning at 2100Z and at night 1100Z have been made between a number of VK5 stations and VK3ATN on 144.100. Signals for some reason or cause have been heard in the morning but not always there. Those participating have been VK5CK, VK5RO, VK5ZDR and VK5LP, occasionally others. Most reports have been from 4 x 1 to 5 x 3, with somewhat stronger signals at 5CK 432 Mhz signal! have been heard from time to time between VK3ATN and VK5.P, but only weak, on CW.

OTHER TWO METRE NEWS

Perth beacon VK8RTV copied in Adelaide 1000Z on 18-12 at 51. New Albany stations on 2 metres are VK5RO, VK5ZKJ and from Darnack further west VK8NL. On 14-12 Wayne P292W worked into the 2 metre repeater at Townsville, later made contacts via Ch. 50 and on SSB. 25-12 VK8M2 heard VK5VF beacon on 144.800 on 0830Z, so it looks as though the path on 2 metres to Perth could be just around the corner once more. VK3ATN worked four VK3s on 432 and also VK3ACH on 1295 Mhz, CW both ways. This latter contact a bit difficult as VK3ACH was keying his FM carrier. ... 2-1-80 VK3ATN worked VK5ZDGW in Griffith who had an IC202 to 5 element beam at 15 feet. ... Roy VK3AIV runs 80 watts on 2 metres, very fine signal at VK5.P. QTH ... 18-12, to 18-12 VK3ATN worked 432 Mhz. ... VK3ATN worked 432 Mhz here at SLP, do very well on 2 metre working backed up with the masthead pre-amplifier I can work anything or anyone I can hear.

TRouble DOES REPEATER

From the "Propagator" comes this month's bad luck story: "The Wolongong repeater is on Ch. 6. First a savage storm caused damage to the receiver, transmitter exciter, and the control unit. Five transistors had to be replaced, causing damage had not been worse, causing some grief. The vicinity of the transmitter building had been burnt by lightning. A large tree nearby had been burnt on one side.

"Two weeks later another storm took its toll of transistors, this time in the control unit.

"Last week's hailstorm which hit Sydney had its epicentre in Robertson. The force of the hail tore stations in the top of the transmitter building, allowing water to penetrate. The water got into the decoder for the auxiliary receiver used for the relay of the Sunday broadcast. A special ground stake has been installed in an effort to reduce currents in the landline due to surge currents from the lightning".

Apart from a gale smashing the whole assembly there doesn't seem much more could go wrong with the installation. Let's hope your troubles are now behind you, boys.

SECOND ARRL MEET COMPETITION

Gerry VK5ZZZ sends me a copy of the results of the second competition, conducted on 144, 432 and 1295 Mhz, with world-wide participating stations. It was won by K1W6E who scored 70,000 points, heard 47 other stations and contacted 39 of them, on 144 Mhz only and using a 160 element collinear 103 stations from everywhere participated, the average QSO for single operator stations was 13.1. The set-up at the winning station consisted of the 160 element collinear fed with 778 helix, a 3N111 MOSFET preamp mounted at the top with a 4 dB coupler, figure, hornbeam converter and 75A3 Hornbeam transmitter used 6306-4X350A-877 running 1000 watts. Next year they plan a bigger and better antenna.

Number two position went to WB5EUA, one of the few with 144 and 432 capab. He's preamps both use DXL 3501A GeAs FETs with 0.5 dB noise figure. The top 432 Mhz honours went to R6BT who used sixteen 21 element yagis, as HP HET110. Gary FET pair with 0.3 dB noise figure, and a pair of 4X250R.

Planned to see Chris VK5MC was able to participate, using his 6.6 metre dish to run up 3600 points with 6 stations heard and worked.

Some stations are very well set-up when one peruses the list, I note 2E5JJ has the 10 metre dish working, whilst JA6DR has a 12 metre dish.

OPPORTUNITY to obtain back copies of AR

To make space in the new executive office it is proposed to deliver for paper recycling all EXCESS COPIES of AMATEUR RADIO accumulated from MARCH 1972 to DECEMBER 1977 inclusive.

Anybody interested in specific issues should apply at once to

PO BOX 150,
TOORAK, VICTORIA 3142
with lists of requirements and
PAYMENT OF 30 CENTS
per copy to cover postage and
packing.

Regrettably some issues of these ARs will not be available, being out of print. Orders will be processed as time permits so some delay in despatch must be accepted.

"WILLIS" AIR-WOUND INDUCTANCES

Take the hard work out of Coil Winding, use — "WILLIS" AIR-WOUND INDUCTANCES

No.	Turns		B & W Equiv.	Price
	On Tech	L'gth Inch		
1.08	1/2	8	No. 3002	99c
1.16	1/2	16	No. 3003	99c
2.08	3/4	8	No. 3006	\$1.16
2.16	3/4	16	No. 3007	\$1.16
3.08	1	8	No. 3010	\$1.40
3.16	1	16	No. 3011	\$1.40
4.08	1	8	No. 3014	\$1.56
4.16	1	16	No. 3015	\$1.56
5.08	1 1/4	8	No. 3018	\$1.75
5.16	1 1/4	16	No. 3019	\$1.75
8.10	2	10	No. 3907	\$2.52

Special Antenna All-Band Tuner Inductance

(equivalent to B & W No. 3907, 7 inch)

7" length, 2" dia., 10 TPI Price \$4.36
Reference A.R.R.L. Handbook, 1981

Willis PI-Coupler Unit — \$23.95

Stocks of Transmission Cables, Insulators and Hard Drawn Copper Antenna Wire

Write for range of Transmission Cables

WILLIAM WILLIS & CO.
PTY LTD

Manufacturers and Importers

77 CANTERBURY RD., CANTERBURY
VIC. 3126 Phone 838-0707

A Call to all
holders of a

NOVICE LICENCE

Now you have joined the ranks of Amateur Radio, why not extend your activities?

**THE WIRELESS INSTITUTE
OF AUSTRALIA
(N.S.W. DIVISION)**

conducts a Bridging Correspondence Course for the AOCIP and LAOCIP Examinations

Throughout the Course, your papers are checked and commented upon to lead you to a **SUCCESSFUL CONCLUSION.**

For further details write to:
**THE COURSE SUPERVISOR,
W.I.A.**

P.O. BOX 123,
ST. LEONARDS, N.S.W. 2065

One wonders at the mechanical problems that must confront stations like YU2RCC who use sixteen 23 element yagis on 432 MHz — and the complexity of feeding the monster! Even K2CR heard one station on his single 15 element yagi on 2 metres! And what about W4WV who ran up 12000 points via 8x antenna 46 element J means!

THE EQUINOX

A few stations around with some very high scores, but the facility of being able to commence at any number up to 1000 makes some of the early high numbers rather suspect. I note VK3ATN has been making a good effort to gather numbers and using several bands to do it. He has managed to stir up some interest in VK5 to get some stations on night and morning at least on 52 and 144 to exchange numbers, but the conditions have been fairly poor so it has been a struggle at times.

In an effort to ensure the Contest continues I hope those operators with lower scores will send in a log particularly as the Contest Manager has suggested a photocopy of your log will be acceptable — this to me is a very sensible departure from previous requirements.

THE EQUINOX

Those keenly interested in six metres will be looking forward to the March/April period in particular in the hope we may have a chance to share in some of the outstanding conditions already enjoyed by stations in the Northern Hemisphere. It is clear that March/April last year was better than September/October last year, and in the Northern Hemisphere it is the other way round, September/October seems to have been superior to the earlier equinox. This seems to suggest conditions are more favourable during the autumn than the spring, but only time will tell!

Just a few suggestions which might help to pave the way for an increase in exotic contacts:

(1) If you can monitor between 30 and 50 MHz watch for a rising MUF which will be shown by overseas commercials becoming apparent in that

area. Even two-way radio stations are audible from U.S.A. and elsewhere, and are a good guide to possible contacts. These will mostly be heard during our mornings, say from 2300Z through to perhaps 0300Z or even later.

(2) If the 49 MHz+ area is active, keep a close watch on 50 MHz with the beam to the north east, in this position you will also hear the JAs if they are strong enough to work. But hearing signals on 50 MHz doesn't always mean they will be on 52 MHz, the MUF sometimes does not rise that high! And don't cheat, wait and work stations on 52 MHz, not 50 MHz. Remember, most overseas areas are dead set against out of band contacts and wide publicity about the VK position has been given in overseas publications — you may not care to have your name on the ARRL and SMIRK blacklist!

(3) When the band is quiet operate on 52.050 by all means — that was the purpose of originally deciding on a calling frequency and it is known overseas. BUT, please do leave a few seconds break between over to allow another station, perhaps from an exotic area, to call in. If the band is in good shape, then after establishing contact on 52.050, move away to allow others to monitor the frequency. The worst thing you can do is to use 52.050 for a crossband contact and so block the frequency for lengthy periods, the only exception might be if you're using VQX so there will be a break between you and your listening station will have a chance to hear another station.

(4) Perhaps most importantly, if you are lucky enough to get a contact with a rare station, keep the contact SHORT, remember there will be many other stations wanting to work him, and the conditions may only remain for a few minutes. All you need for a contact is to exchange signal reports, plus names, a request for a QSL, then sign off, the whole exchange need only take 1 to 2 minutes. This way you won't have other stations breaking in and generally frustrating others and getting a bad name on the band. There is absolutely

no justification for ANY station to have a prolonged contact with a rare station on — do the right thing and share him with the multitude!

So I feel if you bear all of the above in mind there could be many stations sharing some good contacts, particularly if PAT sees fit to join with other administrators and recognise the need for Australian amateurs to be able to share in some way the 50 MHz area at least by 1st March 1981!

Closing with the thought of the month "In the game of life, as in other sports, you can pick out the winners — they're the ones who aren't complaining about the officiating!"

73, The Vocs in the Hills.

QSP

AMATEUR LICENCES

As at 30th June, 1979, there were 12,082 licensed VK amateur stations of which 2,974 were Novice, 3,108 Limited and 5,956 Full Calls. For States, NSW led with 4,043 and Victoria 3,415. NT showed 65 per cent as Full Calls, ACT 63 per cent and the national total 49 per cent — the lowest being Queensland with 44 per cent of the national total. Novices were 25 per cent with the highest percentage of 29 per cent in Queensland and the lowest in the NT of 8 per cent. Limited calls showed up as 26 per cent of the national total, ranging from 31 per cent of the Victorian total down to 16 per cent of the ACT total. At the same date licensed CB stations on HF totalled 173,507.

TF LAND

In a letter to AMSAT (September 1979) Kristian TF3KX briefly outlined the level of activity in Iceland. There are approximately 100 members in the national society, of which 20 to 30 are active on HF, VHF or in special fields of amateur radio such as RTTY, etc. It may pay to also keep a listening watch on OSCAR satellite frequencies from time to time, as Kristian and fellow amateurs are becoming active using OSCAR.

LETTERS TO THE EDITOR

Any opinion expressed under this heading is the individual opinion of the writer and does not necessarily coincide with that of the publisher.

Lot 92, Russell Ave., Woodend 3442
8th January, 1980

The Editor,
Dear Sir,

I am writing to you with an appeal. The appeal is to ask if there is any radio amateur reading this which might be able to help me in learning about RTTY. Just recently I obtained a Model 15 typewriter and I set it up to the point where I can copy reasonably well. However I do need some more help in getting it all to work very well. I am at a disadvantage in that I live in a remote location and have no effective means of contacting anyone else except by letter. There is no Wireless Club where I can see other amateurs and learn from them. This is also one of the reasons that I have lacked the confidence and the knowledge to go for my ticket.

What I have wanted the "shock" of some amateurs have had virtually no contact with any amateurs for some time now and I have never had an amateur come here and visit me.

Terry Robinson U3105

5 Lyle Ave. Lindfield, N.S.W. 2070
20th November 1979

The Editor,
Dear Sir,

Would you kindly publish in our magazine this note of appreciation.

I have just returned from a yachting trip in which I was navigator/radio operator just before typhoon Ty commenced to build up. We lost our engine due to mechanical failure and when the storm started we ripped our mainmast and later our backstay bracket failed so we were without propulsion.

I would like to thank all those hams who assisted by passing messages to the captain's XYL to obtain replacement parts for the engine and to my XYL to advise her of the details of our rescue by the United States Navy and Coastguard. I am especially grateful to the operator who rang the Marine Operations Centre in Canberra to advise them of our 'Mayday' call and who also rang a well known amateur friend of mine in Sydney.

My only disappointment was to find that an amateur I 'knew' from previous contact did not know how to react to a mayday call but casually remarked to the station he was working that he had heard a 'mayday' which appeared to be coming from New Zealand and then went on rag chews.

This contrasted to the American hams who kept watch on my frequency and cheered off anyone who started transmitting within 5 kHz of me. I can now tell you that all to myself now that I am back! The principal amateur in our rescue was K6B-BX who remained on watch for 48 hours except for the period from 0200 to 0900 LMT on our first night.

Thank God for the radio amateurs.

Yours faithfully,
Gordon H. Sanders VK2DGS

"Bonnie Brees", Warramunda, N.S.W. 2741
21st December, 1979

The Editor,
Dear Sir,

I am writing in support of Mr R. J. Somerville's letter in December AR suggesting that past articles of an instructional nature should be made available in book form. Having recently gained the AOCF after studying on and off for some years via the WIA course, which was until recently about the only guide as to the scope of knowledge required, I find that there seems to be a great lack of really comprehensive basic training material. To some this may seem strange since there are many books of basic theory and elementary theory, but unfortunately most are trying to cover a complete radio course

in a couple of hundred pages or less — an impossible task.

Many may argue that it's all in the RSGR or ARRL Handbooks but to me they leave far too much reading between the lines to be classed as satisfactory training texts. I would have hoped that the continual issue of new editions would have done much to remove those vague old explanations that have been rehearsed for many years.

The ARRL is however to be commended for many of its other publications, an outstanding one of which is "Understanding Amateur Radio". This practical little book is a taste of what the Handbook should be and is an invaluable aid for AOCF candidates. Another fine book with a much fuller treatment of electronics but not radio is "Basic Electronics" by Grob.

Undoubtedly the best general text I have seen is "Electronic Communication" by Shrader. I thoroughly recommend this book to all such as myself who have not had the good fortune to be able to collaborate with someone trained in communications radio and have had to learn it all from books.

Judging from the number of novice calls filling up the callbook, there should be plenty of incentive for those better informed WIA members to go together and do something about the situation. I can think of no better way to justify those membership fees and enhance the reputation of the WIA at home and abroad than to put out a really worthwhile training textbook. Why leave it to the Yanks, they may have thirty times the numbers but are they thirty times as smart? Why not simply ask or offer a small incentive to members for submissions of suitable material — the results may be surprising. Remember, all those call signs have had to pass an exam.

Perhaps a good starting point for those contemplating doing something would be to give some credit to men like Galvani, Ampere, Faraday and Hertz. Their discoveries have laid the basis for a means for the use of the technology that has made our age unique.

I would also like to take this opportunity to thank those unsung heroes that have devoted their time and talents to produce the slow motion practice session. Without their help my AOCF would have been extremely hard to get. In terms of simplicity of equipment, width of appeal and communications effectiveness, CW still seems unchallenged. With this excellent service provided each night I wonder at that long list of limited calls. Is the modern amateur to be merely an extravagant CBer or someone with some knowledge and understanding of the privileges he enjoys.

The RF spectrum is a natural resource and with a sound standard of knowledge to decide genuine interest in radio. I see no reason to provide further evidence to justify our occupation of the amateur bands, especially since forward looking Governments should be looking at satellites and that massive undeveloped microwave spectrum for domestic and international communications.

Yours faithfully,

Graham L. Dun

The Editor,
Dear Sir,

I would like to strongly support the sentiments expressed by VK6ED in his letter in November AR. Like VK6ED I am not interested in entering EITHER Phone OR CW. I wish to enter both and meet as many of my old friends as possible, a number of whom served with me during 1939-45. The abolishing of an Open section does appear to be influenced by the "Down with CW" group, but I can well remember coming to those who thought amateurs, who later paid the supreme sacrifice, on CW during 1939-39 was, probably because I could not afford to go on phone anyway.

Other factors annoyed me regarding this year's contest. If one relied on AR for rules concerning the RD contest, it would have been difficult as my July copy of AR arrived on August 21st and having arrived back from overseas on August 28th I had no idea when the contest was to be held. I listened to the pre-contest broadcast from

VK2AWI and little significance was attached to the true meaning of the contest, the role of honour in whose memory the contest is conducted, was not even read out in fact, from what I heard, let us change the name of the Contest say, "The Friendly Contest".

Might I suggest that in future years details are not left to the last minute — we could well have some strike to blame again for late advice of details an outline be given of what the RD contest is all about, that an open section be included, that Novices be encouraged to enter the open section, even a low power section be encouraged.

We owe a lot to those amateurs — and many others — who died during the 39-45 conflict, let us remember them on this occasion each year and give those members who participate the opportunity to enter those sections and modes that give them most enjoyment. If they choose to have the minimum permissible contacts and put in a log (as I did this year) — good thing — if they want to go flat out for 24 hours for a large score (as I have done in the past) — all the better. But let us encourage and advertise the RD Contest.

Yours sincerely,

Jim Andrews VK2BO

8th December 1979

The Editor,
Dear Sir,

ENDEAVOUR AWARD — ROYAL NAVAL
AMATEUR RADIO SOCIETY

Our award, the 'Endeavour Award' has also been given nicely, thanks to AR and I have been advised we have issued 52 awards since Easter. There have been a couple of minor changes to the rules of the award to permit QSOs on VHF and to award double points for VK2BNR, VK2BS, VK2BMA, also VK2BNR counts double points for the 'Mercury Award' as do the two other stations operating from Naval establishments — G2BKN/G4HMS — HMS BELFAST and G2BRN/G3BZU — HMS MERCURY.

To gain an idea of the size of RNARS we are currently allocating numbers in the 1420 series.

We hope to gain a few more members and also interest a few YLs, especially those who were in the WRANS.

If anyone has a Good transmitter for sale we would be grateful if you could let us know.

Terry R. Clark, VK3ALG, RNARS 1158
Austral Air Branch Manager — RNARS
P.O. Box 537, Abury, N.S.W. 2540.

EDITOR'S NOTE: Please see "Awards Column" for the updated rules.

CONTESTS

Wally Watkins VK2DWW
Box 1955, Orange 2800

February:

- 9-10 John Moyle Field Day
- 16-17 ARRL DX CW Contest
- 23-24 French Phone Contest
- 23-24 RSGE 7 MHz CW Contest

March:

- 1-2 ARRL DX Phone Contest
- 9-10 Europe and Africa RTTY
- 22-23 BARTY RTTY Contest
- 29-30 CQ WW WPX SSB Contest

April:

- 25-27 Helvet's Contest

May:

- 24-25 CQ WW WPX CW Contest

ARRL DX Contests, full rules and specimen front sheet and log sheet available from FCM for SASSE.

Watch for W22BK/P-7, CW and SSB on 10, 15 and 20 during March 10-24 1980.

COMMONWEALTH CONTEST 1980 — "BERU" — RULES

1200 GMT Saturday, 8th March to 1200 GMT Sunday, 9th March

MODE
CW only, 3.5 to 28 MHz. Call is CQ GERU.

Eligible entrants are radio amateurs licensed to operate in British Commonwealth call areas as listed below.

SCORING
20 S points per contact exchange (RST 001 etc.), 20 points for 1st, 2nd and 3rd contact with each call area other than one's own, on each band.

G, GW, GD etc are counted as one area. Contacts with one's own area do not count at all. Penalties are imposed for unmarked duplicate contacts, incorrect calls and reports.

LOGS
Separate logs are required for each band showing columns—

1. Date and time GMT
2. Station worked
3. NR sent
4. NR received
5. Band
6. Leave blank (for checking)
7. Contact points claimed
8. Bonus points claimed

Each band log should be separately totalled and should include at the end a check list showing areas worked and number of contacts per area. Separate band totals should be added together and the total claimed score entered on a cover sheet giving particulars of station, QTH, equipment, power, antenna, and a declaration that the rules and spirit of the contest have been observed.

Entries may be single or multiple band. Single band entries should claim contacts on one band only, but submit details of contacts on other bands for checking only.

Entries should be addressed by AIR MAIL to:
D. J. Andrews G3MKJ,
18 Downview Crescent Uckfield,
East Sussex BN9 6JG and TN221UB
Closing date: 12th May, 1980.

COMMONWEALTH CALL AREAS

The following call areas are recognised for the purposes of scoring in the 1980 Commonwealth Contest:

- A2 Botswana, A3 Tonga Is., A5 Bhutan.
C2 Namibia, C5 Gambia, C6 Bahamas
G2/BG/GD/GI/GJ/GM/GU/GW
H4 Solomon Is.
J3 Grenada, J5 St. Lucia, J7 Dominica.
P2 Papua New Guinea.
S2 Bangladesh, S7 Seychelles
T2 Tuvalu, T3 Kiribati
VE1, VE2, VE3, VE4, VE5, VE6, VE7, VE8.
VK1, VK2, VK3 Lord Howe Is., VK3, VK4, VK4
Wilkes Is., VK5, VK6, VK7, VK8, VK9 Christmas Is.,
VK9 Cocos Is., VK9 Norfolk Is., VK9 Heard Is.,
VK9 Macquarie Is., VK9/VPE Antarctic, VB, VP1,
VP2A, Antigua Barbuda, VP2E Anguilla, VP2K St.
Kitts Nevis, VP2M Montserrat, VP2S St. Vincent,
VP2V British Virgin Is., VP5 Turks & Caicos, VP6
Falkland Is., VP8 S. Georgia, VP8 S. Orkney Is.,
VP8 S. Sandwich Is., VP8 S. Shetland Is., VP9,
VQ9 Chagos, VRI British Phoenix Is., VR6, VR5,
VR6, VR9 Sable Is., VY1 Yukon, VYD St. Paul Is.,
VL India, VL Laccadive Is., VU Andaman & Nicobar Is.
YJ

- ZB2, ZC4/SB4, ZD7, ZD8, ZD9, ZE, ZF, ZK1
Cook Is., ZK1 Manihiki, ZK2 Nukunono, ZL1, ZL2, ZL3,
ZL4 ZL Auckland and Campbell Is., ZL Chatham Is.,
ZL Kermadec Is., ZM7

- 3B8/3B7 Agalega and St. Brandon, 3B8 Mauritius,
3B8 Rodriguez Is., 3D2 Fiji, 3D6 Swaziland
4S7


- 5Y3, 5Y2, 5W Samoa 5X5, 5Z4
6Y3, 7Q7
8P, 8R
9G1, 9H Maldives Is., 9L2, 9L1, 9M2 W. Malaysia,
9M6/9M8 E. Malaysia, 9V1, 9Y4

*All calls operated from Commonwealth controlled areas of the Antarctic (VK0, VP6, ZL5 etc.) count as one call area.

Results of the 1979 Contest in which 41 VKs submitted logs appeared in December 1979 Amateur Radio

IONOSPHERIC PREDICTIONS

Len Poynter VK3ZGP/NAC



IF YOU'RE NOT BUYING AMATEUR RADIO ACTION



(IT'S AUSTRALIA'S BEST SELLING AMATEUR MAGAZINE)

THEN YOU'RE NOT KEEPING UP WITH THE LATEST NEWS, VIEWS AND REVIEWS

Please put me down for 12 editions of
Amateur Radio Action starting NOW!

Rates in Australia - \$14.40 Surface
mail overseas - \$18.40 Air mail: To
New Zealand - \$A26.70, Malaysia -
\$A32.60, Japan - \$A38.45; USA -
\$A42.35; UK - \$A48.25

Herewith enclosed cheque/postal
note/money order to the value of -

\$A

NAME

Address

Postcode

Post to: Amateur Radio Action Sub-
scriptions, Box 625E, Melbourne
3001

WICEN

Ron Henderson VK1RH

Federal WICEN Co-ordinator,
53 Hannaford St., Page ACT 2614
Ph. (062) 54 2056, A.M.

EMERGENCY SERVICES COMMUNICATIONS

INTRODUCTION

This issue we continue with the third part of the
Emergency Services Communications Procedure
Paper

20. SIGNAL STRENGTH AND READABILITY

A station that wishes to inform another of its
signal strength and readability will do so by
means of a short and concise report of actual
reception such as "Weak, but readable", "Strong,
but distorted", "Loud and clear", etc. A station
desiring to know how its transmission is being
received will transmit "How do you hear me?"

21. SYNCHRONISING TIME

(a) When a net has been established, Control
should announce the time so all operators
can synchronise their watches. To do this
Control will say, for example
"All stations THIS IS (Call Sign). When I say
time it will be exactly 1500 hours. 15 seconds
- 10 seconds - 5-4-3-2-1 - Time 1500.
OVER"

(b) Control will use the same procedure if a
request for the time is received from a sub-
station.

22. OFFERING MESSAGES

(a) An offer is a short transmission made to
warn the receiving station concerned that a
message follows. All messages will be offered.
The proword used in the exchange of calls
in the offer of a message are "MESSAGE"
or "LONG MESSAGE" or "UR MESSAGE".
"SEND"

(b) When the sending operator has a long message
he warns the receiving operator by
offering the message as a "LONG MESSAGE"

23. RECEIPTS

The transmission of a message is not completed
until the receiving station gives a receipt for it.
This is done simply by using the proword
"ROGER"

Example
"VK1BAA THIS IS VK1BAC send vehicle for
mail - OVER"

"VK1BAA - ROGER - OUT"

24. TYPES OF CALL

There are three types of call which can be used
on a net. They are "Single, Multiple and All
Stations."

(a) Single Call Used by Control to substation,
substation to control or substation to sub-
station.

Example: Control to substation (or substation
to control, VK1WI is control).
Control "VK1BFA THIS IS VK1WI UR MES-
SAGE - OVER"

VK1BFA: "THIS IS VK1BFA - SEND -
OVER"

Control: "THIS IS VK1WI - fresh batteries
have arrived - OVER"

VK1BFA: "VK1BFA ROGER - OUT"

Example: Substation to substation (Directed
Net).

VK1BFA "VK1WI - THIS IS VK1BFA - UR
MESSAGE FOR VK1BFC - OVER"

Control: "THIS IS VK1WI - SEND - OUT"

VK1BFC: "VK1BFA THIS IS VK1BFC SEND
- OVER"

VK1BFA: "VK1BFA - request loan of a new
battery OVER"

VK1BFC: "VK1BFC - ROGER OUT"

(b) Multiple calls: Used by Control to two or
more substations but not used when calling
all substations.

EXAMPLE
Control "VK1BFA, VK1BFB THIS IS VK1WI
- UR MESSAGE - OVER"

VK1BFA: "VK1BFA SEND - OVER"

VK1BFB: "VK1BFB - SEND - OVER"

Control "VK1WI - Collect fresh batteries from
me - OVER"

VK1BFA: "VK1BFA - ROGER - OUT"

VK1BFB: "VK1BFB - ROGER - OUT"

(c) All Stations Call Used by Control to all sub-
stations on the net. (All Stations on the Net
reply in alphabetical order)

EXAMPLE

Control "ALL STATIONS - THIS IS VK1WI
- UR MESSAGE - OVER"

VK1BFA: "VK1BFA - SEND OVER"

VK1BFB: "VK1BFB - SEND OVER"

VK1BFC: "VK1BFC - SEND OVER"

Control ALL STATIONS - THIS IS VK1WI -
Have you received fresh batteries - OVER"

VK1BFA: "VK1BFA - YES - OUT"

VK1BFB: "VK1BFB - NO - OUT"

VK1BFC: "VK1BFC - YES - OUT"

25. SENDING A LONG MESSAGE

A long message is one of more than 30 words
of text. The following procedure is then adopted

(a) The message will be offered using the
proword LONG MESSAGE

(b) It will be sent in sections.

(c) After about 15 groups, the sender confirms
progress by saying "ROGER SO FAR -
OVER"

(d) Receiving stations answer "ROGER" n turn
or, if necessary ask for repetitions.

(e) After obtaining acknowledgements from all
receiving stations the sender pauses for five
seconds. This is to allow any other station
to transmit an urgent message

(f) If there is no interruption the next section
of the message is transmitted

This procedure is continued until the message
is cleared

EXAMPLE

VK1BFC is sending a LONG MESSAGE to VK1BFX.
He sends it in two sections.

VK1BFC: "VK1BFX - THIS IS VK1BFC - LONG
MESSAGE - OVER"

VK1BFX: "THIS IS VK1BFX - SEND - OVER"

VK1BFC: After sending the heading of the mes-
sage says

"BREAK - following accommodation stores re-
quired - by one six hundred hours today -
stop - blankets figures five hundred - sixhena
figures two five zero - ROGER SO FAR OVER"

VK1BFX: "VK1BFX - SAY AGAIN WORD AFTER
Accommodation - OVER"

VK1BFC: "VK1BFC - I SAY AGAIN WORD
AFTER Accommodat on stores - I SPEL - 5 9 7 4
Tango Oscar Romeo Echo Sierra - stores -
OVER"

VK1BFX: "VK1BFX - ROGER - OVER"

VK1BFC pauses for 5 seconds to allow any sta-
tion with urgent traffic to call in

VK1BFC goes on sending the rest of the mes-
sage

"VK1BFX - THIS IS VK1BFC - pillows figures
two five zero - cutlery sets figures two five zero
- cooking sets type Delta figures two - MES-
SAGE ENDS - OVER"

VK1BFX: "VK1BFX - ROGER - OUT"

26. WORDS TWICE PROCEDURE

When communication is difficult, call signs,
phrases, words, or groups are transmitted twice
and indicated by use of the proword "WORDS
TWICE". Repeat or may be verified by use of
the proword "READ BACK"

EXAMPLE A

VK1BFX: "VK1BFC - VK1BFC THIS IS VK1BFX
VK1BFX - UR MESSAGE - UR MESSAGE -
OVER OVER"

VK1BFC: "VK1BFX - VK1BFX - THIS IS
VK1BFC - CK1BFC - SEND - SEND - OVER
OVER"

VK1BFX: "VK1BFC - VK1BFC - THIS IS
VK1BFX - VK1BFX - WORDS TWICE - WORDS
TWICE - PRIORITY - PRIORITY - TIME ONE
TWO TWO ONE SIX THREE ZERO - TIME ONE
TWO ONE SIX THREE ZERO - BREAK - BREAK
- CONVOY has arrived - Convey has arrived -
over - over"

SIDE BAND ELECTRONICS ENGINEERING

P.O. BOX 23, SPRINGWOOD, N.S.W. 2777
WAREHOUSE 213 HAWKESBURY RD. SPRINGWOOD
TELEPHONE (047) 54 1392

Overseas prices again show an upward trend. If you are in need of new equipment it makes sense to purchase now. Prices must increase once current stocks are sold. How about KENWOOD transceivers at the right price, or a YAESU FT-1011Z fitted with fan at \$850 -, HENRY linears \$850 - and \$1050 -, TH6-DXX \$300 -, 18-AVT/WB \$110 -, Rotators, cables and Co-ax connectors all at the right price. Check and compare our prices with others before you buy!

HENRY RADIO — A Famous Brand —

NEW LINEAR AMPLIFIERS —

2KD-5 — 2KW PEP, 80 - 10m SSB/CW/RTTY/AM
\$1050
1KD-5 — 1200W PEP, 80 - 10m SSB/CW/RTTY/AM
\$850

BAIN ANTENNAS

TH6-DXX 10-15-20M, 6-el. yagi.....\$300
18-AVT/WB 10-80M vertical \$110
204-BA 20M, 4-el. Tiger array.....\$220
BN-86 balun for beam buyers.....\$20
HY-Q (USA) 60-ohm 1KW balun.....\$15

ROTATORS & CABLES

All rotators now come with bottom brackets and control-indicator boxes wired
KEN KR-400 medium duty. \$120
KEN KR-500 vertical rotator .. \$140
KEN KS-065 stay/thrust bearing.....\$25
CDR BT-1A light duty 4 position push button programmable. Plus normal operation 120V AC.....\$85
CDR am III heavy duty 120V or 28V AC.....\$178
CDR tail-twister extra H/D 120V or 28V AC .. \$225
RG-8U foam coax cable, per metre.....\$1.00
8-cond. rotator cable, per metre.....75c

ACCESSORIES

Voltage regulator 18V AC Input, 12V DC 3A output \$18
240/18V AC transformer \$1C
Mobile bumper mounts 3/8" 24 thread \$2

KYOKUTO FM-2016A

800 channel, 2 meter FM transceiver with 4-channel memory and scanner 15W.....\$355

TRIO-KENWOOD PRODUCTS

VFO 520 for TS 520S \$130
LF 30A low-pass filter..... \$30
SP-120 (TS-120 series) SP-100) each \$32
DK 520 adaptor TS 520 to DG 5..... \$10

All further Trio-Kenwood accessories and transceivers at competitive prices.

YAESU MUSEN PRODUCTS

FT-1012D 10-16M digital transceiver w/cooling fan fitted.....\$950
SIDE BAND brand microphone to suit..... \$10

CO-AX CONNECTORS

PL-259, SO-239, cable joiners, each..... 60c
Right angle and T-connectors, each..... \$1.00
GLP right angles RG-58U to SO-239, w/lock nut and cap, each.....\$1.50
Double female connectors, each..... 60c
MLS right angles RG-58U to PL-259, each..... 75c
In-line mike sockets 3 & 4 pin, each..... 60c
Mike sockets 3 & 4 pin, each 60c
M-ring body mount w/lock-nut..... \$1.50

NOVICE SPECIALS-TRANSCIVERS

10M sideband SE-502 USB/AM 15W PEP-240V AC, 12V DC, inbuilt SWR/RF meter, 28.3-28.6 MHz clarifier tuning transmit and receive.\$90
10M Universe 224-M, USB/AM, 15W PEP 12V DC, 24-ch. 28.480 to 28.595 MHz, 5-Khz steps-clarifier tuning transmit and receive..... \$95
CONVERSION CRYSTALS for amateur licence holders - set of 8 crystals to convert 23-ch, 27-MHz CB units to 28 MHz. Suitable for Kraco, Sideband, Universe, Hy-range V etc., converts as per Universe 10M above — CRYSTALS & INSTRUCTIONS..... \$32
Set of 4 crystals converts to 28.3-28.6 MHz \$15

All prices are NET, ex Springwood NSW, on pre-payment with order basis. All risk insurance is free of charge, allow for freight charges by air, road, rail or postal, excess will be refunded. Prices are subject to change without prior notice. All orders cleared on a 24-hour basis after receipt of order with payment.

ROY LOPEZ (VK2-BRL) Manager

AWARDS

COLUMN

Bill Verrall VK5WV

7, Lac Ave, Flinders Park, S.A. 5025

WORKED GERMAN LARGE CITIES AWARD

This award is available for working stations in West Germany. It is available in three (3) classes and there is no restriction on the mode used. No band endorsements are made as more than one band may be used in qualifying for the award. Each city may be listed once only in the claim. The three classes are —

Class	DX Stations
3	— 10 Cities
2	— 20 Cities
1	— 30 Cities

QSLs are not required for this award, but a list certified by two other radio amateurs or an officer of a National Radio Society should be submitted together with 10 IRCs. The Award is also available to SWLs on a 'Heard' basis.

Came should be sent to: Karl-Heinz Kummerle, DL2-B, 694 Wehrheim Postfach 23, Germany.

German Large Cities are Aachen, Augsburg, Berlin, Bielefeld, Bochum, Bonn, Bottrop, Braunschweig, Bremerhaven, Darmstadt, Dortmund, Düsseldorf, Duisburg, Essen, Frankfurt/Main, Freiburg, Garmisch-Partenkirchen, Göttingen, Hamburg, Hannover, Heidelberg, Heilbronn, Herten, Karlsruhe, Kassel, Kel, Koblenz, Köln, Krefeld, Leverkusen,

Ludwigshafen, Lubbock, Mainz, Mannheim, Monchengladbach, Mülheim/Ruhr, München, Münster/Westf., Neuss, Nürnberg, Oberhausen, Offenbach/Main, Oldenburg L., Osnabrück, Recklinghausen, Regensburg, Rheinfelden, Saarbrücken, Salzgitter, Solingen, Stuttgart, Trier, Ulm, Wanne-Eickel, Wiesbaden, Wilhelmshaven, Witten, Würzburg and Wuppertal.

"100 X" AWARD

This award is issued by the Mexico DX Club to licensed radio amateurs and SWLs for confirmation of QSO with stations that have in its call sign one or more "X" letters (XE10W, W4LXX, EA3AX, I2XYZ, etc.).

To apply for this award you must have at least 100 points.

Each letter X of stations of any country outside Mexico counts 1 point.

Each letter X of Mexican stations count 2 points. Each letter X of Mexico DX Club members counts 3 points.

QSO with the club station of the Mexico DX Club "XE10MX" counts 10 points.

Only contacts after January 1st of 1973 are valid.

Application and QSL cards must be sent to P.O. Box 21-187 in Mexico City 21.

For sale return of the QSL cards and award, please include 15 IRCs (or 3 dollars U.S.A.).

CENTRAL COAST AWARD (VK2)

The Central Coast Amateur Radio Club issues an award to stations who meet the following requirements —

1 Overseas Stations:

Overseas stations must work Two (2) stations

resident on the Central Coast of N.S.W. OR one of the Club stations VK2EH or VK2AFY

2 VK Stations:

VK stations must work Four (4) stations resident on the Central Coast of N.S.W. plus either of the Club stations VK2EH or VK2AFY

3 Central Coast of N.S.W. Stations:

Central Coast stations must work Ten (10) stations resident on the Central Coast of N.S.W. plus either of the Club stations VK2EH or VK2AFY

4 The Central Coast of New South Wales is defined as that area within the Shires of Gosford and Wyong

5 After the necessary number of stations have been worked send a copy of the log extracts to

The Awards Manager, P.O. Box 238, Gosford N.S.W. 2250, Australia.

After verification of the QSOs the Award will be issued

Good Hunting.

UPDATED ENDEAVOUR AWARD RULES

(See also AR, February 1975 and July 1975)

Rules

1 The name of the award shall be the "ENDEAVOUR AWARD" and shall be open to all radio amateurs and short wave listeners.

2 Applicants must establish two-way amateur communications with RNARS Members residing in Australia. SWLs must monitor Australian RNARS Members.

3 Points will be awarded on the basis of one point per VK RNARS Member worked/heard per band, regardless of mode. Only contacts after January 1st 1975 will count towards the award. Contacts on the VHF bands will count double points. All contacts with RNARS NIMBBA club station, VK2BNU, count double. To qualify the following is required —

For amateurs/SWLs residing inside Australia — 15 points.

For amateurs/SWLs residing inside Oceania — 10 points.

For amateurs/SWLs residing outside Oceania — 5 points.

In addition, for amateurs residing outside Oceania, contacts with VK RNARS Members on the 3.5 MHz band will count double points. For the purposes of this award, any RNARS Maritime Mobile Member when located inside Australian waters may be counted as a VK Member.

4 The Award will be endorsed ONLY at the request of the applicant and the following endorsements are available

ALL CW — ALL SSB — ALL NOVICE — ALL 35 MHz — ALL 80 MHz — ALL VHF — FIVE-FIVE. The last endorsement being for gaining at least five points on each of the five high frequency bands.

5 A special sticker is available to add to existing certificates for gaining 100 POINTS. However, any previous MODE endorsements on the original must hold true for all 100 points, or a second award claim for mixed mode must be made. The sticker is issued free of charge to existing award holders. A SASE or 2 IRCs would be appreciated to cover return postage.

6 To claim the Award, no QSLs are required. Full log details showing the VK member (or /MM-OTH) claimed, their RNARS number, date, time, frequency, mode, plus an application fee of \$1.50 Australian or 7 IRCs are to be sent to the Endeavour Award Custodian —

Mr. R. Baly, 45 HMAS Australia Road, Henley Beach South, SA 5022, Australia. Please enclose all cheques in Australian currency and made payable to "R. Baly". Clearly state what endorsements are claimed. Certificates to successful applicants will be forwarded by air mail.

Join the IW net at 2300Z on Thursdays on 14165 kHz when you have intruder information.

HOLIDAY PLAYGROUND OF TWO CITIES



THE CENTRAL COAST AWARD

Presented by

Central Coast Radio Club

F.A.M. LE ONLY

WHO HAS MADE RADIO CONTACT WITH THE REQUIRED NUMBER OF AMATEUR RADIO OPERATORS WHO ARE MEMBERS OF THE CENTRAL COAST RADIO CLUB

Award No.

Stations Contacted

President

CENTRAL COAST - THE HOLIDAY COAST

The Central Coast, which has been called the Holiday Playground of two cities, embraces more than 125 square miles of the finest and most varied scenery. The area has a great diversity of interests including 30 of the most beautiful beaches on the State, more than 100 square miles of shark-free coves, mountain lookouts and scenery, heavily timbered forests and more than 200,000 acres of wonderful national parks and reserves. The Central Coast is a water wonderland controlled by the Shire Councils of Gosford and Wyong. Gosford is the hub of the coast and the terminus of a fast and modern electric train service from Sydney. Situated midway between Sydney and Newcastle 50 miles from each, with excellent shopping facilities and a population of 78,000, it is a wonderful area in which to live or spend a pleasant holiday.

The Central Coast Radio Club, operating station VK2AFY, is a branch of the Wireless Institute of Australia which is the oldest amateur radio organization in the world.

This Award has been sponsored by The Central Coast Tourist Authority

The Central Coast (VK2) Award

ALARA

AUSTRALIAN LAD ES AMATEUR RADIO ASSOCIATION

Results of the elections which were held at the Annual General Meeting of ALARA. President — Heather Mitchell VK3JZU, Vice President — Raeli Fowler Secretary — David Coolidge VK3ANL, and Treasurer — Mavis Russell VK3BIR. Last year's officers were given thanks for the work they did and the time they contributed. The group gave special thanks to Mavis VK3BIR for all the contributions in time and energy she has made this past year to amateur radio and ALARA.

The next meeting of ALARA will be held at the home of Mavis Stafford VK3KS, 16 Byron Street, Box Hill, on 9 February, 1980. There is no meeting in January.

YL ACTIVITY DAY

Aims: For YLs to meet and get to know other YLs without contest pressure, to have more personal QSOs than ever in a YL, and to help OMs who may need a quick contact for a YL award.

Date: the 8th day (GMT) of every month.
Frequencies: 3.658, 7.058, 14.258, 21.158, 21.358, 28.585 MHz ± QRM.

Times or the hour, every hour if you don't hear any YLs, please call CQ YL.

[Thanks to Dana G4EZI for this information.] ■

CAMEO OF MAVIS RUSSELL VK3BIR, PRESIDENT OF ALARA, 1979

Mavis has had her full call for 2½ years now. She became interested in amateur radio when her husband, Earl VK3BER, received his ticket. She took a correspondence course, but her interest waned. Mavis had heard about the formation of ALARA on the VWA broadcasts, but it was the ALARA sked on 80m that really piqued her curiosity. So, on 1 July 1975, she took classes at the Eastern and Mountain District Radio Club. In 1977, she received the news that she had passed the full call exam. Mavis remembers that it was a "tremendously exciting moment", and it was followed by much celebrating.

Since then, Mavis has been active in many aspects of amateur radio. She has participated in WCEC activities in particular the canoe race on the Murray. She has been on the steering committees of the Frankston and Mornington Peninsula Amateur Radio Club and has been on various committees since its inception four years ago. Presently she is the QSL manager for the club.

Her involvement with ALARA began with the skeds and the monthly meetings in 1975. In 1979 she served as President. Her efforts have brought forth the ALARA award, newly printed but not yet publicised and an expanded membership base. She wants to have more YLs involved in the sked (Mondays 1030 GMT 3.58 MHz ± QRM). With the help of State Coordinators she has been experimenting with moving it into the novice section in the hopes of further participation.

Mavis enjoys working CW and has worked the 100 counts as needed for the DXCC but has yet to apply. Her goals for the coming year are to improve her CW and to get involved with satellite operation in fact the whole family is interested in satellites. Mavis says that one of her sons, aged 18, will be sitting for his novice exam in February. That may result in competition for the use of the rig, with three amateurs in the household.

Mavis is quite active on SSB, especially on 20m and 2m. Early in the morning before work, she can be heard on 10m, sometimes chatting with Earl. YJ3ENEM. It was her on air friendship with Earl that helped Mavis travel to Port Vila and operate there with YJ3 call last October. Her special QSL cards have been printed and are being posted.

The Victorian Division held a pre-Christmas picnic in Woodland at the home of Joan VK3UTU. Among those attending were Norma VK3AYL and Frank VK2AKG, who were married only a week previously. Congratulations and best wishes to the

both of your Norma was the foundation president of ALARA in 1975.

YLRL, ALARA's sister organisation in the US, celebrated its 40th birthday. A YL Anniversary Contest was held and a few VK YLs participated. No news yet about the results.

YL Activity Day is the 6th of every month. Look for YLs on the hour, every hour, at the following frequencies: 3.658, 7.058, 14.258, 21.158, 21.358, 28.585 ± QRM. Geraldine VK2KXI and Helen VK2KXI did call "CQ YL" last month but they were unsuccessful in making contacts. Mavis VK3KS hopes to give it a try next month when repairs to her antenna should be completed.

If you are a YL and would like to join ALARA, the only requirement is an interest in amateur radio. For more information, please contact the Secretary, Box 110, Blackburn, Victoria, 3130.

Maggie VK3MRR

INTRUDER WATCH

All Chandler, VK3LC

FEDERAL INTRUDER WATCH CO-ORDINATOR REPLACEMENT

As denoted in November AR I have relinquished the position of Federal IW Co-ordinator, and have been fortunate in finding a replacement.

Graham VK3NXL is your new Co-ordinator as from January 1980, and it is very fitting that a Novice should take over the co-ordination.

With the conclusion of WARC 79 there is a completely new era commencing for Amateur Radio as a whole, and for Australian Amateurs, too. With the above in mind I am of the opinion that the IW should be handled by new and enthusiastic members, and Novices fall into that category. The old-timers have done a very good job in the past and it is up to the newcomers to do likewise in the future. The future destiny of Amateur Radio is in their capable hands.

Co-ordinators as at the time of writing are —
VK1NBG R. Chorley, 42 Gouger Street, Torrens 2607

VK2AF6 Les Weldon, 11 Raymond Avenue, Northmead 2152.

VK3 —
VK4NMAJ Gordon Loveday, "Avalonmore", Rabyvale 4702.

VK5LG Laila Cotton, 84 Warocca Avenue, Parkholme 5043.

VK6WT Dave Couch, 9 The Grove, Wembley 6014.

VK7HJC Jeff Cordeil, 323 Lenah Valley Road, Lenah Valley 7008.

VK8HA Henry Andersson, PO Box 1418, Darwin 5794.

Federal, VK3NXL Graeme Fuller, PO Box 158, Healesville 3777.

All Chandler VK3LC,

IARU Region 3 IW Co-ordinator.

INTERNATIONAL NEWS

844

A note has been received about the formation of a new society in the Solomon Islands, the S.I. Island Radio Society. The inaugural general meeting was held on 10th October 1979, and a call sign HA4SI has been obtained. The President is HA4DX and Dr. G. W. Hughes is the Secretary. The address is P.O. Box 418, Honiara, Solomon Islands which also serves as their Inland QSL bureau address.

RECIPROCAL LICENSING

Details were published in AR, Jan. 1978, p.25. ■

MAGAZINE INDEX

Ray Hartcopl VK3AOH

From this issue onwards it is proposed to make some alterations to the Magazine Index Department of AR. The title of an article can often be misleading and it is disappointing if one goes to a lot of trouble to hunt up a magazine and then find that the article has—for instance—no constructional information. Therefore it is proposed in future to add a key letter to the various titles listed, G for general, C for constructional, P for practical where there are no actual constructional details, T for theoretical and N for anything of particular interest to the Novice. Any comments from readers as to whether they find the new format helpful would be greatly appreciated.

73 MAGAZINE August 1979

Converter for 2 GHz TV Channels (P); History of Ham Radio (G); The Potted J Weatherproof Antenna (P)

September 1979

History of Ham Radio (G); Remote Control for the IC225 (P)

RADIO COMMUNICATION June 1979

Improving the FT-101 (G).

August 1979

CMOS Kayser with Memory (C)

CQ August 1979

The People's Temple Net (G); Foreign Morse Codes (G, N)

October 1979

DX World Records (G); Crystal-translator Tester (C, N)

HAM RADIO July 1979

UHF Local Oscillator Chain (C); 40 Metre Beverage Antenna (C); Test Equipment Mainframe (C)

August 1979

12V 10A Power Supply (C); Ground Systems (G)

QST June 1979

AR in Tonga (G); 5/8 2 Metre Antenna (C)

September 1979

Printed Line Techniques for VHF (G, C); onephone Ducting (G); Mono-Loop Delta Antenna (C).

These are a few highlights. More next time. ■

QSP

CB AGAIN

According to reports in CQ for October 1979 Japan has recently approved a CB service which will operate in a band consisting of 110 channels. Channel 1 is identical to that in the USA CB service, with the highest channels extending to just under the 10 metre amateur band. ■

USA REPEATERS

How many amateur repeaters are there in the U.S.A? ARRL Repeater Directory lists 4872 in 1979, which excludes some private and closed repeaters mainly in the 70 cm band. There were 3438 on 2 metres, and 728 on 70 cm, with others on 10 (36) and 6 (183) metres, 220 MHz (446) and 1215 MHz band (7) and 24 ATV repeaters. If the growth rate continues there would be over 10,000 in 1982—QST July 1979. ■

VALVE (TUBE) PROBLEMS

Writing in Technical Topics in November 1979 Radio Communications Pat Hawker quotes the growing scarcity (and consequent rising cost) of many once-familiar valve types now that new TV receivers (the last mass market for valves) are virtually entirely solid-state. Some valves for TV sets, not being designed for RF applications, may or may not neutralise satisfactorily depending on the make. Inter-electrode capacitances seem to vary widely between different brands of the same valve type, e.g. 12BY7A. ■

AROUND THE TRADE

ICOM RELEASES MICROPROCESSOR 2m RIQ

Following the tradition of the earlier IC21A 2 metre multi-mode transceiver the IC251A has improved performance and facilities, apart from introducing new power supply technology in common with the 6m version, a pulse type (50 kHz) power supply is used on AC allowing a reduction in weight and heat.

Using micro computer control, a multi-purpose scanning facility allows monitoring of three different memory channels, a program scan giving scanning between two programmed frequencies, and an adjustable scanning speed that stops scanning when a signal is received — on all modes!

Continuous coverage over the complete 2m band is provided with either 1 kHz steps on FM or 100 kHz steps on SSB, with a fast tuning facility also provided.

Further details and prices are available from Vicom at their Melbourne and Sydney addresses or their interstate representatives. ■



CW Electronics Brisbane, has commenced selling and distributing a range of Morse code and/or RTTY interfaces for the Commodore PET computer. These components are marketed under the brand name Macrotronsics and are imported from USA.

The interfaces link the worlds of the computer enthusiasts and amateur radio operator.

The Macrotronsics M650 interface comes complete with relevant software cassette. The manufacturers claim the interface offers a number of interesting features:

- Split screen display with the top six lines for the transmit buffer, middle two showing actual characters transmitted to a/r and bottom twelve displaying the receiving signals.
- Message library functions, you could record the RTTY news service for future reference. The interface offers Auto CWID, eight message memories and enables you to send UTC at a push of a key.
- Select ASCII at 110 Baud or Baudot at 60, 67, 75 100 w.p.m.
- Other features include word orientated editor, instant reply, auto transmitter control from the keyboard plus more.

If you require to drive a model 15 teletype machine, there is a Macrotronsics MLK Loop Keyer module or with a FT101Z a MSK1 Solid State Keyer module to handle the Reed relay keying.

The M65 ham RTTY/morse interface is also available which offers phase locked loop demodulator, LED tuning indicator, built-in side tone oscillator, auto line sending, ten message memories and a Morse code trainer.

The RTTY enthusiast's Macrotronsics FSD-1 RTTY modulator uses a phase locked loop demodulator and provides RS232 output. It allows reception of 170 Hz or 850 Hz shift RTTY signals at the flick of a switch. Tuning is achieved by an 0.3 mA meter that is supplied.

Owners of TRS 80 or Sorcerer computers can easily use some of the range.

For further information contact CW Electronics, Cnr Marshall Road and Chamberlain Street, Taragindi, Brisbane, Qld 4109, Tel (07) 48 6601. ■




Nigel Sheppard (l) and Brian Beamish (r) discuss the Commodore PET.

NEW COMMUNICATIONS MONITORS

Instrument Flight Research (IFR Inc.) have released, through their newly appointed agents, Vicom International Pty. Limited, Professional Products Division, their communications monitor FM-AM 1000A and FM-AM 1000S. The instrument covers 100 Hz-999 999 MHz as a generator and as a receiver 300 Hz-999 999 MHz with accuracy quoted as 1×10^{-4} ppm. The instrument covers all functions as standard, and this includes spectrum analysis (S Model), audio synthesis, two tone generation, GFO for single sideband measurements, power measuring to 100 watts and field strength measurements as well. Indeed, all modes of measurement are available at the flick of a switch.

The instrument is powered by mains voltage (either 240V AC or 110V AC) or by its own built-in Nicad battery pack. Because the instrument is small and light it is well suited to field operation.

Further information and specifications may be obtained from the authorised Australian agents, Vicom International at 68 Eastern Road, 5th Melbourne, Phone (03) 699 6700 or 339 Pacific Highway, Crows Nest, Phone (02) 439 2706. ■




IC225 MAKES 2k

Over 2000 units of the current Icom Model IC225 2m FM transceiver have been sold in Australia, according to the distributors, Vicom International Pty. Limited. This is in addition to the popular IC22A and IC20 series. ■

LEADER LDM170

As part of the vast range of Leader test equipment, Vicom International are pleased to announce the release of their noise and distortion meter (model LDM170).

The instrument is available from Vicom International Pty Ltd and distributors. ■




DAIWA RELEASE NEW SPEECH PROCESSOR

Daiwa Corporation have released the new model RF650 RF Speech Processor designed for amateur radio transceivers.

The retail price is \$108 and is available from the Australian distributors, Vicom International Pty Ltd, 68 Eastern Road, South Melbourne.

The RF650 is shown below with the popular Kenwood TS120V. ■



DIVISIONAL NOTES

VK2

24th URUNGA CONVENTION AND FIELD DAY, EASTER 1980

April 4th, 5th and 6th

Friday 4th 2000 hrs Ocean View Hotel Urunga. Ragchew and Registration, OM \$7, XYL \$5, Family \$15 includes maps and tourist information, all events, morning and afternoon tea, Saturday and Sunday, supper Saturday and Sunday.

Saturday Urunga opposite Ocean View Hotel. Sunday Bellingen Show Ground Coming from Highway turn right at Bellingen Post Office — follow signs.

Car trips have been arranged to local cottage industries for those who are interested. Details will be available at the Registration table.

Trade displays, disposals — bring and sell — lucky registration amateurs displays, cottage industry displays, quiz.

7100 MHz-28.5 MHz-145 MHz monitored for talk-in.

Further information can be obtained from the Coffs Harbour Club Net each Monday at 2000 hrs. Aust summer time on 3610 MHz or from Urunga Convention Secretary Max Francis, Dowle St Bellingen 2454. ■

BUYING OR SELLING QEAT?

HAMADS

MAKE IT HAPPEN FAST

HELP WITH INTRUDER WATCHING

TRADE HAMADS

For a very long time commercial advertising has not been accepted in *AR* Hamads, but as the result of discussions at the 1978 Federal Convention a decision was made to open up a "Hamads-Trade" section. The rule will be \$10 for 4 lines plus \$2 per line (or part thereof), minimum charge \$10, prepayable. Copy is required by the first day of the month preceding publication. This will mean that in future ordinary Hamads submitted from members who are deemed to be in the general electronics retail and wholesale distributive trades should be certified as referring only to private articles not being re-sold for merchandising purposes. ■

HAMADS

- Eight lines free to all WIA members. \$9 plus 3¢ per line for non-members.
- Copy in typescript please or in block letters to P.O. Box 150, Toorak, Vic. 3142.
- Reprints may be charged at full rates.
- Closing date: 1st day of the month preceding publication. Cancellations received after about 12th of the month cannot be processed.
- QTH means address is correct as set out in the WIA 1978 Call Book.

FOR SALE

Kenwood TR710V HF Vcr, c/w (working A1), with manual and orig. packing, 4 mths. old, little use, but slightly scuffed on sides of cabinet, \$510, ONO. Phil VK3NAY/EAU. Ph. (03) 221 6591 A.H.

Telatype Model 15 for RTTY, adjusted to 45.45 baud, good working order, \$50; transformer, 240/110V, for above, \$15. VK3NKP. Ph. (02) 521 2557.

BC-348 Rx with P/S, spare valves and manual, \$50; Gelco G-208 Rx, needs repair, dial mechanism perfect, \$50; air variable capacitors, 40-300 pF, 7 KV, brand new, \$20; 6 position rotary S/W, 13 KV, 20A, compact size, brand new, \$20. John VK2PI. Ph. (02) 822 4865.

Ceiling Commun. Rx 814, with manual, full set of spare valves, \$500; Kenwood TR7400A, as new, 35W output, \$350; Chase Challenger 10, unwrapped gill, \$299. VK2AVP (ex VK2KNK), Ph. (047) 21 4733.

IC5510 6m Tcvr, 100W, IC311, 2m tcvr. 6m 5 ft. yagi, IC229 2m tcvr. FM mobile, Hunter vertical 4-BTV, 13.5V 12A, regulated DC, HD supply. Ph. (03) 242 1231 A.H., (03) 509 8437 Bus.

Hy-Gain 14 AVT Vtr. Antenna, 10-40m, as new, complete with instruction sheet and carton, \$50. VK2ATP, QTHR. Ph. (02) 98 7151.

Drake Comm. Rcvr R4A, hams and ten SW 500 kHz bands, Drake RB, four Drake filters installed, notch filter, exc. selectivity and sensitivity, 1 kHz frequency readout, matching Drake MS-4 comm. speaker, manual, mint cond., \$225. James VK2JJO, GPO Box 5076, Sydney 2001, NSW. Ph. (02) 36 7736.

Yaesu FT7, little use, orig. carton, complete, works like a charm, \$350; Drake W-4 meter, 0-200W, a must for every shack, \$40; L. Wade VK2AGW. Tel. (03) 526 1657 A.H.

FT210 2m Transceiver (rep. 2, 3 and 8 and simplex Ch. 40) and matching FP2 AC power supply, \$160, ONO. M. Eversd VK3AVO, QTHR. Ph. (03) 544 4109.

TH3JR Tribander, 6 mths. old, \$120; FT7 tcvr, \$400; FL110 Yaesu linear, \$180; YO301 Yaesu transceiver, \$280; IC202 2m SSB vcr, \$120; Phillips R/C bridge GM414, \$25. VK3CCE, QTHR. Ph. (03) 526 1657 A.H.

from IC311 all mode, 2m, Tcvr. very little use, faultless, as new condition and operation, \$670. VK3SB, QTHR. (03) 550 3521.

FTDX 400, just re-aligned, good cond., \$350. VK1MP, QTHR.

Complete Station: Yaesu FT101E, good cond., with manual and carton, \$500; Kenwood TR7600 2m tcvr., complete, \$350; RM76 microprocessor, c/w TR7600/7625 for keyboard entry of frequencies, scanning, six memories, etc., \$95; JX100 scanning rvr., 2 mths. old, \$330. Richard Cowles. Ph. (02) 699 9403.

Uniden 2820, \$355; VJ5R 80-10m trap vcr, \$150; 4 el. 6m beam, \$40; CS201 coax switch, \$15; Hansen SWR bridge and FS meter, \$20. David VK3ZCR/NKG. Ph. (03) 460 5270 A.H., (03) 379 9468 Bus.

Trio GO-13000 Oscilloscope, \$180; Yaesu FT7 Tx, \$360; Yaesu FT07 with narrow filter and slow motion drive, \$260; 5 "bandit" quad hubs, never used, \$10 ea. Bruce VK5NBA, QTHR. Ph. (097) 64 7454.

Superb Icom 701, brand new, only removed from carton for checking, completely solid state, no tune (broad band design) final, from 160 to 10m, built in dual VFOs, \$1,000 without 240V power supply/speaker, or \$1,200 with, I need the money. Ian Shaw VK3NLS. Ph. (03) 60 0421, ext. 2066. Bus.

FuX 490, plus home brew linear, \$400 the lot. Ph. (058) 69 3283 evenings.

Trio JRB00 gen. cover, R. 0.55 to 30 MHz and 144 to 148 MHz, bandspread on amateur bands, Q multi. 100 kHz crystal calib. (needs xtal), recently re-aligned, \$125. VK3ZTA, QTHR. Ph. (03) 500 1157.

1986 Army Vcr A-516, good cond., incl. more key, headset, handset, four aerials, covers to fit webbing and also carrying case, best offer. Glenn VK4UN, QTHR.

LK 995 ATU, built-in SWR/power meter, 0-30-250W, manual, \$150; Heathkit cantenna dummy load, 1 kW and oil cable. Will VK3BTO. Ph. (03) 758 5701.

547 6m FM Tunable Transceiver, ex army, \$25, ONO. VK3YGO. Ph. (03) 67 4105 Bus.

FT191B, works perfectly, AC, has faulty DC-DC inverter, causes all items to run, sold as is, but very good condition, original packing, \$500. NOMO. TR2200G, 2m FM portable, Ch. 40, 50, R42, R48, nicads, original packing, as new condition, \$180 ONO. VK4VU. Ph. (07) 52 7239 Mon-Fri. after 5 p.m.

Yaesu FT501B Tcvr, Yaesu FP301 power supply, Hekada W15m V522 Yagi, Emtorator 103 LBX rotor and cable, all items in good cond., tcvr has full coverage on 10 and 11m, complete station as above, \$1000. Genuine reason for selling. Kevin Gock VK3NPK, QTHR. Ph. (051) 52 4632 Bus. ('S1) 57 1492 A.H.

Heathkit SB101 Tcvr, up-dated to SB102, CW filter, 10 to 80m, like new; Heathkit 540 ext. VFO; Heathkit H100 2m tcvr, 240W output, sold as is; Heathkit 12V DC power supply for mobile; connecting cables, manuals — \$850 the lot. VK2DA, QTHR. Ph. (02) 94 1039.

TH60XX Hy-Gain Tri-Band Beam, completely refurbished, new boom section, new SS cables, new trap covers, small elements, traps assembled, sintered, taped and sealed, tuned for 14.7 MHz, used, send beam to mast assembly etc., \$200. VK2DA, QTHR. Ph. (02) 94 1038.

Atlas 210X SSB Transceiver with Shure 400A mika, POA. Icom IC22A VHF transceiver, POA. Ian VK2AVV. Ph. (02) 653 2341 or (02) 406 5665 ext. 258 Bus.

Yaesu Guitzmound HF Ant., base, 2m stub, 60m c-d 40m resonators, \$55. VK2DEP, Corimat, M.S.W. Ph. (042) 83 3509.

Yaesu 301D, 160-10m, 300W, PEP, all solid state, digital readout, exc. cond., \$320. Alex VK2NHD, QTHR. Ph. (02) 772 2645.

FT200 Yaesu Tcvr, with FP200 mains power supply, as new, cooling fan, built-in audio filter for CW, instruction manual. FL FT200 club workshop men, \$300. VK3JAS, QTHR. Ph. (03) 754 4194.

Multi Quartz 16 Transistorised 2m FM Tcvr, 25 ch. capability, xtal inc. rpters. 1 to B, 40 and 50, complete w. usual extras, \$180. IGL 432 MHz strip-line frequency converter, 28 MHz. IGL with HY-Q1A1, neatly boxed, \$20. VK4Z21, QTHR. Ph. (07) 224 0875 Bus.

Kenwood R-5000 Comm. Rx, complete with all accessories, 4 select. filters, exc. bands, VHF converters, matching speaker, 240V AC and 12V DC, Kenwood D-5 dig. display. Factory installed, can be used as ext. for Kenwood VFO for Kenwood 520 and 820 series tcvrs, brand new in factory cartons, \$700 price. Mantred Mayer, Box 120, Vaucluse, 2030. Ph. (02) 371 8854.

Hygain trapped vtr. ant. for 10, 15 and 20m, \$50. VK2AXR, QTHR. Ph. (02) 44 1389 after 18.00h.

Ykakuote 2m FM Tcvr, synthesised 500 channels, dig. readout, mcb, handbook, no mods, exc. cond. \$250. M. Glover VK7HG, Franklin St., Swansea 7278. Ph. (082) 71 8220.

Yaesu FT501B SSB Transceiver, good condition, recent re-alignment, \$450. VK6BD, QTHR. Ph. (08) 24 1591.

FT101B AC-DC Tcvr, 160-10m, SSB-CW-AM, mint cond., little used, complete, \$525. 144V0-VB 40-10m vtr. ant., complete, good cond., \$45. VK6YX, QTHR. Ph. (08) 74 2350.

Black Clearance. ICOM 21A/2V21, 2m FM synthesised, digital readout, full scanning and memory facilities plus several fixed channels, full metering, internal ATU P/S or 12V DC operation, all as new, \$350. Ken KP12A RF speech processor, \$100. DAIWA RF440 RF speech processor, \$90. Digital freq. counter to 250 MHz, \$100. 40m helical whip, 10, 160m helical whip, \$15. Matching speaker for TS550, \$25. Nicad charger for Ken KP202, new, \$12. VK301, QTHR. Ph. (03) 660 9215.

Yaesu FL/FRDX400, matching Tx and Rx, good condition, new final tubes, \$500 ONO. VK3ZNG, QTHR. Ph. (051) 47 2365.

Yaesu FL110 Linear Amplifier, brand new in carton, with accessories, \$200 ONO. VK3ZNC, QTHR. Ph. (051) 47 2368.

Yaesu FT-301 100W. power supply FP301, and ext. VFO FY301, complete with 10W link for Novice use, excellent cond., with cartons, \$1,100 firm. VK3NRI, QTHR. Ph. (03) 614 5068.

R1V1 Equipment in working condition, Model 15 (new) Model 14 speakers, and TDA, Model 19 c/w stereo CH/FL and downhilt on spare, also Siemens Tape Teletype punches and reports. Belcom Satellite UHF vcr and sundry gear. Reasonable offers accepted. VK3ZN, QTHR. Ph. (2) 76 8547.

Ken KP202 handheld 2m FM Tcvr, ch. 2, 4, 5, 6, simplex 40 and 50, exc. cond., c/w charger, nicads, helical and 1/4 wave whip plus FL259 adapter, all only \$175. Mark. Ph. (051) 528 9962 Bus.

Yaesu FT101B/FP300 (black front panel), plastic cover, built-in ATU, exc. cond., working order, some mods., handbook, \$300. VK2ABQ, QTHR. Ph. (02) 451 1313.

2 yokeate suit 40x180 and 40x250 Sura. BK800, \$20 each. Comm. Rx. Drake SP84 (160-10m) 0.15-30 MHz, NB fitted all 23x25 vtr. good work, order, set, yate 12V DC plus 240V mains, \$450 ONO. VK3YNE, QTHR.

TS220B Tcvr with digital display (needs small repair), mcb., key alt in orig. cartons, \$650. Alex VK3ZNS 2m FM Tcvr, power supply, mounting bracket, whips, \$280. Selling for financial reasons. Simon VK3ZJX, 322 The Boulevard, City Beach, WA 6015.

Radio Tower, triangular self-supporting 2 section, height 48 ft., 60 ft. with 2 inch tubing, base size 4 ft. triangle, top section (23 ft.) hinges over, maintenance platform at the top, completely rust proofed up, galvanised, fitted w. commercial heavy duty bearing thrust race, rotor and 140 ft. of rotor cable, dismantled & ready for transport, \$450. David Rosenfield VK3ADM, QTHR. Ph. (03) 592 2168 after 5 p.m.

FT211, complete with YG221 digital freq. display, very good condition, \$700. VKK1, QTHR. Ph. (02) 78 4237.

Yaesu FT5560, 160-10m, 500W, PEP, also spare set valves, \$450. Trio 2200 2m FM port. Ch. 1-8, rpters. alt. Ch. 40, 50, 3 simplex, new nicads, \$215. Atlas 215 160-10m inc. mobile cradle, AC PS, fixed xtal exc. cond., dig. readout, 6058. Video cassette recorder JVC VHS syst., 6 months old, \$950. Also \$300 worth cassettes for \$100. All prices ONO, will freight free. VK3BEE, QTHR. Ph. (050) 24 5814.

FRG-7 Rx, switched SSB filter in addition to normal filter, includes \$250. DAIWA 400 408 w. mcb. and com. transmatch type 505W PEP, \$75. Roy VK3XY, QTHR. Ph. (03) 557 1285.

WANTED

Urgently, Model 15 Teleprinter, am willing to pay up to about \$50 for machine in fairly good condition, set to speed 45.45 bauds, teleprinter transformer also needed. T. Robinson L31105, QTHR.

Moore Keyboard, Aercom or similar, with memory. VK3AE, QTHR. Ph. (03) 211 7965 A.H.

Mod Demod Unit and power supply for model 15 teleprinter. VK8BE, QTHR. Ph. (059) 55 4664.

Two 880G Valves and two 524s. Price, etc., to VK4NUY, 14 Cooradilla Street, Jindalee 4074.

Help! Urgently need circuit for PSU/batt. charger type PP6245 (032V, 0-40A, General Dynamics). Also, amplifier type 1925/1926 for Synestron-Donner counter type 1034. "Delicat" valve or translator Rx built, broken or in bits (will consider other 1-30 MHz Rx). Please write VK3ANG, QTHR, will defray all costs.

Radio and Hobbies, May 1939 (Vol. 1, No. 2), August 1940 (Vol. 2, No. 3), November 1940 (Vol. 2, No. 8), Jim Gordon, 6 Greame Ave., Ringwood, Vic. 3134. Ph. (03) 870 1745.

Yaseu FT221R 2m all mode tcwr, good condition, also IC22A, TR7100 or FT 2m mobile, will pay current market price. Details for km conversion of Cybernet CB rig. Jeff VK8GF, QTHR. Ph. (099) 52 2967.

Service Manual for AS223 Ra, made by TCA for Australian Army. Lionel L. Sharp VK4NS, QTHR. Ph. (07) 59 1845.

Icom IC3PE Power Supply to suit Icom 300E and linear, will exchange brand new IC3PE supply which matches IC23S, BIR Jamieson VK3ZXX, QTHR. Ph. (03) 277 9172.

Home for Memorabilia Home free to collector — Kingsley radio Type K/S9 signal booster with 14 and 20 MHz coils, and KF/C3 tunesable 50 to 54 MHz converter, both as advertised AR 1947/48. Roy VK3XY, QTHR. Ph. (03) 557 1265.

Headphones, early Brown's type, adjustable diaphragms. Details to VK2KI, QTHR. Ph. (02) 78 4237. Yaseu FT201 Xcr (not FT200), top price paid, or exchange FT101. Details to VK3DM, QTHR. Ph. (03) 555 9215.

Solid State High-Band Commercial Transceiver, suit conversion to 2m repeater. Two solid state UHF transceivers, suit conversion to 438 MHz for repeater control, good money for good gear. VK2AZD, QTHR. Ph. (059) 62 3715.

Automatic Keyer. Send details and price to VK2AYR, QTHR. Ph. (02) 44 1589 after 18.00h.

WANTED KNOWN

OSI Superboard 2 or CIP users interested in swapping programs and/or information contact Frank VK4AYE on 21.175 at 2330 GMT (Sunday a.m. local time after the VK4 WIA news), or on 14.133 MHz at 0530 GMT.

TRADE MARCHES

High Gain Beams for 40, 20, 15, 10, 6, 2 and 70 cm, also UHF CB and ATV repeaters, OSI frequency counters and kits, Mirage PWR/SWR meters, also 2m amps with preamp. Write ATN Antennas, Box 80, Birchch 3483, for catalogue.

ETO ALPHA high power 1-30 MHz linear power amplifiers in stock now, model 76PAC with 3 Eimac 8874 tubes, manual tuning, heavy duty power supply, \$2,165; model 37AAC, 2 Eimac 8874 tubes, no tune up, and manual tune if required, \$2,395; export versions all feature 10 meters factory installed; Eto Alpha appointed sole Australian importer and distributor; after sales service. James Goodger VK2JO, Australian Sound and Signal Research, GPO Box 5076, Sydney 2001, NSW. Ph. (02) 388 0428, 389 7786; A.H. (02) 38 7758.

A REMINDER

A WIA MEMBERSHIP CERTIFICATE IS OBTAINABLE ONLY FROM YOUR DIVISION.

SILENT KEYS

It is with deep regret that we record the passing of —

Mr. A. C. LORD VK3BIE
Mr. R. G. J. HORNE VK3BLH
Mr. A. J. WARD VK2VH
Mr. W. S. LAHE VK2LY
Mr. K. J. COLLINS VK2ARY
Mr. K. W. HELEY VK5ZKW
Mr. T. WOODFORTH LS0488
Mr. BEN WALLICH ex G8BV
Mr. A. G. MARKS VK3HW
Mr. A. M. MCGREGOR VK4KX

OBITUARY

RONALD HORNE VK3BLH
Ron Horne, of Maybrough, Victoria, suffered a fatal heart attack on 4th December, 1979. He was previously VK3AGR and VK4RR, and was a well known former member of No. 3 Squadron, RAAF. At the time of his demise he was 61 years of age.

From "Bill" Holland VK3XC.

HAROLD ROAST VK3AX
With the passing of VK3AX (AR Oct.) the ranks of real old-timers are thinning. Licensed before the issue of the VK prefix, Harold lived at Frankston as a youngster and was one of 30B's pioneers. This station opened its country relay at 3LK, Lubeck, in 1936 and Harold moved there shortly afterwards becoming Chief Technician — a post he held continuously until his retirement. Those who visited 3LK will recall what showplace it used to be, the station and equipment positively gleaming, with the surrounding gardens and lawns neatly kept, a tribute to Harold's management and a great deal of personal effort. Harold and his XYL, Maudie, were deeply involved in district sporting and community affairs, tennis being a particular favourite sport, at which they both excelled. Harold was an A1 CW op, his male interest being 20m, a band from which he rarely strayed. With his trusty UC348, home brew Tx and 150 ft. near vertical antenna, his patient and methodical approach netted a formidable DXCC tally which I doubt he ever claimed. Harold and Maudie retired to Frankston in 1972, unfortunately illness overtook him in early 1979 and he passed away last July, just a few weeks after the last time I spoke with him. Sadly I reflect to what extent my own links with the past to radio both amateur and professional have now been severed. Deepest sympathy is extended to his wife, Maudie, and son Roger and family.

Chas. Hawker VK3IB.

ANDREW CHARLES LORD VK3BE
It is with deep regret we record the passing of Andrew Charles Lord (Andy) VK3BE after a long illness. Andy was first licensed on the 26th October, 1938, and was a very active ham on most bands. He served in the AIF as Lieutenant during World War 2. His occupation was firstly with the Ballarat City Council as a rates collector officer and later resigned this position to take his final position as Shire Secretary of the Buninyung Shire. Ill-health forced his retirement earlier than anticipated. Andy will be missed not only by amateurs but people in many walks of life. Deepest sympathy is extended to his sister, Winifred, and brother-in-law, Bert, and other members of the family.

Stanley E. Widgery VK3BE.

SAM LAHE

VK2LY

The death occurred on 20.12.79 of Sam Lahe VK2LY after a short illness. Until taken ill, Sam was an employee of Tamworth Base Hospital, starting work there as a tradesman in early 1942. Soon after he joined the RAAF as a Wireless Air Gunner and served in Australia and overseas. On demobilisation he returned to his former employment, finally becoming Hospital Engineer and later Regional Engineer. To his wife Joan, son Alan and daughter Susan, also his mother, I am sure all amateurs extend their heartfelt sympathy in their great loss.

G. H. Simpson VK2WY

TOM SCOTT

VK2NPK

It is with deep regret that I record the passing to Tom Scott VK2NPK on the 28th November 1979. Since serving with the Signal Division in New Guinea in WW II Tom maintained an interest in electronics. At the age of 58 he gained his Novice licence. He was not only an active operator but was a person who was committed to helping others obtain their Amateur licences. He was a tireless worker for YRS Education Service personally packing and despatching over a thousand Novice Study Kits. He was an outstanding example of a person who put back into Amateur Radio something in return for the fulfillment he gained from it. His efforts and his warm and generous personality will be sadly missed by all those associated with him.

Dave Wilson VK2ZCA/NMW

ARNOLD GILBERT MARKS VK3NVQ

It is with deep regret that I inform you of the passing of a great friend in Gil Marks who passed away on December 24th with microphone in hand.

Gil spent all his life in radio and TV servicing. He was a radar operator in the RAAF during World War 2. He operated a business for many years in Portland and shifted to Geelong where he formed the Geelong Radio Club. He was extremely popular with all he met and highly respected by all for his electronics knowledge and friendly bearing.

He will be sadly missed and I wish to convey to his wife, daughter and son on behalf of all his friends our deepest sympathy. The last entry in his log book was: "Jack said he has not received his results as yet." It received the result on Dec. 27th — VK3NVQ.

John E. C. (Jack) Heaner

ADVERTISERS' INDEX

AMATEUR RADIO ACTION	36
BAIL ELECTRONICS	13
CHIRNSIDE ELECTRONICS	10
GW ELECTRONICS	15, 19
DICK SMITH ELECTRONICS	2
GFS ELECTRONIC IMPORTS	43
IMARK	26
PHILIPS	18
SIOBAND ELECTRONIC IMPORTS	37
SCALAR INDUSTRIES	7
TRIO-KENWOOD	44
VICOM	21, 22, 23
WIA NSW DIVISION	32
WILLIAM WILLIS & CO. PTY. LTD.	32

NOW COMBINE AMATEUR RADIO AND COMPUTERS WITH A SOUTH WEST TECHNICAL PRODUCTS COMPUTER FROM GFS

We have a system to suit you, from hobby level all the way up to a business level system with 2.4 Mega-Byte of on-line disk memory. Also available is a comprehensive range of software packages including many that are oriented to amateur radio. Write or call us for full details of SWTPC's products.



SWTPC



**ATLAS
RADIO INC.**



GFS FOR RECEIVERS

STANDARD C-6500.....\$359.

HF Wadley Loop Communications Receiver.

Manufactured by Marantz Japan the C-6500 is a state-of-the-art HF receiver covering 0.5-30 MHz in 20 x 1 MHz band segments. Its sensitivity is extremely high at 6.5uV and selectivity is 4 KHz on SSB and 7 KHz on AM.



J.I.L. SX-100 16 CHANNELS VHF/UHF SCANNING RECEIVER.....Price \$407.

Still the best value in Programmable Scanners, the SX-100 covers the 6.2 and 70 cms Amateur Bands plus over 32,000 other Frequencies including Channel 0 and Channel 3A TV Sound.

Amateurs can use the SX-100 to monitor band conditions using beacons etc. Firemen can keep informed by listening to firebrigade frequencies. CBers can monitor UHF CB Channels. Professionals can monitor VHF marine and Emergency frequencies. Servicemen can use the SX-100 to check virtually any commercial two-way frequency with its 32,000 channel coverage.

- Covers 30-54, 140-180, 410-514 MHz.
- 240V AC and 12V DC operated.
- 9KHz Channel Spacing.
- Frequencies are programmed using built-in keyboard.
- Built-in Digital Clock & Date.

SEE REVIEW ETV NOV. '79

SKY ACE R-517.....\$104.

The monitoring of aircraft communications has long been a requirement for emergency service organizations, flying schools and clubs, aircraft operators, aviators themselves as well as a band of communications enthusiasts. GFS has a range of airband receivers that should suit all these requirements.



Designed for the enthusiast, the R-517 is a Palm Sized Receiver which features Full 110-144 MHz Tuning plus the 3 Crystal Locked Channels.

- Active built-in AGC
- Built-in Telescopic Antenna.
- Excellent Selectivity.
- VFO main tuning with FINE, central and 3 crystal channels.

NEW! COMNI R-1010 AIRBAND RECEIVER. The R-1010 is a Professional Receiver that uses frequency synthesis thus giving the following outstanding performance.....\$529.

- Frequency range 138-138.075 MHz.
- Channel Spacing 25 KHz.
- Digital Frequency Readout.
- 12 VDC or 240VAC operated.
- Cx-Axial Channel Selector.
- Speech and IF Noise Blanker.
- Weight 3 Kg. Size 10 cms x 5.6 cms x 25 cms.



SCANNER BASE ANTENNAS

- Scan-X 85-520 MHz. 3dB Gain.....\$35.00
- CXD-1 85-480 MHz. Heavy duty.....\$89.00

Write for a comprehensive price list and Catalogue of the complete GFS Product Range. Trade Enquiries Welcome.

TRANSCIVER OF THE DECADE

**NEW
215XLE
LIMITED
EDITION**



■ 80-100 METRE.
■ 250 WATTS.
■ SEMIBREAK-IN CW.
■ BUILT-IN SIDETONE.
Includes all the outstanding features of 215X plus now 250 Watts Input, new R.I.T. control and update frontpanel design.



- 215XLE Transceiver \$795.00 ■ 220CS Console/P.S. \$170.00 ■ 210X Transceiver \$795.00 ■ 200PS Power Supply \$130.00 ■ DD6-C Digital Readout/Counter \$245.00 ■ VK-5M Vox \$79.00 ■ MT-1 Matching Transformer \$44.00 ■ DMK Plug Mobile Mount \$62.00 ■ 16cb Crystal control Adapter \$79.00 ■ DCC Power Cable Kit \$14.00 ■ MKK Mobile Bracket Kit \$14.00 ■ DL-300 300W Dummy Load \$32.00



NEW PRODUCTS FROM MFJ

Now a very wide range of Antenna Tuners

- MFJ-904 30W Ant. coupler/Dual Meter type SWR/Power Meter Co-Ax switch for Bal and Un Bal Line (inc. Balun) \$419.00
- MFJ-902 30W Ant. coupler/SWR/Power Meter for Bal and Un Bal Line (inc. Balun) \$279.00
- MFJ-902 1.5KW Ant. coupler/SWR/Power Meter & Pos. Co-Ax SW for Bal and Un Bal Line (inc. Balun) \$220.00
- MFJ-901 1.5KW Ant. coupler/Pos Co-Ax SW for Bal and Un Bal Line (inc. Balun) \$199.00
- MFJ-903 30W Ant. coupler/SWR/Power Meter/200W Dummy Load/Co-Ax SW for Bal and Un Bal Line (inc. Balun) \$169.00
- MFJ-9418 30W Ant. coupler/SWR/Power Meter Co-Ax SW for Bal and Un Bal Line (inc. Balun) \$145.00
- MFJ-943 30W Ant. coupler for Bal and Un Bal Line (inc. Balun) \$115.00
- MFJ-901 30W Ant. coupler for Bal and Un Bal Line (inc. Balun) \$97.00
- MFJ-900 200W Ant. coupler for Unbal Line (Un Balun) \$85.00

Tunable Active SSB/CW Filters

- MFJ-732 TUNABLE ACTIVE SSB/SW FILTER inc. Peak/Notch Noise Limiters, and Two Variable Frequency Filters \$145.00
- MFJ-731 Tunable Active SSB/CW Filter \$116.00

Electronic Keys

- MFJ-401 the GRANMASTER MEMORY KEYS stores 2 x 50 character messages 8-50 WPM \$145.00
- MFJ-402 Econo Keyer, built-in Paddle, Weight and Speed control. 8-50 WPM solid state keyer \$63.00

Other Accessories

- LSP-2900S ■ Super Logarithmic speech processor 30dB dynamic range and 3 Active Filters. \$97.00
- MFJ-292 Antenna Noise meter wide range 0-250 Ohms. 150 pf. Cx. 1-100MHz. \$83.00
- MFJ-1838 BX 10-30MHz Ferrite. 25dB gain \$63.00

— ANNOUNCEMENT —
TEN METRE OPERATORS.
NOW ENJOY FM OPERATION
WITH THE
COMTRONIX FM-80.

Enjoy the thrill of FM operation that has been so popular amongst 2 Metre operators for years, but with the advantage of being able to work OVERSEAS DX (10 metre FM is very popular in the US with over 70 repeaters already operating). With the FM-80 you have the choice of 80, 100KHz spaced channels, 29.81-29.7 (range can easily be changed to 28.01-28.00 MHz), power output is 10-15 Watts, deviation is +3KHz, receiver sensitivity is 0.5uV for 20dB quieting.

Don't miss out on experiencing this exciting new form of communication. Call or write to us for your FM-80 now.

SPECIAL INTRODUCTORY PRICE \$289.

NEW 1980 CALLBOOKS EXPECTED SOON
US Callbook, over 395,000 listings.....\$19.95
Foreign Callbook, 300,000 listings.....\$18.95

INSTALL YOUR OWN TOWER AND SAVE \$\$\$'s


GFS now have a range of easy to install Self Supporting Towers

- G201 6 m Single Section Tower.....\$79
- G202 6 m Double Section Tower.....\$99
- G203 6 m Heavy Duty Base for G201/2.....\$145
- G204 6 m Heavy Duty Base for G201/2.....\$175
- G205 6 m x 5 cm Tubular Mast for G201/2.....\$65

GREAT CIRCLE

MAP
THIS FINE MAP, CENTRED MAP, IS STILL AVAILABLE FROM GFS

PRICE \$1.00 + 75c P&P



TET SWISS QUADS



This antenna is a PHASED QUAD and well known as a HB9CV QUAD. Its concept is to drive the Reflector and Director at the same time with phase differences to obtain more gain and better front-to-back ratio than the conventional quads.

- 50-52 2m x 2 Stacked 15dB Gain 500
- 50-54 2m x 4 x Stacked 18dB Gain 510
- 50-51 5m x Standard 12dB Gain 510
- 50-52 5m x Standard 12dB Gain 515
- 50-53 10m x Standard 12dB Gain 516
- 50-54 20m x Loaded 16dB Gain 516

ATN ANTENNAS

Write to us for a catalogue and price list on ATN's large range of VHF/UHF & HF antennas.

DSI COUNTERS

GFS are Melbourne agents for the comprehensive range of DSI FREQUENCY COUNTERS. Drop us a line or just give us a call for your DSI counter.

SPECIAL! METAL DETECTORS

Limited Stocks Only, available at the special low price of \$38 + \$3 P&P

G.F.S. ELECTRONIC IMPORTS

15 McKEON ROAD, MITCHAM, 3132. (03) 873 3939



SAVE \$65* — with every SM-220 Monitor, purchased during February, March and April from your authorised Kenwood distributor, you will receive absolutely **FREE** a BS-5 or BS-8 Adaptor.

This adaptor will allow your Kenwood H.F. Transceiver to display signals on each amateur band as selected by the transceiver.

*This offer ends on 31st April, 1980.

SM-220 Station Monitor

Provides efficient station operation and also serves as a high-sensitivity, wide frequency-range oscilloscope for various adjustments and experiments.

Recommended
Retail Price
\$375.



TS-520S 1.8 to 29.7 MHz SSB TRANSCEIVER


Amateurs throughout the world acclaim this rig which was specially engineered for the serious enthusiast.

Recommended
Retail Price
\$650.

TS-120S 3.5 to 29.7 MHz SSB TRANSCEIVER

Ideal front panel layout gives simple operation for all users — novice or advanced, fixed station or mobile. A marvellous combination of high performance and low cost.

Recommended
Retail Price
\$735.



TRIO-KENWOOD (AUSTRALIA) PTY. LTD.

31 Whiting Street, Artarmon, Sydney, N.S.W. 2064. Telephone (02) 438-1277

Authorised Distributors:

N.S.W.: SIDE BAND ELECTRONICS SALES (02) 438-4191 — EMTRONICS (02) 398-6378 •
VIC.: VICOM IMPORTS PTY LTD (03) 699-6700 • **QLD.:** MITCHELL RADIO CO (07) 57-6830 •
S.A. & N.T.: INTERNATIONAL COMMUNICATIONS SYSTEMS PTY LTD (08) 47-3688 •
W.A.: WILLIS ELECTRONICS (09) 321-7609 • **TAS.:** ADVANCE ELECTRONICS (003) 31-5688 •
PLUS MANY OTHER REGIONAL OUTLETS THROUGHOUT AUSTRALIA

Call into
your nearest
authorised
distributor
and ask to see
these and other
high performance
Kenwood units